

# Equipment List, Mechanical

Applicable for C702, C702a & C702c

## Contents

<b>1</b>	<b>General .....</b>	<b>2</b>
<b>2</b>	<b>Column Definitions.....</b>	<b>2</b>
<b>3</b>	<b>Repair Equipment, Mechanical .....</b>	<b>3</b>
3.1	Sony Ericsson Provided Repair Equipment.....	3
3.2	Picture of equipments orderable from Sony Ericsson.....	4
3.3	Equipment Provided by Other Suppliers.....	5
<b>4</b>	<b>Revision History .....</b>	<b>8</b>

## 1 General

This document describes the minimum required equipments for the Mechanical Repair Process of the C702, C702a, C702c mobile phones.

Equipment listed without a part number is not orderable from Sony Ericsson and must be bought locally.

## 2 Column Definitions

The matrices in the end of the equipment tables describe where the actual equipment is needed (marked with an X) or may be needed/optional (marked with a Z).

Flash upgrade:      Equipment for downloading software to the unit, both signalling and test-program.

Manual test:        Equipment necessary to perform a manual test.

Repair:              Equipment necessary for replacing components.

The columns that assist in specifying and/or clarifying the equipment needed are considered description type columns.

- Description      The name of the equipment.
- Part Number    The Sony Ericsson part number to use when ordering from Sony Ericsson.
- Comments      Additional information that helps to specify or clarify the equipment.

### 3 Repair Equipment, Mechanical

Some of the required equipment will be provided by Sony Ericsson and some equipment has to be sourced locally. This chapter will separate these equipments.

#### 3.1 Sony Ericsson Provided Repair Equipment

Description	Part Number	Comments	Upgrade	Flash	Manual Test	Repair
USB cable DCU-65	RPM 13112R1	Used for SonyEricsson programming interface cable - SEPI	X			
Torque Screwdriver *	NTZ 112 459	Torque set to 18 Ncm +/- 0,2 Ncm Torque set to 8 Ncm +/- 0,2 Ncm				X
Bits/Torx/T6	NTZ 112 288	Spare part to screwdriver				X
JCIS No. 0 Screw Bit	NTZ1121052	Spare part to screwdriver				X
Front opening tool	NTZ 112 302/2					X
Flex film assembly tool	NTZ 112 521	Tweezers for flexfilms				X
Battery Eliminator	NTZ 112 533	Dummy battery	Z			
MEGA Pixel Camera Tool	1206-7115	Camera removal tool				X
256MB Memory Stick Micro(M2)	KDR 109 171/256	This item is needed to test the applicable product's memory slot.			X	
Plectrum Tool	NTZ 112 590	Guitar Pick				X

\*Any screwdriver that fulfils torque and bit demand can be used.

The matrix describes where the actual equipment is needed, marked with an X, or may be needed/option, marked with a Z.

### 3.2 Picture of equipments orderable from Sony Ericsson

Pictures of tools that is orderable from Sony Ericsson.

			
KDR 109 171/256	1206-7115	RPM 13112R1	NTZ 112 459
			
NTZ 112 288	NTZ 112 1052	NTZ 112 302/2	NTZ 112 521
			
NTZ 112 533	NTZ 112 590		

### 3.3 Equipment Provided by Other Suppliers

This is the list of equipments provided by other suppliers than Sony Ericsson

<b>Description</b>	<b>Comments</b>	<b>Flash Upgrade</b>	<b>Manual Test</b>	<b>Repair</b>
Battery	BKB 193 192/1	X	X	
-Battery Charger	Standard SonyEricsson charger applicable for C702a, C702c		X	
Computer	Minimum Pentium III 500 Mhz 128 Mb RAM or better. At least 2USB ports	X		
Tweezers	ESD-safe			X
Dentist hook	To be used when removing the adhesives.			X
Nylon Pointer	To be used when loosing hooks.			X
Isopropyl Alcohol	To be used when removing glue.			X
Cotton Gloves	ESD-safe			X

Description	Comments	Flash Upgrade	Manual Test	Repair
Zebra Printer	<p><b>Current Model Options:</b></p> <ul style="list-style-type: none"> <li>• <b>110XIIIPlus</b> or <b>Z4Mplus</b></li> </ul> <p>These models use a DB9 Male-DB9 Female Null Modem</p> <p><b>Discontinued Model Options:</b>  <b>NOTE – The following models may also be used, but Zebra has discontinued selling them.</b></p> <ul style="list-style-type: none"> <li>• 90xi Series</li> <li>• Z4M</li> <li>• Z4000 deluxe</li> </ul> <p>These models use a DB25 Male-DB9 Female Null Modem</p>			Z
Null Modem Cable	<p>This cable connects the Zebra printer to the computer. Two companies that carry this type of cable are CDW (www.cdw.com) and QVS (www.qvs.com).  Part numbers for the <b>DB9 Male-DB9 Female version:</b>  <b>CDW – 361875</b> (6 Feet Long)</p> <p>Part numbers for the <b>DB25 Male-DB9 Female version:</b>  <b>CDW – 375939</b> (6 Feet Long)  <b>QVS – CC314-06</b> (6 Feet Long)  <b>QVS – CC314-10</b> (10 Feet Long)</p>			Z
Hot Air Flow Repair Station, Medium.	To be used when removing phone label (if needed)			Z
Bluetooth-device	To be used to make connection between the phone and the device		X	
Hands free equipment.	To be used to verify the system connector. Applicable for C702		X	
Operator SIM-card	To be used when making a landline call.		X	
Barcode Scanner	The device must be able to decode code128 and 128C			Z

Description	Comments	Flash Upgrade	Manual Test	Repair
Ionized Air Gun or blower	neutralizes the static, therefore allowing dust and fine particles to be easily blown off.			Z
Power supply	NOTE: Only necessary if using the Battery Eliminator.	Z		
Power cables Red & Black	Minimum cross sectional area of conductor: 1.2 mm <sup>2</sup> Maximum length: 1.5 m	Z		
ESD wristband				Z
ESD Gloves				Z

\*Any screwdriver that fulfils torque and bit demand can be used.

The matrix describes where the actual equipment is needed, marked with an X, or may be needed/option, marked with a Z

## 4 Revision History

Rev.	Date	Changes / Comments
1	2008-05-22	Initial release