

User's Manual

i T414



Contents

Chapter one: Basic knowledge.....	3
1.1 BRIEF INTRODUCTION	3
1.2 SAFETY PRECAUTIONS.....	3
1.3 GENERAL NOTES	3
1.4 NOTES TO THE USE OF THE MOBILE PHONE	3
1.5 NOTES TO THE USE OF THE BATTERY	4
1.6 NOTES TO THE USE OF THE CHARGER.....	5
1.7 CLEANING AND MAINTENANCE	5
1.8 GENERAL NOTES	5
Chapter two: before use.....	6
2.1 SIM CARD	6
2.1.1 HOW TO INSERT AND REMOVE THE SIM CARD.....	6
2.2 BATTERY	6
2.2.1 HOW TO REMOVE AND INSTALL THE BATTERY	7
2.2.2 HOW TO CHARGE THE BATTERY	7
2.3 SWITCH-ON	7
Chapter three: Basic descriptions.....	8
3.1 ABOUT THE KEYPAD.....	8
3.1.1 BASIC KEYS	8
3.2 CALL FUNCTIONS.....	8
3.2.1 HOW TO MAKE A CALL	8
3.2.2 HOW TO PICK UP A CALL	9
3.2.3 HOW TO REJECT AN INCOMING CALL	9
3.3 HOW TO USE THE DATA CABLE	9
4.1 PHONEBOOK.....	10
4.2 MESSAGES	10
4.2.1 SMS	10
4.2.2 MMS.....	12
4.2.3 VOICE MAIL SERVER	13
4.2.4 BROADCAST MESSAGE	13
4.3 CALL LOG	13
4.3.1 CALL HISTORY.....	13
4.3.2 GENERAL CALL SETTINGS	14
4.4 MULTIMEDIA.....	15
4.4.1 FILE MANAGER	15
4.4.2 IMAGE VIEWER	15
4.4.3 VIDEO PLAYER	15
4.4.4 FM RADIO	15
4.4.5 VIDEO RECORDER	15
4.5 CAMERA	16
4.6 AUDIO PLAYER	16
4.7 ORGANIZER	16
4.7.1 CALENDAR.....	16

4.7.2 TASKS	16
4.7.3 ALARM.....	17
4.7.4 WORLD CLOCK.....	17
4.7.5 CALCULATOR	17
4.7.6 UNIT CONVERTER.....	17
4.7.7 CURRENCY CONVERTER	17
4.7.8 EBOOK READER	17
4.7.9 STOPWATCH	17
4.8 FUN & GAMES	17
4.9 SETTINGS	18
4.9.1 USER PROFILES.....	18
4.9.1.1 GENERAL	18
4.9.1.2 MEETING	18
4.9.1.3 OUTDOOR.....	18
4.9.1.4 INDOOR	18
4.9.1.5 HEADSET	18
4.9.2 DUAL SIM SETTINGS	18
4.9.3 PEN CALIBRATION.....	18
4.9.4 PHONE SETTINGS.....	18
4.9.5 NETWORK SETUP	19
4.9.6 SECURITY SETTINGS.....	19
4.9.7 CONNECTIVITY	19
4.9.8 SHORTCUTS	19
4.9.9 RESTORE FACTORY SETTINGS	19
4.10 SERVICES	19
4.11 LEMON TWIST	20
4.12 OPERA	20
4.13 MENU DURING THE CALL	20
Chapter five: FAQ	21
1.1 WHY DOES THE PHONE PROMPT "PLEASE INSERT SIM CARD"?	21
1.2 HOW TO GET AND USE THE PIN, PIN2, PUK, PUK2 CODES AND RESTRICTION PASSWORD?	21
1.3 FREQUENT OCCURRENCE OF NETWORK FAILURE.....	21
1.4 YOUR VOICE CAN NOT BE HEARD AT THE OTHER END.....	21
1.5 CHARGING FAILURE OR CHARGING WITHOUT ANY INDICATION	21
1.6 INTERMITTENT SIGNALS	21
1.7 UNABLE TO CALL	21
1.8 SHORT STANDBY TIME.....	21

Chapter one: Basic knowledge

1.1 Brief introduction

Thank you for selecting iT414 color-screen mobile phones.

Before initial installation and use, please do peruse all the documents related to this product, which will facilitate your use of the phone and help you to enjoy its comprehensive functionality and easy operation.

iT414 color-screen mobile phone is specifically designed for GSM/GPRS network environment. Besides basic function of calling, it provides a variety of practical functions for the convenience of your work and life, including dual SIM cards, camera, English input, and phone book in a name-card-holder style, music ringtones, clock/alarm clock, and calculator, games and Mp3 player. Moreover, iT414 adopts a personalized human-computer interface. With perfect design and function, it can satisfy your various demands.

iT414 color-screen mobile phone complies with GSM/GPRS technical specifications and has acquired the certificates issued by authoritative institutes at home and abroad.

The company reserves the right to modify the contents of this manual without any prior notification.

1.2 Safety precautions

➢ If your mobile phone is lost or stolen, please inform the Telecom departments or agencies immediately in order to ban the use of this mobile phone and SIM card. This will protect you from any economic losses due to the misuse of your phone by others.

➢ When you contact any Telecom department or agency, you are required to provide the IMEI number on your mobile phone, which is printed on the label at the back of the phone. You can easily see it after removing the battery. Please carefully remember this number for future use.

➢ To avoid any misuse of your mobile phone by others, please take preventative measures as follow:

- Set PIN number for SIM card and make timely modification before others know the number.
- Please don't put your phone in any visible place before you leave the car. You'd better take it with yourself or lock in a suitcase
- Set call restriction.

1.3 General notes

➢ The mobile phone can merely use the battery and charger specified by the phone manufacturer. The use of any other battery or charger might lead to battery leakage, overheating, burst and burning.

➢ Please don't strike, shake and throw the mobile phone fiercely so as to prevent any malfunction and burning of the phone.

➢ Please don't put battery, mobile phone and charger into a microwave oven or high-pressure equipment. Otherwise it might lead to circuit damage, burning and other accidents.

➢ Please don't use the mobile phone near from the places with the flammable and explosive gas so as to prevent any malfunction of the phone or fire accident.

➢ Please don't put the mobile phone in the places with high temperature, high humidity or lots of dust so as to prevent any malfunction of the phone.

➢ Please put the mobile phone in places out of the reach of children in case that it might be mistakenly regarded as toys and therefore causes injuries.

➢ Please don't put the mobile phone on uneven or unstable surfaces so as to prevent any malfunction or damage of the phone due to falling.

1.4 Notes to the use of the mobile phone

➢ Please switch off the mobile phone in the plane, hospital and places where the use of mobile phone is prohibited as it impacts the normal operations of the electronic equipment and medical apparatus. You should comply with relevant regulations on these occasions. The mobile phone features a function of automatic power-on; therefore please

check your alarm setting to make sure that the phone will not automatically turn on during flight.

➤ Please don't use the mobile phone near from the weak-signal or high-precision electronic equipment because the interference of radio wave might lead to disoperation and other problems of the electronic equipment. You should pay special attention to the following equipments: hearing aids, pacemakers and other medical electronic equipments, fire detectors, automatic doors and other automatically controlled devices. Please consult the equipment manufacturer or local seller to know the phone's impact on pacemakers and other medical equipments.

➤ Please don't impose great forces on the LCD screen or use it to knock against others. Otherwise it might lead to the damage of the LCD screen and the leakage of the LCD liquid. There is a risk of blindness if the liquid enters eyes. In this case, use clean water to wash eyes (Do NOT rubs the eyes) and go to hospital immediately.

➤ Don't disassemble or rebuild the mobile phone so as to prevent any damage, electrical leakage and circuit failure of the phone.

➤ In very few cases, there might be a negative impact by mobile phone on the electronic devices of some vehicles. In this context, please don't use the mobile phone so as to avoid any risk of driving safety.

➤ Please don't use the needle, pencil tip and other sharp-edged articles to press the buttons so as to prevent any damage or misoperation of the phone.

➤ Please don't use the mobile phone if its antenna is damaged. Otherwise it might be harmful to human body.

➤ Keep the mobile phone away from magnetic articles such as magnetic card. Radiation wave from the phone might erase the information stored in the floppy disk, bank card and credit card.

➤ Please keep small metal articles (e.g. thumb pins) away from the phone. When the phone works, the speaker becomes magnetic and attracts these small metal articles, which might consequently hurt human body or damage the phone.

➤ Protect the mobile phone from moisture. The intrusion of water or other liquids into the phone will lead to overheating, current leakage and malfunction of the phone.

1.5 Notes to the use of the battery

➤ Please don't throw the battery into fire so as to prevent any burning and burst of the battery.

➤ Don't forcibly press the battery into the phone during installation. Otherwise it might lead to liquid leakage, overheating, burst and burning of the battery.

➤ Please don't use a wire or pin to short-circuit the battery or put the battery together with the necklace and other metals. Otherwise it might lead to leakage, overheating, burst and burning of the battery.

➤ Please don't weld any end of the battery so as to prevent any leakage, overheating, burst and burning of the battery.

➤ There is a risk of blindness if the liquid in the battery enters eyes. In this case, do NOT rub the eyes. Use clean water to wash eyes and go to hospital immediately.

➤ Please don't disassemble or rebuild the battery so as to prevent any leakage, overheating, burst and burning of the battery.

➤ Please don't use or put the battery near from fire, heater or the places with high temperature so as to prevent any leakage, overheating, burst and burning of the battery.

➤ If there is any abnormality like temperature increase, color change or deformation occurring to the battery during the process of use, charging or storage, please stop using and replace the battery.

➤ If the liquid in the battery contacts the skin or clothes, it might lead to skin burn. In this case, use clean water to wash it and go to hospital immediately if necessary

➤ If the battery leaks or releases a strange smells, please take it away from the open flame so as to prevent any burning or burst.

➤ Please protect the battery from moisture so as to prevent any overheating, fuming or corrosion of the battery.

➤ Please don't use or put the battery under direct sunlight or near from the vehicles with high temperature. Otherwise it might lead to leakage and overheating, reduced performance and short lifetime of the battery.

➤ Please don't charge for more than 24 consecutive hours.

1.6 Notes to the use of the charger

➤ Please use 220V AC for charging. The use of other voltages will lead to electrical leakage, burning and damage of the phone as well as the charger.

➤ Short circuit of the charger is strictly banned to prevent electric shock, fuming and damage of the charger.

➤ Please don't use the charger with damaged power line so as to prevent any burning or electric shock.

➤ Please clean the dust on AC socket on a timely basis.

➤ Please don't put a container with water near from the charger so as to prevent any overheating, electrical leakage and malfunction of the charger due to contact of water.

➤ If the charger contacts water or other liquids, pull out the power plug from the AC socket to prevent overheating, burning, electric shock and malfunction of the charger.

➤ Please don't disassemble or rebuild the charger so as to prevent any hurt to the human body, electric shock, burning and damage of the charger.

➤ Please don't use the charger in the places with high humidity such as a bathroom so as to prevent electric shock, burning and damage of the charger.

➤ Please don't contact the charger, power line and AC socket with wet hands so as to prevent electric shock.

➤ Please don't put heavy loads on the power line or rebuild the line so as to prevent electric shock and fire.

➤ Please pull out the power plug from the AC socket before cleaning and maintenance

➤ In order to avoid electric shock and fire, hold the charger instead of the power line when you try to pull out the plug.

1.7 Cleaning and maintenance

➤ The mobile phone, battery and charger are not waterproof. Please don't use them in the places with high humidity such as a bathroom. They should also be protected from rain.

➤ Use soft and dry cloth to clean the mobile phone, battery and charger.

➤ Please don't use ethanol, diluents or benzene to clean the mobile phone.

➤ The dirty socket might lead to poor contact and power failure, making it unable to conduct charging. Please clean it periodically.

1.8 General notes

Mobile Phone:

➤ Please use the phone in an environment with a temperature of 5°C~40°C and a humidity of 35%~85%.

➤ Please use the phone in the places most possibly far from the ordinary phone, television, radio and automated office equipment, in order to avoid any interference between the mobile phone and other equipment.

Battery:

➤ Please put the battery in cool and shady places without direct sunlight.

➤ The battery has a limited lifetime. Its working hours will gradually shorten after a period of frequent charging. If the charging process proves to be ineffective after many times' practice, it means the battery has been used up and should be replaced with a new battery of the specified type.

➤ Don't mix the worn-out battery with ordinary domestic garbage. Please follow the relevant instructions and throw it into specific garbage box for the battery.

Charger:

➤ Please don't conduct charging in the following places: places under direct sunlight; places with a temperature of less than 5°C or higher than 40°C; places with high humidity, lots of dust or great vibrations (which might lead to malfunction); places near from the television, radio and other electrical appliances (which might affect image and sound effect).

Chapter two: before use

2.1 SIM card

Before use, you must insert valid SIM card into the mobile phone. SIM card is the key for you to access the digital GSM network

All information concerning network connection and initialization of the call records is stored in the metal flake of the SIM card. In the same card, there are other data including the names, phone numbers and short messages received and saved in your phone book. SIM card can be taken out and inserted into any GSM mobile phone for use (it will be automatically read by the new phone).

In order to prevent the loss of information, you should avoid touching the metal panel and keep SIM card away from electric and magnetic fields. Once the SIM card is damaged, you will have no access to the GSM network.

* Note: Do switch off the phone before you take out the SIM card. It is strictly banned to take out the SIM card when it is still connected to the external power supply; otherwise the SIM card may be damaged.

2.1.1 How to insert and remove the SIM card

➤ SIM card is usually embedded in a bigger card. Care must be taken to separate it from the bigger card before its insertion into the phone.

➤ Switch off the phone, remove the battery and cut off the external power supply.


➤ Insert the SIM card into the SIM card holder.

➤ Before you take out SIM card, switch off the phone first and then remove the battery. After that, you can open the holder and remove the card, as the following picture shows:



Mounting the T-Flash Card

Insert the T-Flash card, with the gold contacts face down, and into the card slot. Align the card to the arrow sign as the following picture shows:



2.2 Battery

The battery is initially charged with 50% of its full capacity, which can be put into use right after you unwrapped the package. The charging duration for new battery should be at least 14 hours. It should be used up (without any power to start the phone) before the first time of full charging. Repeat this process again and again. After three times of full charging, the battery may gradually reach an optimal state of use.

2.2.1 How to remove and install the battery

➤ **To remove the battery:** ① Push the back cover side wards; ② Lift the battery upwards and remove it.

➤ **To install the battery:** ① Insert the battery into battery holder; ② Push the back cover side wards till it's securely engaged.

2.2.2 How to charge the battery

➤ Connect the charger to the power supply.

➤ Connect the plug of the charger to the side of the mobile phone. (Note: The side with a sign of arrow should face upwards.)

➤ After that, there will be a battery indication symbol flashing repeatedly at the top right corner of the phone screen. If the phone is switched off during charging, on the screen there will also be an indication symbol, which means the phone is under charging. If the phone is overused in the case of low battery, the indication symbol might take a while to turn up on the screen after the charging process starts.

➤ When the battery indication symbol at the top right corner of the screen turns full without any further flashing, it means the charging process, which generally takes 3~4 hours, is finished. It is quite normal that during charging, the battery, mobile phone and charger will get hot.

➤ After charging, cut off the AC power supply as well as the connection between the mobile phone and the charger.

***Note:**

- During charging, the phone must be put in the places with good ventilation at a temperature of +5℃~+40℃ and use the charger specified by the phone manufacturer. The use of any unauthorized charger might lead to danger and violation of the authorization and warranty clauses.

- When the phone automatically turns off or displays "Low Battery", it should be charged on a timely basis. If the battery is not used up before charging, the phone will automatically shorten the charging duration.

- The standby time and call time provided by phone manufacturer are based on ideal conditions. In practical use, standby hours of the battery might change according to different network conditions, working environments and usage manners.

- Before charging, please first confirm the battery has been properly installed. During charging, the battery cannot be taken out.

- After charging, please disconnect the charger from the phone and AC power supply.

- If you have not disconnected the charger from the phone or AC power supply, after a quite long period (about 5~8 hours), some of the electricity in the battery will be consumed and the charging process will start again. We advise you to avoid this operation so as to prevent any negative impact over the performance and lifetime of the battery.

2.3 Switch-on

➤ Long press the **Hang-up Key** to switch on the phone. Long press the same key again to switch off the phone.

➤ If you switch on the phone without inserting the SIM card, or with the SIM card is inserted into the position for the secondary card, the phone will prompt you to insert the SIM card. After the SIM card is inserted, the phone will automatically check whether this SIM card is available.

➤ Then the following prompts will turn up on the screen in sequence:

- Input PIN1 (if you have set the SIM card password) (Please refer to 4.9.6 "Security Settings" for details).

- Input the phone password (if you have set phone unlock password) (Please refer to

4.9.6 "Security Settings" for details).

➤ After SIM card is successfully decoded, the phone will automatically search for the useable network (the screen displays the information of network search). Once the network connection is established, the name of the network supplier will show up on the center screen, which indicates the phone has been in a standby mode for normal use.

* Note: If the screen displays "EMERGENCY", it means you are already out of network coverage (service scope), but you can still make emergency calls so long as the signal strength is adequate.

Chapter three: Basic descriptions

3.1 About the keypad

3.1.1 Basic keys



➤ **Navigation Key:** view menu options or setting up and down when moving around

➤ **OK Key:** select the menu after the confirmation button

➤ **SIM Card 1(2) Dialing Key:** to dial telephone numbers or pick up incoming calls

➤ **Hang up Key:** to end calls or reject incoming calls; long press this key to switch on/off the phone. Under other circumstances, a press of this key usually leads back to the home screen.

3.2 Call functions

When the logo of the network service provider turns up on the screen, you can make or receive phone calls. The signal columns on the top left of the screen indicates the strength of the signal. Barriers exert considerable adverse effect on the call quality. Therefore, to move about within a small area may effectively improve the call quality.

3.2.1 How to make a call

➤ Domestic calls:

Press the number keys to input a telephone number, or, select from the SIM Card 1 or SIM Card 2, then press the **Dialing Key** to start the call. If you want to change the telephone number, press the **Clear Key** to delete the input characters. An animated picture indicating the process of connection may appear on the screen. Information about the call mode will appear on the screen after the call is picked up at the other end. If the put-through tone is activated, a tone will be given. (Network support is required.)

Press the **Hang-up Key** to end a call.

Area code+telephone number+Dialing Key

> How to dial the extension of a fixed telephone

The extensions of some fixed telephones cannot be directly reached. You have to dial the switchboard number first and then dial the extension number. If you insert a character P (for "pause") between the switchboard number and the extension number, the switchboard will complete all the dialing actions for you and connect the extension automatically. Long press the ***** Key** to input "P" (At this time Character "P" will appear on the screen.)

Area code+switchboard number+P+extension number+Dialing Key

> Examples for the use of "P" character:

For example: If you have a voice mailbox system to be used through dialing under the telephone number 8880000, the mailbox number is 6666 and the password is 8888, then you can dial in the following way:

8880000 P 6666 P 8888

The first part of this number targets the voice mailbox system.

After the telephone is picked up, 6666 will be dialed to select the mailbox.

Before 8888 is dialed, the second "P" will generate a delay of 5 seconds. (The first P is inserted to wait for the call to be put through and the second P generates a delay of 5 seconds)

> International calls:

To make an international call, long press the ***** Key** until the character "+", a prefix character for the international long-distance call, turns up on the screen. This will allow you to make an international call from any country when you don't know the international call prefix number (for example, the prefix number for China is 00) of the place where you are.

Following the prefix number, input the country code and complete telephone number which you want to call. Country codes are based on international conventions. (e.g., Germany 49, UK 44, and Sweden 46, etc.)

Just like the usual practices to make an international call, the "0" which starts a city area code should be omitted.

E.g., if you want to dial a Indian service hotline from another country, you should dial

+91 21 114

+Country code+complete telephone number+Dialing Key

> Emergency calls:

So long as the mobile phone is within the network coverage (to check the signal columns on the top left of the screen which indicates the signal strength), you can call emergency service, even without a SIM card. If your service provider offers no roaming service in this area, then the information "Restricted to Emergency Call Only" will appear on the screen, only allowing you to make emergency calls.

3.2.2 How to pick up a call

> Under normal conditions, press the pick-up key to pick up an incoming call.

> If "Press Any Key to Answer" is activated, then press any key to pick up an incoming call.

> If earphones are connected to the phone, you can also press the key of the earphones to pick up an incoming call. If it is not convenient for you to press the key, you can activate "Automatic Pick-up" after connecting the earphone to the phone. The incoming call will be automatically picked up after 5 seconds of ringing or vibration.

3.2.3 How to reject an incoming call

> You can press the **Hang-up Key** to reject an incoming call.

3.3 How to use the data cable

> When the mobile phone is switched off, plug the data cable in and the mobile phone will be under the charging mode.

> When the mobile phone is switched on, plug the data cable in and two menus will be displayed:

- **Storage device:** When the mobile phone is switched to the storage mode, a computer can be used to read and write the memory card.

- Chapter four: menu details

4.1 Phonebook

➤ **Add new contact:** to add a new telephone number to the phone book. You can select the SIM card or the mobile phone as the storage device.

* Note: There is slight difference in storage formats between the two storage devices.

➤ **View:** View the information in the phone book.

➤ **Send text message:** People to send text messages in the phone book.

➤ **Send multimedia message:** Phone book of people to send MMS.

➤ **Call:** Select the phone book of people with SIM1 or SIM2 phone call.

➤ **Edit:** Edit phone book information.

➤ **Delete:** to delete phone entries. You can delete all the phone entries contained in the SIM card, or those in the phone book of the mobile phone. If you want to delete individual entries, select the "one by one" option.

➤ **Copy:** the phone book information from the SIM card to your phone or from phone to SIM card copying

➤ **Move:** the phone book information from the SIM card mobile phone or from phone to move to the SIM card.

➤ **Send contact:** Send the information in the phone book, with the cards the way to SMS, MMS or Bluetooth.

➤ **Add to Blacklist:** Contacts in the phone book to the blacklist, ban call comes.

➤ **Caller groups:** This mobile phone provides you with 5 incoming call groups. For each group, you can change the name, ring tone, incoming call icon and video. You can also perform customized settings for each member of the group.

➤ **Phonebook settings:** to set parameters relevant to the phone book, including four submenus

- **Preferred Storage:** to select the preferred storage device: the mobile phone or the SIM card.

- **Speed dial:** Setup shortcut to dial number.

- **My number:** Edit or send your phone number

- **Vcard version:** Mobile phone version of e-cards.

- **Extra number:** You can view and change other numbers stored in the SIM card, such as local number.

- **Memory status:** to check the space of the phone book in the SIM card and in the mobile phone

* Note: This mobile phone can store up to 1000 telephone numbers.

- **Copy contacts:** On all contacts in the phone book copy.

- **Move contacts:** On all contacts in the phone book mobile.

- **Delete all contacts:** Delete all contact information.

4.2 Messages

4.2.1 SMS

➤ **Write message:** Access the submenu "Write message" to input a message.

- **Send to:** to send a message. You will access a recipient editing box, where you can input numbers by pressing the number keys. You can also press the "Search" Key to select telephone numbers stored in the phone book, and then press **"OK" Key** to send messages.

- **Input method:** Select the input method editor.

- **Insert template:** insert text in the edit template cell phone text messages

- **Advanced:**

1. **Insert object:** to insert an object into the message being edited, such as a picture, ringtone, animated picture, etc.

2. **Insert number:** to change the input method for editing a message.

3. **Insert name:** to insert number

4. **Insert bookmark:** to insert bookmark to SMS.

- **Save to drafts:** to edit the message saved to Drafts.

* Note: The SMS centers in some cities and regions do not support long messages with more than 160 English characters).

➤ **Inbox:** to view the messages received. After the message list of the inbox appears, the user can press "**OK**" **Key** to read the details of the message. At this time the following options can be made:

- **Reply:** to reply to the sender of the current message
- **Call sender:** Call the sender of information.
- **Delete:** to delete the current message
- **Forward:** to forward the current message
- **Delete:** Delete information.
- **Delete all:** to delete all messages in the inbox
- **Advanced:**

1. **Use number:** to pick the number of the sender of the current message for dialing or storing it in the phone book.

2. **Use URL:** to extract the URL address (first of address must <http://www> or wap) in the current short message; then display them by list form. If you select one of the addresses, you can connect directly or add it to bookmark.

3. **Use USSD:** The use of information in the USSD.

4. **Copy to SIM card (mobile phone):** If the message is stored in the mobile phone, it will be copied to the SIM card; and vice versa.

5. **Move to SIM card (mobile phone):** If the message is stored in the mobile phone, it will be transferred to the SIM card; and vice versa.

6. **Copy all:** to copy all the messages stored in the SIM card to the mobile phone, or vice versa.

7. **Move all:** to transfer all the messages stored in the SIM card to the mobile phone, or vice versa.

➤ **Outbox:** to view the messages unsent out. After the message list in outbox, the user can press "**OK**" **Key** to read the details of the message. At this time the following options can be made:

- **Forward:** Into the SMS editor.
- **Delete:** to delete the current message.
- **Delete all:** to delete all messages in the outbox.
- **Advanced:**

1. **Use number:** to pick the number of the sender of the current message for dialing or storing it in the phone book.

2. **Use URL:** to extract the URL address (first of address must <http://www> or wap) in the current short message; then display them by list form. If you select one of the addresses, you can connect directly or add it to bookmark.

3. **Use USSD:** The use of information in the USSD.

4. **Copy to SIM card (mobile phone):** If the message is stored in the mobile phone, it will be copied to the SIM card; and vice versa.

5. **Move to SIM card (mobile phone):** If the message is stored in the mobile phone, it will be transferred to the SIM card; and vice versa.

6. **Copy all:** to copy all the messages stored in the SIM card to the mobile phone, or vice versa.

7. **Move all:** to transfer all the messages stored in the SIM card to the mobile phone, or vice versa

➤ **Drafts:** Drafts of the information on editing and settings.

- **Send:** The message sent to.
- **Delete:** to delete the current message.
- **Delete all:** to delete all messages in the outbox.
- **Advanced:**

1. **Use number:** to pick the number of the sender of the current message for dialing or storing it in the phone book.

2. **Use URL:** to extract the URL address (first of address must http://www or wap) in the current short message; then display them by list form. If you select one of the addresses, you can connect directly or add it to bookmark.

3. **Use USSD:** The use of information in the USSD.

4. **Copy to SIM card (mobile phone):** If the message is stored in the mobile phone, it will be copied to the SIM card; and vice versa.

5. **Move to SIM card (mobile phone):** If the message is stored in the mobile phone, it will be transferred to the SIM card; and vice versa.

6. **Copy all:** to copy all the messages stored in the SIM card to the mobile phone, or vice versa.

7. **Move all:** to transfer all the messages stored in the SIM card to the mobile phone, or vice versa

➤ **Templates:** Some common phrases can be written into the common information so as to avoid repeated and word-by-word input when a message is being sent. The common phrases can be edited or deleted.

➤ **SMS settings:** When using the short message function you must first make the necessary settings. Enter the "**SMS settings**" submenu to select **SIM1/2 message settings** to operate as follows:

- **Profile settings:** to select a suitable mode for the mobile phone message. Under each mode, you can set the corresponding names, message center numbers, valid period and message format.

- **Voice mail server:** For a voice as input box, each other can hint after the prompt input message.

- **Common settings:** to set whether to activate "Message Report".

- **Memory status:** to view the space of the SIM card or that of the mobile phone mailbox

- **Preferred storage:** to select the mobile phone or the SIM card as the storage device

4.2.2 MMS

A multimedia message may carry text, pictures and sound. Through multimedia message service, you can not only send and receive pictures and text, but also receive attached audio files. Taking advantage of the color screen, multimedia messages feast your eyes and ears with brilliant colors and vivid audio effect.

This mobile phone is able to receive multimedia messages with a size up to 50KB.

Multimedia messages with a size over 50KB cannot be received by the mobile phone. And likewise, the maximum size of the messages to be sent is also 50KB.

This mobile phone supports multi-page multimedia messages. That is to say, a multimedia message may consist of several pages, and each page can include a picture, a piece of tune and some characters. If a multimedia message carries pictures, the mobile phone will zoom in or out the pictures automatically so as to adapt it to the screen.

* Note: This function needs support from the service provider.

➤ **Write a message:** Select it to create a new message. You can fill in the boxes of recipient, copy, secret copy, subject, contents and attachment.

➤ **Inbox:** to view the multimedia messages received (Detailed operation is identical with that of the text messages)

- **View:** to view the current multimedia messages

- **Reply:** to edit the MMS to reply sender, at the same time, subject change to "Re." and old subject.

- **Reply by SMS:** the edits the SMS to reply sender, at the same time.

- **Reply all:** to edit the MMS to reply all, at the same time, subject change to "**Re:**" and old subject.

- **Forward:** to forward the current multimedia message to other recipients.

- **Delete:** to delete the current MMS.

- **Delete all:** to delete all the current MMS.

- **Save as template:** to save MMS to Templates.

- **Properties:** to view the details of the current multimedia message, such as the sender, date, time and size

- **Use details:** to pick up the number of sender and the bookmarks of content. you can Write MMS, Dial the number or Save to Phonebook, also you can Go to the bookmarks or add bookmarks.

➤ **Outbox:** to store the multimedia messages which have not been successfully sent

- **View:** to view the current multimedia messages

- **Send:** to resend the current multimedia message

- **Delete:** to delete the current multimedia message

- **Delete all:** to delete all the contents in the outbox

- **Save as template:** to save MMS to Templates.

- **Properties:** to view the details of the current multimedia message, such as the sender, date, time and size

- **Use details:** to pick up the number of sender and the bookmarks of content. you can Write MMS, Dial the number or Save to Phonebook, also you can Go to the bookmarks or add bookmarks.

➤ **Draft box:** If a message is not to be sent immediately after being edited, it can be saved in the draft box. The message will be transferred to the sent message box after it is sent.

- **View:** to view the current multimedia message

- **Send:** to resend the current multimedia message

- **Edit:** to edit the current multimedia message

- **Delete:** to delete the current multimedia message

- **Delete all:** to delete all the contents in the draft box

- **Save as template:** to save MMS to Templates.

- **Properties:** to view the details of the current multimedia message, such as the sender, date, time and size

- **Use details:** to pick up the number of sender and the bookmarks of content. you can Write MMS, Dial the number or Save to Phonebook, also you can Go to the bookmarks or add bookmarks.

➤ **MMS settings:** to set parameters relevant to the sending and receipt of the multimedia messages

- **Profiles:** MMS network settings state

- **Compose:** include **Creation mode**, **Picture resizing** and **Auto signature**.

- **Send:** include **Validity period**, **Delivery report**, **Read report**, **Priority**, **Slide timing**, **Delivery time**.

- **Retrieve:** include **Home network**, **Roaming**, **Read report**, **Delivery report**.

- **Filter:** include **Anonymous** and **Advertisement**.

- **Memory status:** view **Usage**, **Used space**, **free space**.

4.2.3 Voice mail server

Every voice mailbox has the following functions:

➤ **Editing:** to edit names and telephone numbers

➤ **Connect to voice:** to connect to the voice mailbox through dialing

4.2.4 Broadcast message

Select this to receive and read the information provided by the cell broadcast. The functions are as follows:

➤ **Receipt mode:** to receive/reject cell broadcast

➤ **Read message:** to read the information received from the cell broadcast

➤ **Language:** to select a language

➤ **Channel settings:** to set the channels of the cell broadcast, for example, to select/add/edit/delete a channel.

4.3 Call log

4.3.1 Call history

➤ **SIM1/2 Missed calls:** Missed calls can be recorded.

➤ **SIM1/2 Dialed calls:** Dialed numbers can be recorded.

➤ **SIM1/2 Received calls:** Received numbers can be recorded.

On the interface of call record list, press "**OK**" **Key** to view the details of a record, such

as the date, time of dialing, name and number, as well as times of dialing.

On the interface of detailed information, press "Option" and you can perform the following operations on the currently selected record,

- **View:** View phone information
- **Call:** to dial the current telephone number.
- **Send text message:** to send the SMS to this number.
- **Send multimedia message:** to send the MMS to this number.
- **Save to Phonebook:** to save the current number to the SIM card or mobile phone.
- **Add to Blacklist:** The contacts in blacklist, banning this person is dialed telephone send information.

- **Edit before call:** to edit the current telephone number and store it into the phone book.

- **Delete:** to delete the current record.
- **Delete all:** Delete all records current.
- **Advanced:**

SIM1/2 call time: Under this menu there are three submenus, i.e., "Last call duration", "Total duration of outgoing calls" and "Total duration of received calls".

- **Last call time:** to view the duration of the last call
- **Total sent:** to view the total duration of the outgoing calls
- **Total received:** to view the total duration of the received calls

SIM1/2 call cost: It provides you with the information about accumulated call charge.

- **Last call cost:** to view the charge of last call
- **Total cost:** to view the accumulated call charge

1. **Reset cost:** Input the PIN2 code to reset the charge counter. The counter will then start from 0.

SIM1 test msg counter: SIM1 information counter.

SIM1/2 GPRS counter

- **Last sent:** to record the quantity of bytes which have been sent last time
- **Last received:** to record the quantity of bytes which have been received last time
- **All sent:** to record the total bytes which have been transmitted
- **All received:** to record the total bytes which have been received
- **Reset counter:** to reset the counter

* Note: SIM2 call history is same with SIM1 call history* Note: The PIN2 code is needed in some operations. Please contact your service provider to obtain the PIN2 code.

* Note: This function needs network support.

* Note: SIM2 call history is same with SIM1 call history.

4.3.2 General call settings

SIM1/2 call settings

- **Call waiting:** to activate/deactivate the call waiting function. Select "Query" to view the current state of call waiting function.

- **Call divert:**

- **Divert all voice calls:** to divert calls under all circumstances. The number of rings at that shall trigger depends on network.

- **Divert if unreachable:** to divert all incoming calls when the phone is not reachable due to some network error or other reasons

- **Divert if no answer:** to divert the incoming call if it is not answered.

- **Divert if busy:** to divert all incoming calls when there is at least one call in progress on the handset.

- **Diver all data calls:** to divert all data calls.

- **Cancel all diverts:** this shall deactivate this facility.

- **Call barring:** to restrict call activities.

- **Outgoing calls:** to restrict the outgoing calls

- **Incoming calls:** to restrict the incoming calls

- **Cancel all:** to cancel the restrictions which have been set (PIN2 code needed).

- **Change barring password:** to change the password

- **Line switching:** you can switch "Line 1" or "Line 2".
- **Closed user group:** Off with the group.

Advanced settings

- **Auto record call:** on/off auto record call.
- **blacklist:** Prohibit a particular number.
- **Auto redial:** When this function is activated, a call failure will be followed by an automatic redialing.
- **Call time display:** Turn on or off to this option, can display or not display the call time.
- **Call time reminder:** allow user to remind him about duration of a call.
- **Off:** to cancel this function.
- **Single:** a single reminder beeps only once, the times may range from 1 to 3000 seconds.
- **Periodic:** to periodic reminders beep periodically every time the timer expires, the times may range from 30 to 60 seconds.
- **Auto quick end:** is to limit call time, you can select item to set by the up/down key.

4.4 Multimedia

4.4.1 File manager

Memory card for mobile phones and store documents.

4.4.2 Image viewer

To manage the photos which have been taken by the mobile phone.

- **View:** to zoom in and preview the selected photo.
- **Send:** With the MMS or bluetooth devices transmit photos.
- **Use as:** use the selected photo as the wall paper, screen saver, power-on/off animated pictures, incoming call icon, to multimedia message and to Bluetooth.
- **Rename:** to change the name of the selected picture
- **Delete:** to delete the selected picture
- **Delete all files:** to delete all the photos in the album
- **Sort by:** to sort the pictures contained in the selected file folder according to name, type, time, size or none.

Storage: Stored for mobile phones or MMC card

Video: Place the video folder to play the file.

4.4.3 Video player

It is used to play saved videos, offering the following functions:

- **Play:** to play a selected video.
- **Send:** With MMS or Bluetooth devices transmit video files.
- **Rename:** to change the name of the selected video files.
- **Delete:** to delete the selected video files.
- **Delete all files:** to delete all the video files in the album.
- **Sort by:** to sort all videos in the current folder according to the name, type, time, size or null.
- **Storage:** to select the storage path for playing videos, either on the mobile phone or memory card.

4.4.4 FM Radio

- **Channel List:** list of all search channels.
- **Manually Input:** input a frequency.
- **Auto search:** search and add channel to list.
- **Setting:** FM-related settings.
- **Record:** FM record.
- **Append:** add extra record basis on select audio.

4.4.5 Video recorder

The phone features a function of video recorder. Choose "Video Recorder" in the menu. Press the ok key start video recording.

Options:

- **Camcorder settings:** to set relevant parameters of video recorder.
- **Video setting:** to set relevant parameters of photographing.

- **White balance:** to set the white balance mode during photographing.
- **Effect settings:** to set effect modes of photos.
- **Storage:** to store videos in the phone or memory card.
- **Restore default:** set all settings to preferred settings.

4.5 Camera

The phone features a function of camera. Select "Camera" in the menu. Press the camera key on the side of the phone for photographing. **Options:**

- **Photos:** to access the album.
- **Camera settings:** to set relevant parameters of photographing.
- **Image settings:** to set the size and quality of photos.
- **White balance:** to set the white balance mode during photographing.
- **scene mode:** Used to convert the day and night mode.
- **Effect settings:** to set effect modes of photos.
- **Set frame:** Set the preview interface frame.
- **Storage:** to set the default storage pathway for the photos.
- **Restore default:** Reset all settings to the default values.

4.6 Audio player

Click "List" at the bottom left corner of the screen to enter the play list. You can scroll the screen to search for a specific song and play it.

On the interface of song list, click "Option" at the bottom left corner to set relevant parameters of a song.

- **Play:** to play a selected song.
 - **Details:** to check the detailed information of a song.
 - **Add to ringtones:** to add current song into ring tone database.
 - **Refresh list:** to update song list.
 - **Settings:** to set the multimedia video player
1. **Pre. Play List:** to set default reading path.
 2. **List auto gen.:** to set whether or not to automatically update the song list every time the phone is switched on.
 3. **Repeat:** to repeatedly play songs if this function is activated.
 4. **Shuffle:** to randomly play songs if this function is activated.
 5. **Background play:** to set it on, you can listen to music with other operation.
 6. **bluetooth:** Connect with bluetooth devices with bluetooth devices, output

4.7 Organizer

4.7.1 Calendar

Press "Option" to access the submenu.

- **View :** Look up the current routing.
- **Add event:** Edit operation as follows:

Reminder.

Meeting.

Course.

- **Delete event:** Deleted when the event set.
- **Jump to date:** Input the **Date**, press the **left soft key "Ok"** to jump to the appointed date.

- **Go to weekly / monthly view:** To display tasks by week or month

* Note: Owing to the limited storage space, the users are requested to save no more than 35 records; otherwise the records will be lost.

4.7.2 Tasks

- **View:** to view the saved memos.
- **Add:**
 - **Date:** date on which the memo will give a prompt
 - **Call:** Tel memorandum will be given prompt.
 - **Anniversary:** Anniversary will be given a reminder alarm.

View: View the task information.

Add: Add the task information.

Edit: to modified the saved memo.

Delete: to delete one selected memo.

Delete overdue: Remove overdue tasks.

Delete all: Remove all tasks.

Jump to date: Input the **Date**, press the **left soft key "Ok"** to jump to the appointed date.

Save as file: Save the file in document form.

4.7.3 Alarm

➤ **Switch-on/off:** to switch on/off the alarm

➤ **Time:** to set the time of alarm

➤ **Alarm options:**

- **Once:** to alarm only once for the agenda

- **Daily:** to alarm at a set time every day

- **Customized:** to set the alarm to a defined time in a week

4.7.4 World clock

Enter World clock submenu, display world time zone map, move coordinate location by touching screen arrow, the interface will show the city time located by the coordinate.

4.7.5 Calculator

Your mobile phone provides a calculator with 4 basic functions to facilitate simple calculations.

Enter the "Calculator" submenu to display the operation interface of the calculator:

➤ Use the Number keys from 0 to 9 to enter the numbers you wish to enter, use the # key to enter the decimal point.

➤ Press the up/down and left/right keys to enter the symbols for the four mathematical operators +, -, x or ÷

➤ Press the Right Soft Key to backspace the numbers digit by digit; press the Right Soft Key to exit the calculator function; Press the Left Soft Key or "OK" key to obtain the result of calculation.

* Note: An error caused by rounding may arise due to the limited accuracy of this calculator, especially when a dividend cannot be divided exactly.

4.7.6 Unit converter

The weight and length of conversion.

4.7.7 Currency converter

About national currency.

4.7.8 Ebook reader

You can read files (*.txt) saved in the phone or Memory Card. (Memory card have been inserted into the mobile-phone). You need to copy the file to [File Manager]/Phone (or Memory Card)/ EBook, then enter E-Book to read it.

Select "Option" to select the operation as follows:

- Open E-Book: to read the detailed contents of the selected file

- Clean up bookshelf: to clean up the bookshelf.

- Global settings: to set Font Style, Font Size, Scroll By, Auto Scroll, Scroll speed, Full Screen and Encoding.

- Book info: to display Title, Size and Format.

- Delete: to delete the selected file

- Delete All Files: to delete all the files in the EBook menu

- Sort by: to array all the files in the EBook menu, you can select By Name, By Type, By Time and By Size, or select none to not array the files.

- Apply global set: to apply Global Settings

- Help: how to use shortcuts by 0-9 key

* **Note: Only the file (*.TXT) which size is smaller than 2M and which is saved in the [EBook] can be displayed in this menu. Only the file of Unicode encode format can be displayed**

4.7.9 Stopwatch

Timing with stopwatch.

4.8 Fun& Games

-
- **JAVA:** JAVA application
 - **JAVA settings.**
 - **Games**

1. Puzzle

2. Magic Sushi

3. Games settings:

Turn On or Off Game music, Sound effect, Vibration, and change the volume.

4.9 Settings

4.9.1 User Profiles

4.9.1.1 General

➤ **Activate:** to select this to access the general mode.

➤ **Customize:** to select this to customize the general mode. The functions are as follows:

- **Tone setup:** to allow the user to customize different ring tones with different option, for example, incoming call, power on or off, and so on.

- **Volume:** Two type of volume can be set: Ring tone (including incoming call, alarm, power on, power off, message tone) and Key tone (associated with key press).

- **Alert type:** This option allows the user to set the kind of alert he expects whenever there is an incoming call. User can select only one option from Ring, Vibe. only, Vibe. and ring and Vibe. then ring.

- **Ring type:** This option allows the user to set mode of ring, include Single, Repeat and Ascending.

- **Extra tone:** The user can turn on or off the tone as follows: Warning, Error, Camp on and Connect.

- **Answer mode:** The user can select different modes of answering: Any key (except for the Hang-up key, right soft key) and Auto (display when the earphone insert).

4.9.1.2 Meeting

The operation is the same as that of the general mode.

4.9.1.3 Outdoor

The operation is the same as that of the general mode.

4.9.1.4 Indoor

The operation is the same as that of the general mode

4.9.1.5 Headset

Plug the earphone and this mode will be automatically activated. The operation of the personal settings is the same as that of the general mode.

4.9.2 Dual SIM settings

In the submenu, you can select **Dual SIM open**, **Only SIM1 open**, **Only SIM2 open** or **Flight mode**.

4.9.3 Pen calibration

You can adjust touch screen more flexible and precise.

4.9.4 Phone settings

➤ **Time and date:** to set time and date

- **Set home city:** to select the different city in 77 cities.

- **Set time/date:** to set the current time and date

- **Set format :** to set the display format of the time and date

➤ **Schedule power on/off:** You can edit 4 times to turn on/off the mobile-phone. Each time includes setting as follows: Status (Disable or Enable), Power on or off and time. Finish setting, when the time arrive, mobile phone will turn on/off according as the status.

➤ **Language:** to set the language of the mobile phone menus

➤ **Pref. input methods:** to select a default input method

➤ **Display:**

- **Wallpaper:** to select a wallpaper for the standby interface

- **Screen saver:** to select a picture to be used as the screen saver and set the waiting time

- **Power on display:** to select an animated picture to be displayed during switch-on

- **Power off display:** to select an animated picture to be displayed during switch-off
- **Show date and time:** to turn on or off, set whether display the date and time on standby interface.
- **Show owner number:** to turn on or off, set whether display owner number on standby interface.
- **LCD backlight:** to set the brightness of the LCD backlight and the waiting time.
- **Greeting text:** Editing startup greeting.
- **Dedicated key:** In this menu, you can edit the shortcut function of navigation keys on standby: Up key, down key, Left key and Right key.
- **UART setting:** UART option.

4.9.5 Network setup

- **SIM1/2 net work setup**
- **Network selection:** Include new search, select network, and selection mode.
- **Preferred networks:** to preset several network preferred by the user

4.9.6 Security settings

- **SIM1/2 security setup**
- **Phone lock**

You may set a password to protect your phone from unapproved use. Once you have selected this function, you have to input your phone password each time you switch it on so as to unlock it, and then make or receive calls. The user may remove the phone password, but under such circumstances the mobile phone will not be protected against unapproved use.

- Input the phone password. Press the **Right Soft Key** to delete the wrong input. Press **"OK" Key** to confirm.

For example, if you want to set 0000 as the phone password, input **0000**.

* Note: The default phone password is 1122. You should replace it with your own password as soon as possible. If you forget your mobile phone password, you have to contact your service provider or the local authorized service center to unlock your phone.

- **Auto keypad lock:** A time select from 5 sec, 30sec, 1min and 5min, on standby, if you do nothing in the time of setting, keypad will automatically lock. If you select "None", cancel this function.

- **Change password:** to change the phone password

* Note: Some functions call for support from your service provider.

- **Mobile tracker:** you can open and set receiver number, since model has changed sim card, phone will send tracker message to the designed number automatically
(Notes: default password is 0000, the same as phone lock)

4.9.7 Connectivity

- **Bluetooth**

This mode will be activated after the Bluetooth is switched on. The operation of the personal settings is the same as that of the general mode.

- **Data account:** Mobile phone network Settings of the data.

- **GPRS**

- **Account name:** You can select "Edit" to change the name of the account.
- **APN:** to input APN.
- **User name:** account name of a dialing server (not a WAP gateway)
- **Password:** account password of a dialing server (not a WAP gateway)
- **Auth. type:** to the options have Normal and Secure

4.9.8 Shortcuts

You can edit the shortcut menu, it will display in the [shortcuts] menu.

4.9.9 Restore factory settings

This will reset the mobile phone functions to default values. (Notes: default password is 0000, the same as phone lock)

4.10 Services

- **Menu functions:**

- **Homepage:** Select this to log on the homepage. A homepage is a WAP website which is selected by the user during the settings of an activated connection. If you have not performed any settings, a website preset by the manufacture will be used.
- **Bookmarks:** This function displays all the available bookmarks. You can select the websites that have a direct connection to the bookmark, edit the name of the bookmark, edit the address or delete the bookmark.
- **Recent pages:** Display the recent pages. Select one page, can go to at first hand.
- **Input address:** Use this menu to manually enter the URL address of a website and example, service messages may consist of notifications on news briefings, or a line of a text message, or a WAP service address.
- **Service inbox:** Select "Service inbox" to view received service messages. Your mobile phone can receive service messages sent by your service provider. For example, service messages may consist of notifications on news briefings, or a line of a text message, or a WAP service address.
- **Settings:** to Select "Settings" to enter settings for online browsing, including "Select SIM", "Edit profile", "Browser options", "Service message settings", "Clear cache", "Clear cookies"

* Note: GPRS service calls for network support. It can only be used within the GPRS network coverage after the service application is approved.

4.11 Lemon Twist

1. Twitter
2. Facebook
3. Nimbuzz
4. Buzz In Town
5. Yahoo Cricket
6. Yahoo mail
7. Yahoo Front Page
8. Yahoo News
9. Yahoo Finance
10. Yahoo Astrology
11. Yahoo Search
12. Yahoo Movies
13. Yahoo Flickr

4.12 Opera

You can open Opera mini Java applications to browser website.

4.13 Menu during the call

During the call, press "option" to access the call menu. The operation method for the call menu is the same as that of the function menu.

This call menu can only be seen during the process of call. In addition, the functions such as call waiting, call hold-on, multi-party meeting need network support. Please contact your service provider for details.

In the call menu, you can perform the following operations:

- **Hold single call:** to hold on the current call or restore the call held on
- **End single call:** to end the current call
- **New call:** to make a new call
- **Phonebook:** to browse the phone book
- **Message center:** to write and send a message
- **Sound recorder:** to record a new audio file
- **Background sound:** to turn on/off Call Background sound
- **Mute:** not to send/send the local voice of the call
- **DTMF:** to deactivate or activate DTMF sound.
- **Multi-party call**
 - **Switch:** to switch between the active call and the call held on
 - **Conference:** to start a telephone conference
 - **Call transfer:** to transfer the current call to another mobile phone

- **End single line:** to end the current active call
- **End all:** to end the current call(s)
- **Phone book:** to access the phone book
- **Message:** to access the message menu
- **Audio recording:** to record an audio file
- **Mute/restore:** not to send/ to send local voice of the call

*Note: Some items can only appear under specific circumstances. For example, "switch" will appear only when a call in dialogue and a call held on coexist.

Chapter five: FAQ

1.1 Why does the phone prompt "Please insert SIM card"?

1. The SIM card is in poor contact with the phone or the SIM card has not been inserted into the phone.
2. Replace with a new SIM card and try again. If the phone is in good condition, it means the original SIM card is defective. Please contact the SIM card operator.
3. If the surface of SIM card or the SIM card interface shows a sign of oxidation. Please use ethanol to clean it; or use clean soft cloth to wipe it.
4. If all the above prove ineffective, please contact *** service center or go to *** maintenance store for repair and test.

1.2 How to get and use the PIN, PIN2, PUK, PUK2 codes and restriction password?

1. Please contact the local operator for inquiry.
2. If a wrong PIN code is input for three consecutive times, the SIM card will be locked.
3. Please contact SIM card operator for the inquiry of PUK code.

1.3 Frequent occurrence of network failure

1. You might be in a place with weak signals or shield. Please leave the place and try again.
2. The phone needs inspection and test. Please contact *** service center or go to *** maintenance store for repair and test.

1.4 Your voice can not be heard at the other end.

1. First make sure whether it is a problem of network. Then try again.
2. You might be in a place with poor network connection. Please leave the place and try again.
3. This may caused by the poor relay connection of the network operator.
4. If all the above proves ineffective, please contact *** service center or go to *** maintenance store for repair and test.

1.5 Charging failure or charging without any indication

1. It might be due to poor contact between the charger and the phone. Please make sure the connection is reliable.
2. During charging, the phone will display "Charging" only when it is power-off. There is no indication of "Charging" when it is switched on.

1.6 Intermittent signals

1. If you are in a place with unstable local network signal, the phone might indicate unstable signals. Please leave the place and try again.
2. If all the above prove ineffective, please contact *** service center or go to *** maintenance store for repair and test.

1.7 Unable to call

1. You might be in a place with poor signals. Please move to a place with stronger signals.
2. Local network operator might be busy now. Please try to call later.
3. If all the above prove ineffective, please contact *** service center or go to *** maintenance store for repair and test.

1.8 Short standby time

1. The standby time of the phone might change according to different network signals in different places.
2. It is affected by many factors including ambient temperature, distance from the base station, etc.

Ser. No.	State	City	ASC Name	Address	Contact Person	Phone No.	Email Id
1	AP	Ananthapur	R.K. Mobile Services	R.K MOBILES SERVICE, SHOP NO:1, 1ST FLOOR, OPP-MUNI RATHNAM MOTORS, BESIDE PROFESSIONAL COURIER, KAMALA NAGAR, RAJU ROAD, ANANTAPUR-515001	Mr. Pavan Kumar	9885908738	rksol.kur@gmail.com
2	AP	Hyderabad	Prime Tech Services	Rajnigandha Apartments, Chaitanyapuri, Shop No.-8, Opp. Chaitranapuryri bus Stop, Dilsukhnagar, Hyderabad, AP.	Shyam Sunder	9849990038	shyam0038@yahoo.co.in
3	AP	Warangal	Siri Agencies	F9 Shutter 2nd Floor, KR & MS Reddy Complex, Hanmakonda, Andhrapradesh	Mr. Raghu Babu	9346311223	raghunallapu2010@gmail.com
4	AP	Karimnagar	Sagarika Technologies	# 2-8-40, Circus Ground Lane, Mukarampura,	Mrs. Sagarika	9866423456	sagarika.technologies@yahoo.in

				Karimnagar.			
5	AP	Warangal	S.S. Bharti Communication	8-9-100/12, Victory Estate, J.P. N Road, Chourastha, Andhra Pradesh.	L. Sudarshan Rao	934655223	ssbharti05@gmail.com
6	AP	Nellore	Tirumalaa Electronics	D No.-16-2-268, Behind Mayuri Restaurent, Pogathola, Nellore.	S Naga Praveen	9347033153	tirumalaaelectronics@gmail.com
7	AP	Nalgonda	R.S. Communication	6-5-3, Viswalaxmi Complex, Beside Aircel Office, Hyderabad Road, Nalgonda.	Mr. Raju	9885399868	rsserv4comm@gmail.com
8	AP	Ongole	SRI CHAKRI MOBILES PLAZA	Shop No 3, C.V.N. Complex, Opp:Thatha Building's, Sivalayam Road, Ongole, Prakasam Dist. Andhra Pradesh	K.CHAKRADHAR	8008350555	chakrihnp@gmail.com
9	AP	Eluru	Excellent Mobiles	Near Vaibhav Jewellers, Main Bazar, 1 Town, Eluru, Andhra Pradesh	K N V Krishna Rao	9441414874	excellentmobileseluru@gmail.com
10	AP	Karimnagar	Om Mobiles (A.P.)	2-9-44/7, Siti Cable Lane, Jammikunta, Distt.-Karimnagar	G. Gyanender	9849869285	om.jmkt@gmail.com

				r, Andhra Pradesh			
11	AP	Adoni	Sai Cell Solutions	Bhavana Hospital Complex, Opp.-Kotla Circle,M.M. Road, Adoni, Andhra Pradesh	K.Rama Subbaiah	9703265876	saillemon.adoni@gmail.com
12	AP	Mahbub Nagar	Sri Chakra Mobile	Shop No. 4 , Shareef Complex , Nr. New Bus Stand, Mahbub nagar.	Anil Kumar	9396333111	srichakramobile@yahoo.com
13	AP	KHAMMAM	LAXMI SREENIVASA ENTERPRISES	H.NO.9-7-37, Opp. MASJID, KASBA BAZAR	Mr. V.MAHENDRAN ADHA REDDY	9849836531	lemonkmm@gmail.com
14	AP	KADAPA	S V Technologies	Door No-1/331,Maruthi nagar,National lodge complex, Opp: New Apsrtc busstand ingate, Kadapa	Ravikumar	9396999044	sv.kadapa@gmail.com
15	AP	Kurnool	Anwar Communication	C/oANWAR MOBILES SERVICE CENTRE, Shop NO. 9 , Bhupal Complex , Park Road , Kurnool	Mr. Zakir	9866026731	anwar_marketing@yahoo.com
16	AP	SECUNDRABAD	SAAROOPY	#	Subramanyam	97046651	saaroopyamobiles

		DERABAD	A MOBILES	3-4-126,Beside janapriya bus stop, Annapurna colony,main road,Mallapur.		66	@gmail.com
17	AP	Vijayawada	Vashnavi Technologies	Flat no 105, Rajsree apartments, # 29-4-20, kodandaramireddy street, Beside Ing vysa bank, Governorpet.	V.Satyanarayana Rao	9949941400	satyan20_v@rediffmail.com
18	AP	Nandyal	M.V. Distributors	# 3-185, Bairmal Street, Nandyal, Kumool District.	M. Chandramouli	9849840006	m.vdistributors@yahoo.co.in
19	AP	Anantapur	Bharathi Mobile shoppe	# 11/40, ladies club bldg, subash road, Anantapur.	Dhanunjaya Reddy	9866347317	tdreddy123@gmail.com
20	AP	Srikakulam	New Vision Comm.	Nehru Road, UPSTAIR Plastic World, Srikakulam.	srinivasarao.b	9849228121	nuuvvision@rediffmail.com
21	AP	Secunderabad	SRI SAI Comm.	1-7-301, SHOP NO.-26, Hardy complex M.G.Road.	Mr.Mani	32436463	srisaicomcommunications.service@gmail.com
22	AP	Hyderabad	Hi Fi Mobile	# 6-133 Opp: Hetero Pharmacy, Dwarkapuri colony,Chintal,	Mr.Satish Reddy	9291503773	satishreddy.goli@yahoo.com

				Hyderabad.			
23	AP	Visakha patnam	Arun Cell Care	D.no: 47-3-18/5, shop no: 05, Sri nilaya complex, Dwaraka nagar 5th lane Visakhapatnam.	N.G. Arun kumar swamy	98850361 43	aruncellcare@yah oo.in
24	AP	TIRUPA THI	CMT COMMUNIC ATIONS	# 13-7-796-14-B, TUDA OFFICE ROAD, TIRUPATHI	K.TEJA	93936202 09	cmt_tpt@yahoo.co m
25	AP	Manche riyal	Sri Sai Communicat ion	Shop No. 08, Mounika Complex, Bellampally Chourasta, Manc heriyal.	Rajesh	93941434 20	lg.rajesh09@gmail .com
26	AP	Kothagu dem	Telangana Mobiles	S C Shop No.-7, M G Road, Kothagudem, Disst.-Khamma m, Andhra Pradesh	P Ramarao	98662414 66	telanganamobiles @gmail.com
27	AP	Guntur	Vasavi Associates	4/1, Arundelpet, opp. Ing Vaysa Bank, Guntur, Andhra Pradesh	Vvssmanikaya Rao	98853908 17	jobsheet9@gmail.c om
28	Arunachal Pradesh	banderd ewa	Hi Tech	Boro Mahajan Building, Po Banderdewwa, Near Bluehill Bus Counter, Distt. Papum Pare. Arunachal	Wasim Ahmed	94360424 25	capitaltvservice@g mail.com

				Pradesh.			
29	Assam	Barpeta	New Micro Solution	Saradha Complex,durgabari Road,Barpeta Road,Barpeta,Assam	Manash Kr. Mandal	9085327767	m_solution05@yahoo.co.in
30	Assam	Nagaon	R T Service	Room No.-27, 1st Floor, Market Complex, Nurul Amin Stadium, Nagaon, Assam.	Usha Das	3672251259	rtservice.ngg@gmail.com
31	Assam	Guwahati	Multitrack	Bora Service Station, G S road, Guwahati, Assam	Ka;;o; Dutta	9564444684	multitrack_ghy@rediffmail.com
32	Assam	Golaghat	Mobile Care (Golaghat)	Near Garodia Hardware Store,Dhodar Ali (Main Road),Golaghat, Assam	Ranju Dev	940129208	rajudev72@gmail.com
33	Assam	Dhubri	Mahabir Electronics(Dhubri)	Opp.-Shahitya Sabha, G.T.B Road, Dhubri, Assam	Bibek Jain	9864361236	amit_ajmera25@yahoo.in
34	Assam	Champaguri	D M Mobile Care	Champaguri, Road No.-8, Opp. Bimal Engineering, P.O.+P.S.,Distt.-Bongajom, Assam	Pabtira Das	9706023177	phyprabin@yahoo.co.in
35	Assam	Sivasagar	K.R.Enterprises	Babupatty,Near ICICI Bank,	Isfaqar Rahman	987078688	issaqraman@yahoo.com

				Sivasagar, Assam			
36	Assam	Guwahati	SPECIAL PROJECT	K K Commercial, Kundil Nagar Road, Opp.- Megha Plaza, Basistha Charali, Guwahati, Assam	Daulat	9717095250	a
37	Assam	Barpeta	A.H.Service Centre	Howly Chari, PO- Howly, Distt.- Barpeta, Assam	Md. Abid hassan	9954589999	adib.hassan49@gmail.com
38	Assam	KARIMGANJ	Monalisa Servicing Center	Spice Servicing Venter, C/o-Monalisa, Shibbari Road, Opp.- Customs Office, P.O. Distt.- Karimganj, Assam	Prabal Chakraborty	9859938866	prabalc10@gmail.com
39	Assam	Tinsukhia	Netsol Tinsukhia	TDA Central Plaza, 1st Floor, Tinsukhia, Assam-	Mr. M.D. Shakil	9435412475	netsoltinsukia@yahoo.co.in
40	Assam	Dibrugarh	Speednet @ Ajmera	Ajmera House, Thana Charali, Dibrugarh, Assam-	Mr. Kamal Kishore jain	9435030660	speednet.dib@lem onmobiles.com
41	Assam	Hojai	B.S. Cell Point	Dadabhai Shopping Center, Main	Mr. Bapan Saha	3674250002	bscellpoint@yahoo.com

				Road , Hojai, Assam -			
42	Assam	Jorhat	Mahabir electronics	Opp. Balaji canvas store, J.B.Road,	Avinash Dutta	99549832 94	avinashjrt@gmail.c om
43	Assam	Silchar	DIGITAL WORLD	RAJA BAJAR COMPLEX (Shop no 12B), CRCUIT HOUSE ROAD (OOP D.S.A), Silchar 1	Mr. Raj kumar singha	99541603 5	<digitalworldsilchar .lemon@yahoo.in
44	Assam	Dibrugar h	Gem Palace Trading	Keshan Market,Opp. Ranghar Cinema Hall,H. S. Road,Dibrugarh- 1,(Assam)	Deepak Ranasaria	94353300 61	gem.dibrugarh@le monmobiles.com
45	Bihar	Patna	S S Services	Shop No.-102, 1st Floor, Kaushlaya Estate, Dakbunglow Road, Patna, Bihar	Pramod Kumar Singh	99555949 81	s.s.1services1@g mail.com
46	Bihar	Vaishali	Varaities	Cinema Road, Hajipur, Vaishali, Bihar.	Surendra Kumar Chaudhary	99340808 55	varaities_hjp@yah oo.com
47	Bihar	Begusar ai	Shivam Fonex	Market Today, Kachahri Chowk, Begusarai, Bihar	Amit kumar	93085301 75	shivamfonexbgs@ gmail.com
48	Bihar	CHAMP RAN	PRATAP COMMUNIC ATION	CHURCH ROAD , NEAR St MARRY	RAVI PRATAP	99310732 96	pratapcommunicati on@yahoo.com

				SCHOOL ,BETT IAH W. CHAMPAN, BIHAR			
49	Bihar	Samasti pur	Chaudhary Communicat ion	Dimond Plaza Station Road, Rambabu Chowk, Samastipur, Bihar.	Abhinav Kumar	97982287 20	pintu28183@gmail .com
50	Bihar	Mohnia	Chandigarh Infosys Computer Institute	Near Power Grid, Bhabhua Road, Mohania, Kaimur Bihar.	Kyamudin Ansari	90312182 55	kyamu4969@rediff mail.com
51	Bihar	Nalanda	Prabhat Traders	Main Road Patna Anchal, Islampur, Distt-Nalanda, Bihar	Satyendera Kumar	98352719 67	prabhat.trading@y ahoo.co.in
52	Bihar	Araria	Shiv Shakti Enterprises	Bhagat Market, A.D.B. Chowk, Araria, Bihar	Ranjeet KR Bhagat	99340538 95	mmxshivshaktiarar ia@gmail.com
53	Bihar	Madhub ani	Sharma Electronic	Hasmi Market, Baba Bazar, Maszid Chowk, Madhubani, Bihar	Manoj Kumar Sharma	99392122 16	mksharmaelectroni c@gmail.com
54	Bihar	Jamui	Kajal Music Centre	Krishnapatti Chowk, Maharajganj, Jamui, Bihar.	Birendra Kumar Gupta	99310737 06	birendrakumargupt a08@rediffmail.co m
55	Bihar	Sitamar hi	Suraj Mobile & Repairing Centre	old Bus Stand, Sursund Road (Near J J	Sanjeev kumar	99732988 88	suraj.1max@gmail .com

				Hospital), Sitamarhi, Bihar			
56	Bihar	Munger	Shyam priya mobile.Com	Dindayal Chowk, Chowk Bazar Munger, Bihar	Prem Sharma	93048084 94	joshi.vinayak2@g mail.com
57	Bihar	Madhep ura	Mobiles Care	Main Road, opp.- ADB Bank, Madhepura, Bihar	Sanjay Kumar	99395242 04	sanjaymobilecare @gmail.com
58	Bihar	Auranga bad	Galaxy Mobile	Radha Complex, Near hotel J.K, M.G. Road, Aurangabad, Bihar	Birendra Kumar Singh	80026530 55	galaxymobile.com @gmail.com
59	Bihar	Motihari	MaaCommu nication	1st Floor, Nagar Palika Market, Room No.-4, Gandhi Choak, Meena Bazaar, Motihari, Bihar	Om Prakash Kumar	98018134 92	maacommunicatio nmotihari@gmail.c om
60	Bihar	Katihar	S.B.D Enterprises	C/O Meghani Pay Phone, Binodpur, opp.krisha Agency, Katihar	Mr. Sunil Kumar Meghani	94302293 00	meghanitelecom@ redmail.com
61	Bihar	Purnia	Vinayak Enterprises	Rajni Chowk, Bhatta Bazar, Purnia	MR.RAJA	96610351 41	lemonpurnia@redif fmail.com
62	Bihar	Patna	B.M. Trading	Shop No. 19, Kumar Tower, Boring Road Crossing,	Brajesh Kumar Singh	93349083 75	bmtrading@sify.co m
63	Bihar	Bhagalp ur	OM Mobiles	Laxmi Complex, Dr. R.P Road,	Mr. Om	97093595 20	ommobilesbgp@g mail.com

				Khaliffbag, Bhagalpur, Bihar			
64	Bihar	Ara	Baba Mobile Care	Pratap Palace, K.G. Road, Ara, Bihar	Binod Kumar Ojha	93867412 01	evergreenbinod@g mail.com
65	Bihar	Kishang anj	Albaksh Enterprises	Dey Market, Kishanganj, Bihar	ajay	93864827 00	mobileplaza2000 @rediffmail.com
66	Bihar	Muzaffa rpur	Sai Enterprises	Kacchi Sarai Road, Near Kanhauli Naka, Muzaffarpur.	Mr. Sanjeev Kumar	99315548 63	saienterprises501 @yahoo.co.in
67	Bihar	Darbhan ga	Tamana Enterprises	Shop No.-3, Shivam Complex, Kathalwadi, Darbhanga, Bihar	Parwez Ahmed	95463344 44	servdrb@gmail.co m
68	Bihar	Saharsa	Maa Pavitri Telecom	Bangow Road, Near Rupawati High School, Saharsa, Bihar	Lalan Kumar	99313735 88	lalan588@gmail.co m
69	Bihar	Buxar	Maa Mangla Enterprises	Bhojpur Khadi Gramodyog, Bari Bazar Road, Civil Lines, Buxar, Bihar	Stish Kumar	94314411 04	k.sat_9431441104 @rediffmail.com
70	Bihar	Chapra	I T Services	Behind Bank Of Broad ATM, Municipal Chowk, Chapra, Bihar	Prashant_srivast ava	93342587 01	itservices.chapra@ gmail.com
71	Bihar	Sasara m	Mobile Point	Laxmi Market, Gandhi Path,	Suresh Pd. Singh	94310758 85	suresh.prasad38@ gmail.com

				Sasaram, Bihar.			
72	Chhattisgarh	Korba	Ideal Mobile & Computer	Shop No.-2, Plot No.-781, Kamla Complex, Subhash Chowk, Opp.-Pushplata Gurdan, Niharika Korba	Dilip Kumar	9827494129	sudeshwardewan@yahoocom
73	Chhattisgarh	Bilaspur	Vasu Mobile Repairs	In Front of Shyam Talkies, Bilaspur (C.G.)	Laxmi Narayan Gupta	9826551593	lalumobile@yahoo.com
74	Chhattisgarh	Raipur	Vaishnavi International	Sakharam Moolchand Badha, Lohar Dukan Ke baju, Lalta Chowk, Jorapara, Raipur,	NITIN SHARMA	9424207574	vaishnavinternational@hotmail.com
75	Delhi	Delhi	Mobile Planet	19-20 second floor corner market malviya nagar new delhi	Shri Krishan	40529788	krishmohan74@yahoo.in
76	Gujarat	Himmat Nagar	Satyam Infotech	F-7, Ganesh Chambers, Civil Circle, S.T.Road, Himmat Nagar, Gujarat-383001	Kalpesh Kumar N. Chaudhary	9723927976	kalpeshchaudhary@yahoo.co.in
77	Gujarat	Jamnagar	Krishna Mobile Point	Limda Lane, Jamnagar, Gujarat	Ranipa Hiren	9173777770	hiren.patel32@yahoo.com
78	Gujarat	Surendranagar	Raj Infonet	G-1, Ratnasagar Apartment, Swastik Chowk, Surendranagar,	Rajesh R Khatadia	9898682974	rajinfonet@yahoo.com

				Gujarat			
79	Gujrat	Dahod	Digiphics Media	3-Ekta Complex, Opp.-Kotak Mahindra Bank, Near Canara Bank, Gadi Fort Road, Dahod, Gujrat	Bhavesh Patel	9687619401	digiphics@gmail.com
80	Gujrat	Vadodra	Mahim Corporation	GF-2, Rutukalash Complex, Tulsidham Char Rasta, Manjalpur, Vadodra, Gujrat	Rushabh Shah	9824333785	rishabhcommunications@yahoo.com
81	Gujrat	Junagadh	Ultra Mobile (Gaurav Enterprise)	Star Complex, Bus Stand Road, Junagadh, Gujarat	Mahendra Bhai	9925757275	ulnamobile2010@gmail.com
82	Gujrat	Anand	Jay Zulelal Telecom	24, Apna Bazar, Municipal Shopping Center, Near Ice Factory, Anand, Gujarat	Ramesh	9998783453	dipesh_thaker2002@yahoo.com
83	Gujrat	Ahmedabad	S K Services	ul-6 shivangi apartment, opp goyal intersity block-c, near drive in palora apartment, drive in, ahmedabad	Rachana K Patel	9904043477	sk.services24@gmail.com
84	Gujrat	Surat	Kash Peripherals	06/669, Lal Darwaja, Moti	Upendra rangrej	9824112347	upendra_rangrej@yahoo.com

				Sheri			
85	Gujrat	Godhra	Padmavati Communicat ion	GF-7, B N Chambers, Nr Police Headquarters, Godhra	Mr. Manas Maheshkumar Shah	94285453 05	godhra.service@g mail.com
86	Gujrat	Old Ahemda bad	Perfect Communicat ion	-4 ajit Vijay Complex ,Below City Point, Opp Nilkant Hotel,Ajit Mill Char Rasta Rakhial Ahmedabad-23	Rajesh K Shah	98250094 90	p_communication9 2@yahoo.co.in
87	Gujrat	Rajkot	K.K. Mobile Zone	Kaveri Complex, Shop No.-L-5, 20, NEw Jagnath, Yagnik Road, Rajkot, Gujrat.	Kaushik G. Shah	98986282 69	kk_cool2002@yah oo.com
88	Gujrat	Bhavna gar	MOBITEL SERVICES	GF-21, Business Centre, Rupam Chowak, Bhavnagar, Gujrat	Mihir Vajaria	98254535 55	mobitel_services@ yahoo.com
89	Haryana	Hissar	Mobile Palace	Shop No.-8, Basement,Red Cross Market, Hissar, Haryana	Narender Singh	90346910 06	mobilepalace@gm ail.com
90	Haryana	Rewari	S S R Care Center	Shop No.-437, Shopping Complex, Model Town, Rewari, Haryana	Sanjay Rastogi	98123011 13	sanjay_rustagi@ya hoo.com
91	Haryana	Hissar	Mobile	Shop No.-29, Jai	Amit Kumar	97283519	mobilegalaxy9@g

			Galaxy	Bhart Mandal Dharmshala, Opp.- Bajaj Sweets, Bhagat Singh Road, Hansi, Hissar, Haryana		80	mail.com
92	Haryana	Jind	Shivam Communicat ion	New Bus Stand Road, Opp.- PNB Bank, Safidon, Jind, Haryana	Puneet	98136216 21	shivam.communic ation621@gmail.c om
93	Haryana	Ambala Cantt	Bee Ess Aar Communicat ion	27th First loor, M.C. Market, Behind Nigar Cinema	Rajiv Gupta	17140062 29	bsr.amb@gmail.co m
94	Haryana	Yamuna Nagar	Cell Point	Shop No. 9, Isher Complex, Yamuna Nagar	Manoj kumar	98139232 39	cellpoint.dhiman95 @gmail.com
95	Haryana	Sonipat	Luxmi Telecom	Shop No.104,1st Floor, P.P.Tower, Nr.Subash Chowk,Atlas Road,Sonipat	Subhash Saini	92530633 50	luxmitelecom61@g mail.com
96	Haryana	Panipat	Parasnath Telecom	Shop No. 17, Gupta Complex, Bishan Swaroop Colony, Nr Prem Hospital	Mr Baldev Raj	18040003 60	paras.nath@hotmail il.com
97	Haryana	Jind	Saini Mobile Repair	Kundan Cinema, Safidon Road	Mr. Narender Saini	93158893 26	narendersaini40@ yahoo.com
98	Haryana	Sirsa	Service Zone	89, Bishna Market, Sirsa. (Haryana)	Praveen Kumar	92155080 08	service.sirsa@lem onmobiles.com
99	Haryana	Rohtak	Shree	8, Naryan	Mr. Sandeep	92158448	shreeservice.rohta

			Service Point	Complex, Civel Road	Deswal	46	k@lemonmobiles.com
100	Haryana	Kamal	Tara Tele& mobile	Shop no,-3&35Mela Ram School Market, Near Civil Hospital	Mr. Vivek Chaudhary	989615500	vivek_chaudhary2110@yahoo.com
101	Haryana	Bahadur agh	Baba Communicat ion	G1, Shyamji Complex, Bahadurgarh, Distt-Jajjhar, Haryana	Sumit	8053680837	sumit9918@yahoo .in
102	Haryana	Faridabad	Soni Telecom	Shop No-44, 1st Floor Neelam Chowk NIT, Faridabad, Haryana	Vinod Kumar	9312423999	sonitelecom.7@g mail.com
103	Haryana	Panipat	Radhe Krishan Communicat ion	1st Floor, 946/8, Upsatirs Vodafone Store, Near Railway Road, G. T. Road, Panipat, Haryana-132103	Sanjay Muwaal	9896708156	radhe.krishna@live.com
104	Haryana	Faridabad	Cosmos Communicat ion	Shop No.-67, Sector-29, Huda Market, Faridabad, Haryana	Vijay kumar	1294169759	cosmos.faridabad @gmail.com
105	Haryana	Kurukshetra	Kurukshetra Communicat ion	Uttam Market, Post Office Street, Mohan Nagar, Kurukshetra, Haryana	Manjit Singh	999116446	kkcr.comm@gmail.com

106	Haryana	Panchkula	Saini Mobile Care	Shop No.-32, Phase-1, Abheypur, Panchkula, Haryana	Mahesh Saini	9815738575	sainimobiles@rediffmail.com
107	Haryana	Palwal	I. Tech Mobile Repairing	Shekhpura Gali No.-2, Kitwari Chowk, Palwal, (Haryana)	Imran Khan	9813170786	imran00000786@yahoo.com
108	Haryana	Gurgaon	Ansh Communication	Near Nokia Care, opp. Air Force School, Delhi Road, Gurgaon, Haryana	Ajay Verma	9312180588	anshcommunication@gmail.com
109	Haryana	Bhiwani	Shri Krishna Telecom	Shop No.-4, 1st Floor Radhika Complex, Hansi Road, Bhiwani, Haryana	Deepak Madaan	9253392633	dev_madaan@rediffmail.com
110	HP	Baddi	Chawla Communication	Near Laj Dharm Kanta, Sai Road, Distt. Solan (H.P.)	Deepak Chawla	9857557555	deepakchawla.baddi@yahoo.in
111	HP	Shimla	Manoj Enterprises	CABIN NO. 109, PC CHAMBER, OPP. JODHA NIWAS PARKING, Shimla, Himachal Pradesh	sood ji	2651464	sudvicky@yahoo.com
112	HP	Kangra	Sharma Mobile	Gupt Ganga Road opp water	Anuj Sharma	9817036114	anujsharma_mobiles@yahoo.co.in

			Repairs	suply office, Kangara			
113	HP	Una	Brahma Electronics	mc market una	monoj	9318622045	brahma.electronics una@gmail.com
114	HP	Kullu	Cell Point	Near Jawala Mata Mandir, Shamshi	Sunil Khanna	9857061116	cellpoint.kullu@gmail.com
115	HP	SUNDE R NAGAR	Mobile Care	NH-21, Old Bus Stand, Sunder Nagar, Distt. Mandi	Mr. Naveen Kumar	9816580674	mobilecare111@gmail.com
116	HP	Solan	Rattan Mobile	New Bustand Shop No.14 Bye pass solan. Solan (H.P.)	Tilak Raj	9816507700	rattanmob@gmail.com
117	Jammu & Kashmir	Udhampur	Pee Kay Traders	Link Road, Near Forest Office, Udhampur, Jammu & Kashmir	Vishal Mahajan	9796032273	itbhai@gmail.com
118	Jammu & Kashmir	Kathua	Shanu Mobile Centre	Laxmi Market, Ward No.-5, Kathua.	Bishnat Kumar	9419150247	bk.elect@yahoo.com
119	Jammu & Kashmir	Rajouri	Ankur Mobiles	shop No.-3, Bus Stand, Rajouri, Jammu & Kashmir	Adishvar Mahajan	9622026861	www.adi_shvar@yahoo.com
120	Jammu & Kashmir	DODA CITY	Khan Studio	Old Bus Stand, Doda City, J&K-	Mr.Mansoor Khan	9906039303	tabishkhanzahoor@gmail.com
121	Jammu & Kashmir	Jammu	Gips Computers	House No. 74, Ambedkar Nagar ,New High Court	Mr.Shabbir Hussain	9419175721	shabbirshah69@yahoo.com

				Road ,Old Janipur, Jammu.			
122	Jammu & Kashmir	Srinagar	Smart Care	OPP. HDFC BANK, KARAN NAGAR, SRINAGAR	Mr MANZOOR HAMID BHAT	9018111102	smartservice06@yahoo.co.in
123	Jharkhand	Pakur	Mobile Hospital	Tin Bangla Main Road, Harindanga Bazar, Pakur, Jharkhand.	Suman Kumar Choudhary	930445465	himanshupkr@yahoo.co.in
124	Jharkhand	Dumka	Mobile Care(Dumka)	OPP-SADAR HOSPITAL,NEAR JHARKHAND MEDICAL,DUMKA, Jharkhand	Rajesh Kumar Prasad	9934665555	rajesh.dumka@gmail.com
125	Jharkhand	Bokaro Steel City	Mobile Clinic	C1-22D, City Centre, Sector-4/A, Bokaro Steel City, Jharkhand	Praveen Kumar	9853311131	mobileclinic@gmail.com
126	Jharkhand	Jamshe dpur	S.M. Communication	241, Akash Deep Plaza, Golmuri, Jamshedpur, Jharkhand.	Sumit Manchanda	9386483870	sm.communication107@gmail.com
127	Jharkhand	Palamu	Maa Mobiles	Jail Road, Jail Hata, Daltonganj, Palamu, Jharkhand	Navin Kumar Kashyap	9852797505	iwcc@rediffmail.com
128	Jharkhand	Ramgarh	Yeshe Care	New Bus Stand, Bijulia,Adarsh Nagar, Ramgarh	Subash Kumar Gupta	9693551483	yeshucommu.ramgarh@yahoo.in

				Cantt, Jharkhand			
129	Jharkhand	Giridih	Astha mobile Sewa	Astha Mobile Sewa,Buxidih Road,Near Sahara Office,Beside Indo German Computer Institute,Giridih, Jharkhand	Sanjay Kumar	97086097 41	asthamobile@gma il.com
130	Jharkhand	Ranchi	Cyber Communicat ion	Shop No. 54, Co-Operative Market Complex, Ashok Nagar.	Mr. Arun kumar & mukesh kumar	99313734 02	cybercomranchi@ gmail.com
131	Jharkhand	HAZARI BAGH	Digital Services	Plaza Market, Near Kallu Chowk, Pugmill	Mr.Shish Alam	93344864 65	shishalam@yahoo. com
132	Jharkhand	Dhanba d	GLOBAL AUTOMATI ON	NEAR MAIN GURUDWARA, OPPOSITE SUPER MARKET,ABOV E SERVO LUBE SHOPKATRAS ROAD, BANK MORE,DHANBA D,JHARKHAND	Subroto, Chandan	92343943 11	g.automation@live .com
133	Jharkhand	Deoghar	Nisha Telecom	Stasang Chowk, Opp. - Satsang College, Deogarh, Jharkhand	Ashok Kumar Barnwal	94709001 27	nishatelecom.deog har@gmail.com
134	Karnataka	Bangalo	Bhoomi	Do No-3&4,	Y. Nagendra	94495215	nagendrababu.y@

		re		Service Road, Remco Layout, Vijaya Nagar, Bangalore, Karnataka		42	gmail.com
135	Karnataka	Hassan	R T S Cell Point	Opp.-Science College, Salagame Road, Hassan, Karnataka	Sunil Kumar	99728349 97	rtscellpoint@gmail. com
136	Karnataka	Udupi	NAGASHRE E COMMUNIC ATIONS	Shop no-6, 1st, floor, Naraharicomple x, Kalsanka	Mr. MAHESH	92414620 68	nagashreecommu nications@gmail.c om
137	Karnataka	Mangalo re	Padmashree Enterprise	No.406, 2nd floor, Kunil centre, Hampankatta, Mangalore-1	Mr.Prabhakar shetty	90355600 06	mrpadamashree_e nt@rediffmail.com
138	Karnataka	Davang ere	N R Marketing	S.NO 27 CHETNA HOTEL ROADMUSLIM HOSTEL COMPLEXDAVA NGERE	Mr.N R Rafi	98860313 55	rafi_nr07@yahoo.c om
139	Karnataka	Hubli	Nayana Enterprise	G-28,Eureka Centre,Kopikkar road Hubli-20	Mr. Reddy	99456986 26	nayana.entp@gma il.com
140	Karnataka	Kolar	Chinmaya Mobile	Sharda talkies road, Bazar street, Kolar	Mr. Chandrasekar	99022272 71	chinmayemobiles @ymail.com
141	Karnataka	belgaum	I Brain Digital	Ist Floor, Unit#3, CTS No.-2840,	Prasad Pednekar	80504849 03	ibrainsupport@gm ail.com

			Gadget Solutions	Yash Palace, opp. Samadevi Temple, Sanyukta Maharastra Chowk, Khadebazar, Belagum.			
142	Karnataka	Mudhol	M.Gouse Mobile Service Centre	Anjuman Complex, Shop No.- 26 Near Bus stand, Mantur road, Pin-587313	Mr. Mahammadgouse	9663335556	mgouse.mumal@rediffmail.com
143	Karnataka	Shimoga	Cell Solutions	3rd Cross, Durgigudi, Park Extension. Shimoga	SREENAG.S.N	9844174143	svcellsolutions@yahoo.co.in
144	Karnataka	Karwar	Cell-N-Care	G-01, Shivdad Appartment, Opp. Maladevi Ground, Main Road Karwar.	Satish V.Bhatkal	9844061001	cellncare@gmail.com
145	Karnataka	Mysore	Canara Telecommunication	1225, 1st cross, Krishnamurthy Puram, Opp. Vjasaraj Mutt Mysore.	Mr. Rajesh	9845097967	canrajesh123@rediffmail.com
146	Karnataka	Bhatkal	Mobile World	MOBILE WORLD S H COMPLEX NAWAYATH COLONY Bhatkal	T S AZEEM	9845532167	tsazeem@hotmail.com

147	Karnataka	Bijapur	Mobile Solutions	Opp. Ram Mandir, Ram Mandir Road Bijapur	PRASHANT	9945622345	mobilesolutionsbjp@gmail.com
148	Karnataka	Bangalore	M S N COMMUNICATION	#32, Shop No.3, Arvind Complex, Beside Sanimahatma Temple (Near Banashankari Temple) Banashankari, Kanakapura Road, Bangalore	Jaffar Shariff	9342886000	jaffarshariff11@yahoo.com
149	Karnataka	Bangalore	S V Technology	#675, 1st Floor, 2nd Block, MKK Road, 20th Cross, Rajajinagar, Bangalore	BASAVARAJA M/Deepak	9986527244	sv.technologies@airtelmail.in
150	Karnataka	Bangalore	My Mobile Care	1st Floor, 286/1, Begur Road, Bommanahalli, Bangalore.	Praveen / Kumar	9341333512	mymobilecare.care@gmail.com
151	Karnataka	Udipi	P.S. Communications	Shop No.-37, 2nd Floor, Krishna Kripa Complex, Near K.S.R.T.C Bus Stand, Udupi, Karnataka	Kiran Kumar	9880129602	pstelecommunion007@gmail.com
152	Karnataka	Bellary	Chandrika Electronics	Shop No.-3, SLV Towers, Parvathi Nagar, Main	Tekkalakota Narasimhalu	8392267329	chandrika.bellary@rediffmail.com

				Road, Bellary,Karnatka			
153	Karnataka	Gulbarga	Sreenivasa Electronics	10-7/16/D1, NV Complex, SB Temple Road, Gulbarga,Karnataka	Srihari Rao Amberkar	9632233383	sreenivaselectronics@yahoo.co.in
154	Karnataka	Bangalore	Movil Servico	Office No.27, 1st Floor, Opp. KEB Office, 5th Main Ganganagara, Bangalore-32, Karnataka	Ananth	9535176767	movilservico@gmail.com
155	Kerala	Trivandrum	Global Mobile Masters	2nd Floor, Corporation Golden Jubilee Building, Opp. S.M.V.H.S. Over Bridge, Trivandrum, Kerala.	Arun Nath C.L.	9446967729	leesons2008@yahoo.com
156	Kerala	Calicut	MOBILE LAB	Darusalam Complex, L.G. Road	PRABEESH	9846143013	mobilelab.clt@gmail.com
157	Kerala	Thrissur	Celltech	5/1, N P Tower, C. Achuthammon Road, Poothole. P.O.-Thrissur, Kerala	Santom Kalloor	9349331113	celltech.tri@gmail.com
158	Kerala	Malappuram	Volga Communications	pattambi Road, P.O. Valanchery, Malappuram, Kerala	K P Neena	9846007440	volgacommunications@gmail.com

159	Kerala	Kannur	Yello Green Mobile Centre	Pallikulam, P.O. Chirakkal, Kannur, Kerala	Sree Kumar	9946161867	pk.sreekumar.knr@gmail.com
160	Kerala	cochin	Doctor Fone Services	1st floor, Prateeksha Buildings, Rajaji Road, Cochin	K.N.DANI	9846002563	doctorfone@yahoo.com
161	Kerala	Ernakulam	Wire Free World	Basement Floor, Penta Menaka, Marine Drive, Ernakulam, Kerala	M D Jaison	9995494545	wirefreeworld@in.com
162	Kerala	Cochin	Cell Dreams	Shop No. A-1, 1st Floor, GCDA Complex Marine Drive, Cochin, Kerala	Anoop	9846711110	celldreamskochin@gmail.com
163	Maharashtra	AHMED NAGAR	Abhi Services	B-4, Adarsh Sammrudhi Appt, Near Choupati Karanja	Mr. Anil B Apte	9373317179	abhianr@gmail.com
164	Maharashtra	Ghatkopar	Fraslin Tech Care Pvt. Ltd.	Shop No 56, Padma prabhu Bal. Sai nagar. Near Shreyas Cinema, L.B.S Marg Ghatkopar west	Maria Deva Rajan	226529743	fraslin.rajan@gmail.com
165	Maharashtra	Nagpur	Om Electronics	1st floor, Rajat Plaza - 1, Shop No:- 76, Opposite Union Bank, Ghat	Amit Sawarkar	9730077716	omelectronics.amit@gmail.com

				Road, Nagpur, Maharashtra			
166	Maharashtra	Wardha	Fiza Mobile	Rajkala Talkies Road, Opp. bank Of Maharashtra, Wardha, Maharashtra	Atik Shaikh	98907070 85	fizamobile@gmail. com
167	Maharashtra	Akola	Savita Enterprises	Opp. Mahanagar Palika, Kala Chabutra, Akola, Maharashtra	Rohan P Nichal	99602845 90	r_rohan2006@rediffmail.com
168	Maharashtra	Solapur	Nana Enterprises	D-12, Siddheshwar Market Yard, Hyderabad Road, Solapur, (Maharashtra).	Mujip Nabilal Nadaf	99753607 86	siddheshwar3338 @rediffmail.com
169	Maharashtra	Kandivali (W)	Bhagwati Mobile	Shop No.-10, Rock Avenue, Plot-D, Hindustan Naka, Opp. Joy Ice Cream, Kandivali (W), Mumbai (Maharashtra).	Pradeep Agarwal	98929782 10	pradeep_8090@yahoo.com
170	Maharashtra	Beed	Rajlaxmi Mobile Shopee	In Front Of Sangali Bank, Stadium Road, Beed, Maharashtra.	Popat Kundlik Shinde	94213243 33	rajlaxmimobile333 @gmail.com
171	Maharashtra	Karanja (Lad)	Mobile Doctor	Saraf Line, Karanja (Lad), Distt. Washim.	Manish N. Gulkari	98504077 74	doctormng@rediffmail.com

				Maharashtra.			
172	Maharashtra	Jalna	SMS Mobile & Computers Sales & Service	Shop No.-10, B-1 Wing, B.R. Jindal Super Market, M G Road, Jalna, Maharashtra	Manohar Punjaram Gawai	9764308110	manoharsms@yahoo.co.in
173	Maharashtra	Amravati	Tirupati Mobile Care	In Front of Ajmera Decoration, Gandhi Chowk, Amravati, Maharashtra	Gaurav S Pande	7875139899	gaurav24pande@rediffmail.com
174	Maharashtra	Gondiya	Alfa Systems	Sarafa Line Deshbandhu Ward, Gondiya, Maharashtra.	Anil G Bhojwani	9822200272	alfasystemgondia@gmail.com
175	Maharashtra	Mumbai	Ideal Enterprise	Shop No.1, Near Welecome Hotel, Dattapada Cross Road No.-1, Borivali East, Mumbai, Maharashtra	Asif A Baig	9867425898	ideal_enterprise@indiatimes.com
176	Maharashtra	Panvel	Sai Telecom	Shop No.148, Building No.1/2, Municipal Complex Mall, Near Shivaji Chowk, Old Panvel(MH)	Mr. Pardeepkumar Ishwar Mote	9967965370	galaxy.ente@gmail.com,saitelcompnvel@gmail.com
177	Maharashtra	LATUR	Krisna Computer	NEW GANDHI MARKET COMPLEX	Mr. Manoj b. Tiwari	996024627	kcmlatur@yahoo.com

				NO.112, SHO NO. 180, BESIDE INDIRA MAHILA BANK, LATUR			
178	Maharashtra	Jalgaon	Limra Mobiles	45 A, E-Wing, First Floor, Golani Market, Jalgaon.	Mr. Wasim Sayyed	93701100 92	wasim.sayyed@yahoo.co.in
179	Maharashtra	Kalyan	The Skylark Associates	Shop No. 4, Suha Apartment Opp. Reliance Fresh & Attitude Furniture, Syndicate Murbad Road, Kalyan West, Kalyan	Mr. Ejazuddin Qamruddin Sayed	93207757 57	skylark.lemon@gmail.com
180	Maharashtra	Nasik	Servings Enterprises	Shop No. 8, Ground Floor, Kapote - Meher, Renuka Nagar, Wadala Naka Near Dearka	Mazhar Ahmed	93709694 12	servings.nasik@gmail.com
181	Maharashtra	Aurangabad	Unique Telematics	Shop No. 108/B, Tapadiya Super Market, Behind Sajawat Handlooms, Nirala Bazaar	mr mahesh	93252103 64	unique.aur@rediffmail.com
182	Maharashtra	Ahmednagar	Sagar Mobile Shopee	Bazartal, Mhasobha Gate, Karjat, Distt- Ahmednagar, Maharashtra	Dilip N Dhree	99708492 38	aegarmobileshopi@rediffmail.com

183	Maharashtra	Pune	Reliable Enterprises	A-27, Jai Ganesh Vision, AkurdiPune	Linu Thomas	9028077345	reliableent9@gmail.com
184	Maharashtra	Pune	Viraj Communication & Gift Articals	Shukarawar Peth, Shivaji road, Near Vanraj Mandal, pune , Maharashtra.	Sandeep Mate/Raju	9890139351	virajcommunications@gmail.com
185	Maharashtra	Satara	Yaadein Communication	Shop 2 Govind Arcade, Near Old RTO Office, Satara (Maharashtra)	Sandeep Maruthi Shirke	9021740791	ms.satara@rediffmail.com
186	Maharashtra	Nanded	Padmaja Mobiles	303-305, 1st Floor, Shukla Complex, ITI , Nanded, Maharashtra	Vaishali Staish Kandharkar	2462255566	padmaja.mobiles@gmail.com
187	Maharashtra	Sangli	Omkar Communication	1358, Risala Road, Near Divekar Hospital, Khan Bhag, Sangli, Maharashtra	Vitthal Magdum	9270059858	omkartelecell@gmail.com
188	Maharashtra	Kolhapur	Sukir Mobiles	415/1A, E Kevis Plaza Near Usha Talkies, station Road, Kolhapur, Maharashtra	Sukir Bakare	9890125840	sukirmobiles@yahoo.in
189	Maharashtra	Chandrapur	Shiva Mobile Shoppee	ramnagar, Sindhi Colony, Chandrapur, Maharashtra	Bharti Talreja	9370350092	mah.talreja@gmail.com

190	Maharashtra	Yavatmal	Sajal Enterprises	R N Telecom, Jaihind Chowk, Suyash Complex, Hanuman Akkhada Road, Yavatmal, Maharashtra	Hatik Ahmed Khan	9860648797	sajal_enter123@yahoo.co.in
191	Maharashtra	Buldana	Shravani Services	Gaware Complex, Opp. Bus Stand D.P. Road, Chikhli, Maharashtra	Pramod	9372506179	pramoddeshmukh@rediffmail.com
192	Manipur	Kakching Bazar	Ibohal Enterprises	Kakching Bazar, Manipur	Ksh Birla Singh	9774333030	birla012009@gmail.com
193	Manipur	Thoubal Awang Leikai	Glamour World	Thoubal Awang Leikai, Manipur	S Swamendrajit	9862088127	glamourworld@gmail.com
194	Manipur	Imphal	I R Enterprises	Paona Bazar, Imphal-01	Mr. Yambem Roshan Singh	9206043370	ir.imphal@lemonmobiles.com
195	Meghalaya	Shillong	San Cellular Concept	Q.E.L. Arcade, Laitumkhrach, Opp.-Post Office, Shillong, Meghalaya	Pheelangam Shimery	9862511101	samsungshillong@gmail.com
196	Meghalaya	Shillong	S N Enterprise	Jail Road, Opposite-P. K. T.V. House, Shillong, Meghalaya	Laxmi Nath	9402134788	rahuldas198@gmail.com
197	MP	Sagar	Neeta Computers	Hanuman Mandir Gali-5, Civil Lines	Ramesh gupta	9329414144	neetacomputers@gmail.com
198	MP	Jabalpur	Diwakar	G-14, Javanti	Preeti & Seema	93000324	diwakar_jabalpur

			Agencies	Complex, Marhatal		47	@yahoo.com
199	MP	Ujjain	Q S A Electronics	Amar Singh Marg, Mumgi Nurshing Home Ki gali, Opp. Dr. Neelam Charles N.H. Ujjain, MP.	Saiuddin	98930717 72	saifyqsa@gmail.co m
200	MP	Khargon e	Shri Sai Communicat ion	A-35, Radha Vallabh Market, Khargone, Madhya Pradesh	Manish Gupta	99771266 99	manish_rgupta@y ahoo.com
201	MP	Vidisha	Raj Mobile World	3, Swarankar Colony, Near Vijay Talkiz, Vidisha, Indore, Madhya Pradesh	Akshay Raj Johari	98932400 82	rajmobileworld@liv e.com
202	MP	Morena	S S Mobiles	In front of Nagar Palika, Near Collector Bunglo, Rathi Complex, MS Road, Morena, M.P.	Deepak Gupta	98931518 15	deepak20678@ya hoo.in
203	MP	Rajgarh	Khushi Traders	New Bus Stand, Naka No.-3, Rajgarh, Madhya Pradesh	Rani Morya	98268253 88	bhupesh_morya@ yahoo.co.in
204	MP	ratlam	Neeraj Telecom	15,16- Model Market, Aaram Lodge, Naharpura, Ratlam, Madhya Pradesh	Neeraj Vaghela	98930412 41	neerajtelecomratla m@yahoo.co.in

205	MP	Bhopal	Poojya Enterprises	UG-2, Radhye Krishna Complex, M.P. Nagar, Zone -II, Bhopal	ASHISH DWIVEDI	4226754	poojyaenterprises@gmail.com
206	MP	Indore	Ayushi Electronics	M-115, Yashwant Plaza, Opp. Railway Station, Indore, Madhya Pradesh	Madhu Dwivedi	9826104249	vestarindore@yahoo.com
207	MP	Dewas	New Taj Electronics	4, New Market, Moti Bunglow Main Road, Dewas, Madhya Pradesh	Shabbir, Jabbir	9893064949	tajdws@gmail.com
208	MP	Gwalior	Sonu Mobile & Repairing Center	126, Mayur Market Thatipur Morar	Ashish Gupta	9301253659	seth_anurag@hotmail.com
209	MP	Indore	R C Services	UG-38, Silver Arcade, 56 Shope, Indore, Madhya Pradesh	Ram Chandra Choudhary	9893148101	ram_pco@sifymail.com
210	Nagaland	Dimapur	Space Net	Cross Road Galleria Complex, M.P. Road	Mr. Sandeep Sharma	9612303582	devsharma72@rocketmail.com
211	Orissa	Anogul	Swastik Mobile	Hatatota, Talcher, Near Dental Clinic, Distt.-Anogul, Orissa	Sujit Gamaik	9776494999	sujit.1810@rediffmail.com
212	Orissa	Bhubaneswar	Space Telecom	Plot NO - 27Bapuji NagarInfront of	Swati Mishra	9439726057	space.telc@gmail.com

				Govind ComplexBhubaneswar,Orissa			
213	Orissa	Keonjhar	Gayatree Enterpriser	House of Chandra Mohan Behera,Plot no-273 Village-Kasipur, Po-Keonjhargar, Ward no-9,Near-Income-taxofficeDistt.-Keonjhar, Orissa	Chakradhara Behera	9583509495	ettchandan@gmail.com
214	Orissa	Sambalpur	Mobile Care	At-G.M.College Chowk, P.o./Dist-Sambalpur, Orissa	Saroj Kumar Sai	9777469999	mobilekr4@gmail.com
215	Orissa	Bhadrak	Babool Mobile	Near Radhika Lady Park, College Road, Jaganathpur, Bhadrak, Orissa	Susant Das	9937072562	babool.mobile@gmail.com
216	Orissa	Nayagarh	Tathastu Infotech	College Road, Naygarh, Orissa.	Ramani Ranjan Jena	9937075420	adoninfotex@gmail.com
217	Orissa	Dhenkanal	Sony Communication	Ganesh Bazar, Near Telephone Bhawan, D.K.Road Dhenkanal, Orissa	Kabita Panda	9437426042	sonycommunicationdkl@gmail.com
218	Orissa	Kantabanjhi	Mobile Zone	Main Road, Kantabanji, Orissa	Adesh Agrawal	9937074636	adesh4169@rediffmail.com
219	Orissa	Jatni	M M	Masjid Market	Nilroj Ranjan	67424900	mmdistributors201

			Distibutors	Complex, Ramachandrapu r Bazar, Jatni, Orissa	Mishra	45	0@gmail.com
220	Orissa	Bhuban eswar	Smart Services	105, Post Office Lane, Bapujinagar, Bhubaneswar, Orissa	Pradeep Kumar Jena	98530611 33	smartservices_ps @yahoo.co.in
221	Orissa	Balaso re	URA Mobiles	Station Road, Near City Lodge	Mr.Uttam Pal	97779813 00	uramobile2@yaho o.com
222	Orissa	Cuttak	Channel - 4	Singh Plaza Dolamundai, Cuttak	Mr.Murli Dhar Nayak	67123267 97	channel.ctc@gmail .com
223	Orissa	Rourkel a	Black Buck Digital Services	1st floor, vedbigyan bhawan, shaktinagar	Biswajit Dash	98615757 07	blackbuckrkl@gma il.com
224	Orissa	Berham pur	Orissa Enterprises	Park Street, Behrampur- 2	Mr.Anand	90401060 10	orissa.enterprises @gmail.com
225	Orissa	Ryagad a	SREEVANI TRADERS	Hotel Kapilas lane, Opp ADB(SBI) New colony Ryagada	Mr.K.Mitra Gupta	94377210 71	mitragupta@hotmail il.com
226	Orissa	Bhuban eswar	M Care	PLOT NO-94, SAHID NAGAR, IMFA PARK EAST GATE, BHUBANESWA R, KHURDA, ORISSA	Murlidhar Nayak	67425480 66	mcare.bbsr@gmail .com
227	Orissa	Dhenka nal	RT Mobile	Mahabir bazar, D K Road, Dhenkanal,	Mr.Sangram Kumar panda	94371878 8	sangramkumarpanda@yahoo.com

				Orrisa -			
228	Orissa	Bolabgir	GSM Solutions	Stall No.-14, Kalamandal Road, Bolangir, Orissa.	Nisis Patra	9776323834	rohitsenisis@yahoo.co.in
229	Punjab	Batala	Verma Telecom	Near SDM Court, DBN Road, Batala, Punjab	Dhreej Verma	9914460261	vermatelecom261@rediffmail.com
230	Punjab	Ludhiana	Sai Ji Telecom	shope no.4 pearl place ghumar mandi	kamal sony	1615020310	saijitelecom@yahoo.com
231	Punjab	Chandigarh	Alpha Infotech	No. 2068/1Burail, Sector-45A, Chandigarh	Mr. Yashpal Singh	9888290217	yashpal.singh34@gmail.com
232	Punjab	Batinda	13 Balaji Computers	d-10 b.k super market opposite santoshi mata mandir back side dhobi bazar	Mr. Dinesh Kumar	9464980013	daksh1313@gmail.com
233	Punjab	Samana	L.S.Mobile Repair	Post Office Road Samana	Mr. Gurpreet Singh	9888316926	idea_idea56565@yahoo.com
234	Punjab	Amritsar	GSM Services	1-B, Liberty? Market, Opp. Railway Link Road.	nitin	2560540	gsm-services-amritsar@gmail.com
235	Punjab	Jalandhar	Shree Communication	126, Ashok Nagar, Basti Sheikh Road	batra	9814265656	batra_aakash@yahoo.com
236	Punjab	Dinanagar	Surya Enterprises	Brahman Sabha Mandir Road, Dinanagar	raj kumar	9876997954	suryaenterprises18@gmail.com

237	Punjab	Chandigarh	Global Teletec	SCO 272, 2nd Floor Sector-32 D, Chandigarh, Punjab	TK SHARMA	5088604	mstradelink@rediffmail.com
238	Punjab	Patila	G. M. Telecom	Shop No.-7, New Cloth Market, Near Share Pwnjel Market, Patila, Punjab	Mandeep Singh	9814505020	mandy80104@yahoo.co.in
239	Punjab	Rajpura	Parveen Electronics	House No.-1756/2-3, Mahabir Mandir Road, Rajpura, Punjab	Mr. Parveen Electronics	9815482310	par_electronics@yahoo.com
240	Punjab	Phagwara	R K Mobile	Friends Colony, Opp-JCT School, Pagwara, Punjab	Rakesh Kumar	9814430959	rakesh_2050b@yahoo.com
241	Punjab	Ferozepur	Shivam Mobile Care	32, Red Cross Market, The Mall, Ferozepur, Punjab	Vivek	9914700053	mobilecarefzr@gmail.com
242	Rajasthan	Karauli	Lahas Telecom Center	Damp Road, Hindaun City, Diss.-Karauli, Rajasthan	Bhagwansy Agarwal	9828238988	lahastelecom@yahoo.com
243	Rajasthan	Udaipur	Panesar Telecom	20, ANand Plaza, Ayad Udaipur, Rajasthan.	Gurpreet Singh Panesar	9828166145	lemon.gurpreet@gmail.com
244	Rajasthan	Sri Gangan	Aadhunik Care House	12 Market Complex, Purani	Mahaveer Prasad Jain	9461360400	aadhunikcare@gmail.com

		agar		Subzi Mandi, Birbal Chowk, Sri Ganaanagr.			
245	Rajasthan	sikar	Gem Mobiles	Bhati Mension, Bajaj Road, Sikar, Rajasthan	A. Kaleem Khan	98292136 56	kalimkhan.skr@gmail.com
246	Rajasthan	Sawai Madhopur	Siddhi Vinayak Telecom	Shop No.-63, Shiva Kapda Market, Bazariya,Sawai Madhopur, Rajasthan	Rashid Mohd	94611737 86	rashid.saharamobile786@gmail.com
247	Rajasthan	Pali	Rajveer Teleecare	Near Manthan Cinema, Naga Baba Bagechi, Pali- Marwar, Rajasthan	Kuldeep Singh	92144793 33	rajveer.teleecare@gmail.com
248	Rajasthan	Barmer	Krishna Mobiles	G-11, Palika Bazar, Station Road, Barmer, Rajasthan	Nitesh Kumar	96605582 61	krishnamobiles2010@yahoo.com
249	Rajasthan	Alwar	Guru Vallabh Care Center	Gulab Bagh Road, Opp.-Agarwal Dharamshala, Near Bus Stand, Alwar, Rajasthan	Ankush Jain	81043989 97	guruvalabbh_alwar@rediffmail.com
250	Rajasthan	Udaipur	Multi Care	Opp.- Udaipur Hospital, Gulab Bag Road, Udaipur, Rajasthan	Harsh Raj Gupta	92510755 51	multicare2011@gmail.com
251	Rajasthan	Jaipur	Bhumika Electronics	116-F,Basement Ganpati	Madan Murari Sharma	98285031 60	bhmikaelec@sify.com

				plaza,M.I Road,Jaipur,Raj asthan			
252	Rajasthan	Baran	Anshul Services	Inside Old Telephone Exchange, Hospital Road, Baran, Rajasthan	Suresh Gupta	94143090 30	anshulmobilebaran @yahoo.com
253	Rajasthan	Hanuma ngarh	Daksh Communicat ion	Near poice Staion, Nohar, Distt- Hanumangarh, Rajasthan	Dinkar	97857035 81	dakshcommunicatio n.nohar@gmail.co m
254	Rajasthan	Bikaner	Dollphin Mobiles	Hera Lal Mall, opp.-Railway Station, Bikaner, Rajasthan	Hemchand Nagal	92145215 18	hemchandnagal07 @gmail.com
255	Rajasthan	Dausa	Akash Telecommuni cation	2nd Floor, Bus Stand, Lalsot, Distt.- Dausa, Rajasthan	Yogendra Kumar	98751510 00	yogesh_tally@redif fmail.com
256	Rajasthan	Tonk	Rajat Communicat ion	Clock Tower, Tonk, Rajasthan	Rishab Tikkiwal	80585944 44	rtikkiwal123@rediff mail.com
257	Rajasthan	Ajmer	Aadinath Telecom	Nr. Dr. Chandra Narayan, Ghee Mandi, Naya Bazar, Ajmer	Mr. Kamal Jain	99829512 17	rajjain_kamal@yah oo.co.in
258	Rajasthan	Ganagp ur	Akash Enterprises	Opp. Panchayat Bhawan Dist. Sawai Madhupur	Mr Yogesh Agerwal	98751510 00	yogesh_tally@redif fmail.com
259	Rajasthan	Jaipur	Galaxmial Telecom	G-43 Ganpati Plaza, A Block,	Mr. Ramesh Verma	90014630 25	suneel.verma29@ gmail.com

				M I Road			
260	Rajasthan	Kota	Gulati Communicat ion	Shop-7,Plot No 1-D-1, Sheela Choudhary Road, SFS Colony,Talwandi	saurabh	98293596 20	gulatiinfotec@yaho o.com
261	Rajasthan	Jhunju nu	India Cell Service	Opp. Prabhat Cinema Station Road, Street Kabadi Market	Mr. Mo. Yunush	98296107 30	indiacellphone@ya hoo.com
262	Rajasthan	Jodhpur	Ram Sanehi Trading Co.	Inside Narshingh Bhawan,Opp.Ya sh Yamaha Showroom,Behi nd Shiv mandir, Gol Building circle, Sardharpura,Jod hpur	Bhupendra bansal	92148977 03	ram.jodhpur@lemo nmobiles.com
263	Rajasthan	Bharatp ur	S.D. Mobile Center	Shop No.-5, K.B. Plaza, Near Central Bank of India in front of Laxman Mandir, Bharatpur (Rajasthan)-	Jitender bansal	93516235 26	maxx.bharatpur@y aahoo.com
264	Rajasthan	BIKANE R	SHREE KHETESHW AR TELECOM	Shop no.-208,1st floor ganpati plaza,K.E.M. Road ,Bikaner, Rajasthan	Ashok Singh	92147736 10	kheteshwar.teleco m@gmail.com
265	Rajasthan	hanuma ngarh	Shree Shyam	opp lakhotia chakki durga	narander wadhwa	96490020 00	narander_wadhwa @yahoo.com

			Communication World	mandir road hanumangarh, Rajasthan			
266	Rajasthan	BARAN	Shreenidhi Mobile	Dalla Ji Ki Dharam salla ke niche,HOSPITAL ROAD BARAN (RAJASTHAN)	gaurav	9929690003	gauravgargbaran@gmail.com
267	Rajasthan	Bundi	Shri Vinayak Associates	Shri Om Complex, New Dhanmandi Road	Bhanu Sharma	9660956789	bhanusirji@yahoo.in
268	Rajasthan	DHOLPUR	TIRUPATI TELECOM	SHOP NO.-12 BHAGWATI MARKET NEAR JAGAN TALKIES JAGAN TIRAHA DHOLPUR	Mr. Mohsin Khan/Mr.Devendra Parmar	9351623526	tirupati.Dho@lgmobiles.com
269	Rajasthan	Sawai Madhopur	Rahul Enterprises	Kachari Road, Gangapur City, Distt. - Sawai Madhopur, Rajasthan	Rahul Aggarwal	9828268666	rahulenterprises77@yahoo.com
270	Rajasthan	Tonk	Softcom Mobile Point	Nazar Bazar Road, Tonk, Rajasthan	Syed Eaize Shah	9214736304	fizesshah@yahoo.com
271	Rajasthan	Bhilwara	Software World	Bazar No.-2, Behind Police Control Room, Bhilwara, Rajasthan	Parkesh	9950937505	nikiljain@rediffmail.com
272	Tamilnadu	Namakkal	A S M Cell phone	13, Theppakkulam	M. Abu Raj Ali	9865346147	asmcell@hotmail.com

			Service	Complex, Near Old Bus Stand, Tirchengode, Namakkal, TamilNadu			
273	Tamilnadu	Salem	Spiks	Dr Arumugam Complex, Salem Mani Road, Attur Tk, Salem, Tamil Nadu	A.Anbalagan	9364233777	lemon.attur@gmail.com
274	Tamilnadu	Tiruvan namalai	Harish Mobiles	No.-25-B, K.S. Complex, Thiruvoodal Street, Tiruvannamalai-1, Tamilnadu	M Harish	9790150076	spicetvmalai@gmail.com
275	Tamilnadu	Tuticorin	The Chennai Cell	46/12, Pearl Plaza, vasanth & Co. Complex, (Back Side), Thevarapuram Road, Tuticorin Road, Tamilnadu	M. Anbalagan	9976181633	thechennaicelltuty@gmail.com
276	Tamilnadu	Madurai	Mobile Gallery	137A, 1st Floor, North Veli, Opposite Sulta Hotel, MADurai, Tamilnadu.	M.A. Ahamed Sultan	9894621292	mobile_gallery2004@yahoo.com
277	Tamilnadu	Dharma puri	Sri Vishnu Agency	e9.suresh electricals complex.3rd floor. Rajagopal gounder street.Dharmapu	Mr.Sugavaneswaran	9080569002	suganlei@gmail.com

				ri.636709			
278	Tamilnadu	Chennai	Systematic Communication	Old NO.36, New No.30, Azimulk 1st street, Thousandlight, Chennai-600006	Mr.Venkatesh	9840567556	systematic@airtelmail.in
279	Tamilnadu	Salem	ALLIED ELECTRONICS	266C, Advaida Ashram Roads, Near New Bus Stand	Mr. Thomas Jacob	9842446067	alliedtms@gmail.com
280	Tamilnadu	Tirupur	Venus Institute of Cell Phone Technology	284, Kumaran Plaza, Kumaran Road, Tirupur.	Kingslin Johnson	944234001	victking40001@gmail.com
281	Tamilnadu	Vellore	South India Solutions	V.A.G.Complex (Near Palace Cafe) 27, Katpadi Road, Vellore Pin-632004	Mr. Athaulla	9715552627	vellore.lemon@gmail.com
282	Tamilnadu	Coimbatore	SRK Micro Mobile	Shop No.37 Century Tower, No.638 Sathy Main Road, Near GP Hospital, Gandhipuram	P.Rajkumar	934552690	p.rajkumar245@gmail.com
283	Tamilnadu	Theni	Kumar Mobile Care	D.NO.51, SUBBAN STREET, Theni-625531. (Tamilnadu).	kumar	9842349081	lemon_theni@yahoo.com
284	Tamilnadu	Pondicherry	Sri Sai Enterprises	83, Thennansalai Road, Sanjay	bhanu sharma	9994918693	srisaenterprises2009@ymail.com

				Ghandhi Nagar, Pondicherry-13,			
285	Tamilnadu	Triuchir appalli	Gayathri Communicat ions	Shop no.-5, 1st Floor, Shara Complex(opp.- Ramba Theatre), Karur Bypass Road,Triuchirap palli, Tamilnadu	S. Marimuthu	99948388 87	gayathricommunic ations@gmail.com,
286	Tamilnadu	Villupur am	Shri Karpakavina yagar Agencies	Shri Ammam Enterprises No.-6(C-12), Rahmath Shopping Complex, Trichy Main Road, Villupuram, Tamilnadu	K Ganesh	99941622 61	k-ganesh2000@ya hoo.com
287	Tamilnadu	Tirunelgl i Junction ,	Sri Shardha Electronics	66 A/9, babuji Nagar, Madurai road, Tirunelgli Junction, Tamilnadu	S. Gurusrinivassan	94431310 62	guru.srinivass@g mail.com
288	Tamilnadu	BHAVA NI	K.K. Swamy Agencies	No. 400/A, Mettur Main Road, Bhavani	K.K.SAMY	96295766 66	kksamy007@ymail .com
289	Tamilnadu	Tamilna du	Mobile India	9,GST ROAD, Tambaram Sanatorium, Opp. To fire Station, Chennai, Tamilnadu	T.RAVI	95660736 03	mobileindia2008@ rediffmail.com
290	Tripura	Agarlath	J A K	2nd Floor,	Babul Deb	94361221	jakenterprise.agt@

			Enterprises	Rampari Mansion, Datta Super Market, Sakunlata Road, Agarlath, Tripura		85	rediffmail.com
291	UPE	Mirzapur	Swastik Telecom	Imarti Road	Mr. Shishir Agrawal	9415232277	swastik.mirzapur@lemonmobiles.com
292	UPE	Banda	Max Computer & Mobile Services	Jal Sansthan Road, Gular Naka Banda, Uttar Pradesh.	Alok Tiwari	9335877349	alok_chp@yahoo.co.in
293	UPE	Bahraich	Khatu Shyam and Company	Laxmi Plaza, Near Chawani Chauraha, Opp. Allahabad Bank ATM, Bahraich	Gopal	9984184166	khatu.bahraich@lemonmobiles.com
294	UPE	Gorakhpur	M.M Communications	C/o ICON TS, 4-Jai Joshi Complex, Medical College Road, Basharatpur	Ashwani Kumar	9336422769	mm.gorakhpur@lemonmobiles.com
295	UPE	Ghazipur	Aditya Mobile World	Lal Darwaza, Near Shiv Temple, Distt. - Ghazipur, Uttar Pradesh	Aditya Kumar	9415887413	chaurasiaaditya1@gmail.com
296	UPE	Basti	Royal Enterprises	Shop No- 12, Nagar Palik Market, Company Bag, Basti , Uttar Pradesh	Rajesh Singh/Deepak Kumar	9838771562	rajeshsingh.basti@rediffmail.com
297	UPE	Unnao	Avijit	251 ,A.B. Nagar	Mr.Vishnu	93353532	avijit.unnao@lemo

			Infotech	Opp.Collector ganj Unnao - 209801	Pandey	22	nmobiles.com
298	UPE	Allahab ad	B.R.B.M. Teleservices	30,V.N.Marg (City Hotel Building) Allahabad-21100 3	Girish Kumar Agrawal	0532-2401 5	brbm.allahabad@l emonmobiles.com
299	UPE	Chitrako ot karwi	Bansal Mobile Sansar	Kali Devi Chauraha, Purani Bazar Karwi	Sandeep Bansal	93358690 00	bansalmobile.chitr akoot@lemonmobi les.com
300	UPE	Faizaba d	Care Electronics	Shop No. 3, Build. No. 5/11/114, Hamdani Kothi,Pargana Haveli, Reed Ganj.	Mr. Naval K. Gupta	96969859 77	care.faizabad@le monmobiles.com
301	UPE	Kanpur	Carewell IT Services Pvt. Ltd	Govind Nagar, Opp. Natraj Cinema	Mr.Amit Asthana	51232602 61	carewell.kanpur@l emonmobiles.com
302	UPE	Maudah a	Chotu Mobile Center	Rashmi Petrol Pump, Maudaha,	Mr. Radha Krishna Gupta	96160961 60	chotu.hamir@lemo nmobiles.com
303	UPE	Kushina gar	Ganpati Enterprises	Gandhi Nagar, Near Head post Office Padrauna, Kushinagar, Uttar Pradesh	Rajeev kumar Mishra	98382762 75	ganpat_enterprise s@rediffmail.com
304	UPE	Etawah	Front Line Computers	132, Civil Lines, Pakka Talab Chauraha, Pin-206001	Mr. Puneet Kaushik/Mr.R.R. Tiwari	92194041 94	front.etawah@lem onmobiles.com

305	UPE	Farrukh abad	Gupta National Radios	2/74, Ghumna Bazar, Farrukhabad	Basant Kr.Gupta	98386483 03	visheshtelecom@i n.com
306	UPE	Kanpur	K Mobile	FFD-12 3rd Floor, Somdutt Plaza, Kanpur	Mr. Sanjeev Singh	96700376 32	bablu_kumar946@ yahoo.com
307	UPE	Raebare li	Karuna Enterprises	Shop No.-3, Bajpai Market, Malik Mau Road, Beli Ganj	Vikas Jain	97924000 05	karuna.raebareli@l emonmobiles.com
308	UPE	Salemp ur	Sai Service Station	Statio Road. Salempur, Uatter pradesh	Santosh	99367025 00	saisalempur@yah oo.com
309	UPE	Hamirpu r	Kaushal Mobile Shop	Paliwal Complex, King Road, Hamirpur	Anurag Tiwari	98386300 43	kaushal.hamirpur @lemonmobiles.co m
310	UPE	Sonebh adra	MAA Duiza Telecom	Aryan Samaj Chauraha	Ved Prakesh	94554642 26	chintu2552@yaho o.co.in
311	UPE	Varanas i	MAA DURGA ELECTRON ICS	C 26/1 A,GANESH BAGH,KABIR ROAD,NEAR PETROL PUMP, VARANASI. PIN:221001	MS REKHA R SRIVASTAVA	98072078 11	maa.varanasi@le monmobiles.com
312	UPE	Sultan Pur	Mobile Place	Shop no.6, Super market Sultan pur-228001	Mr. Pawan Pandey	98386247 13	mobile.sult@lemon mobiles.com
313	UPE	Jhansi	Plus Computer Repairing Centre	Ground Flour372/a,civil line gwalior roadnear babu lal ka	Sujit Kumar	94539419 65	pluscomputer.jhasi @lemonmobiles.co m

314	UPE	Sitapur	Shagun Mobile	karkhanaJhansi shop no. 1 jama masjid alamnagar sitapur	santosh prajapati	98399431 31	shagun.sitapur@le monmobiles.com
315	UPE	Hardoi	Shipra Electrical & Appliances	RD Plaza Shop No.6 Near Agrawal Dhramsala Circular Road	Mr. Gaurav Gupta	98389083 32	shipra.hardoi@lem onmobiles.com
316	UPE	Gorakhp ur	Shivam Infotech World	PT.Harihar PD. Dubay Marg Betiahata, Gorakhpur	Mr. VISHAL PANDEY	93364153 12	iconinfosys@rediff mail.com
317	UPE	Varanas i	Vishal Communicat ion	S. 21/112,A-1 Englishiya Line, Varanasi(UP)	Mr. Vishal	98392594 4	vishal.var@lemon mobiles.com
318	UPE	Ballia	Harshit Electronics	Brighu Ashram, Near Purranchal Cinema, Ballia, Uttar Pradesh.	Desh Deepak Gupta	93057501 10	ddg74@yahoo.co m
319	UPE	Ambedk ar Nagar	Satyam Communicat ion	Lohiya Chowk, Shahzadpur, Akbarpur, Ambedkar Nagar, Uttar Pradesh.	Satyam Mehrotra	99194995 71	satyam.akb@rediff mail.com
320	UPE	Deoria	Shivam Infotech	Civil Lines Road in front of Jila Panchayat Karyalay, Deoria (Uttar Pardesh)	Vishal Pandey	93364153 12	shivaminfotechworl d@gmail.com
321	UPE	Sitapur	M D Mobile Solutions	Near RTO Office,	Anoop Prajapati	95065566 66	mdmobilesolutions 77@gmail.com

				Lakhimpur, Sitapur(Khieri), Uttar Pradesh			
322	UPE	Faizabad	R S Enterprises	8/5/3 A, Janana Hospital Road, Near Old Sona Biscuit Factory, Rehabganj, Faizabad, Uttar Pradesh	Manoj Ahuja	99192649 99	rs.ent11@yahoo.in
323	UPE	Gonda	Jaiswal Services	Infront Of Dadua Bazar, Post Office, Sahabganj, Station road, Gonda, Uttar Pradesh	Navendera Jaswal	94757656 56	jaiswalservices@g mail.com
324	UPE	Allahabad	Micronet Solution	B-38/1, Vashihta Vinayak Tower, Tashkand Marg, Civil Lines, Allahabad, Uttar Pradesh	Hashmi Kamal	94156128 80	micronetsolution@ gmail.com
325	UPE	Maunathbhanjan	A B Mobile	Naveen Market, Near Old Distt: Hospital,Opp.-B. J.P. Office, Sahadatpura, Maunathbhanjan , Uttar Pradesh	Vijay Gupta	98074916 76	vijay_abmobile@re diffmail.com
326	UPW	Hathras	Arya Electricals	Lakshmi Talkies Market ,Kamla Bazar ,Hathras	Vikas Sharma	92194286 5	aryaelectrial@yah oo.com
327	UPW	Shamli	Dev	Dhimanpura,Ne	Yogesh,Manoj,a	92195164	dev.telecom@yaho

			Telecom	ar Muzaffarnagar Bus Stand, Opp. India n Overseas Bank	mit	00	o.co.in
328	UPW	Firozab ad	Gauri Infocare	20, Ratan vihar complex, suhag nagar	Mr. Vinod kumar, Rajkumar	93197551 55	rajcumarchandra@ rocketmail.com
329	UPW	Shamli	Hari Om Cellulars	Bara Bazaar, Shamli, Distt. Muzaffarnagar - 247776, (U.P)	Mr. Vikrant Gupta	97580067 91	hariomsanchar_vo dafone@reiffmail.c om
330	UPW	Meerut	India Electronics	A 77 Bank Street opp. Scout guide school Lalkurti, Meerut, (U.P)	Mr. Saeed khan	99976921 65	tkhan2256@gmail. com
331	UPW	Aligarh	Infocare	#13,14, Vikram Arcade Railway Road, Aligarh	Prabal Bansal	75204404 95	prabalbansal@gm ail.com
332	UPW	Agra	Jain Sons	3-A, Raghu Shopping Complex, M.G. Road, Agra, Utter Pradesh	V. K Jain	56240002 15	jainsonsvk@hotmail. il.com
333	UPW	Baghpat	Kissan Communicat ion	New Railway Station, Nehru Road, Baraut , Baghpat (U.P.)-250611	Mr. Yashveer Singh	93593661 11	yashveer333@yah oo.com
334	UPW	Agra	A- Care Centre	BLOCK NO. 28/2, SHOP NO.B-111, JYOTI	Ashok Goyal	93193807 77	acarecentre@gmai l.com

				BUILDING, OPP.POST OFFICE, SANJAY PLACE, AGRAUtt Pradesh.			
335	UPW	Bijnor	Majid Telecom	G.K. Complex Near PNB Kotdawar Road Najibabad Dist> Bijnor-	Mr.Abdul Majid	98974706 80	majid.bij@lemonm obiles.com
336	UPW	Mainpuri	S.S. Computers	Near Raj Marriage Home, Haridarshan Nagar, MainPuri (U.P)	Ankit Mishra	92595181 06	ss.mainpuri@lemo nmobiles.com
337	UPW	Etah	Triveni Computer Service	688/01 Vijay Nagar,In Front of Sarda Cinema,Thundi Sarak.	Vinod Kunar	93681116 81	triveni.etah@lgmo biles.com
338	UPW	GHAZIA BAD	V.M. Computer Services	C/O Money Communication ,S hop No.1, C-22, RDC, GHAZIABAD(U. P.)	Akash Singh	12045684 95	jp.sharma83@gma il.com
339	UPW	Shajaha npur	Websity Computers	71, Tarin Bahadurganj, Near Clock Tower	C.M.Jauhari,Dha ram Veer Singh	92354282 72	c_jauhrari@yahoo. co.in
340	UPW	Bareilly	AaroHi Services	SA-21, D.D. Puram, Bareilly,	Aarti Tondon	99274123 45	aarohiservices@g mail.com

				utter pradesh			
341	UPW	Saharanpur	Tirupati Enterprises(Saharanpur)	Pooja Complex, Opp civil Court,Court Road, Saharanpur,	Manu Tyagi	9837690000	service.saharanpur@gmail.com
342	UPW	Mathura	R.K INFOTECH	G-3 AATITHYA PALACE COMPLEX, SONKH ADDA, JUNCTION ROAD	alok gupta	9319999666	rk.mathura@lemon mobiles.com
343	UPW	Etah	Sarvesh Communication	Co-oprative Society, Aliganj, Etah, Uttar Pradesh	Pravesh Singh	9837713964	sarvesh.kumar0000@rediffmail.com
344	UPW	Kasganj	Prem Computer Services	Roop Complex, Nadrai Gate, Kasganj, Kashi Ram Nagar, Uttar Pradesh	Vinay Kumar	9045309545	vinayinfo2000@yahoo.com
345	UPW	Hapur	Krishika Telecom	Front of R K Plaza, Gurudwara Market, Railway Road, Hapur,Gaziabad h, Uttar Pradesh	Sunil Kumar	9219132812	krishikatelecom@gmail.com
346	UPW	Modi Nagar	Shiv Telecom	Opp.- Modi Nagar Dharam Kanta,Near Raj Chopla, Modinagar, Ghaziabad, Uttar	Ankit Kumar	9319486010	shiv.ankit09@gmail.com

				Pradesh			
347	UPW	Moradabad	Shree Balaji Infotech(Moradabad)	1st FLOOR, OPP AHINSA HOTEL, GMD ROAD, BUDH BAZAR CORAHA, Moradabad, Utter Pradesh	Mukesh kumar	9219901466	mukee_tanwar@yahoo.com
348	UPW	Bulandshahr	M N Telecom	1st Floor, Birhamaputra Complex, Kala Aam, City & Distt.-Bulandshahr, Uttar Pradesh	Murtaza Solanki	9358011688	mntelecom.solanki@gmail.com
349	UPW	Meerut	Manthan Traders	D-3, Damodar Colony, Near Joshi Appartments, Meerut Uttar Pradesh	Dhreeaj Tyagi	9759607777	manthantraders@rediffmail.com
350	UPW	Muzaffarnagar	Sai Communication	Ch. Charan Singh Market, Shop No.-1, Near Mahaveer Chowk, Muzaffarnagar, Uttar Pradesh	Rajeev Madaan	9997544308	madaan.rajeev123@rediffmail.com
351	UPW	Rampur	Choudhary Service Centre	Nawab Gate, Mala Road, Rampur, Utter Pradesh	Adil Choudhary	9690500786	adil.choudhary@yahoo.in
352	UPW	Amroha	Shree Jee Traders	Bazar Jatt, Near Tehseel,	Arun Bharghav	9319728799	shreejeetraders@ymail.com

				Amroha, J P Nagar, Utter Pradesh			
353	UPW	Gautam Buddha Nagar	TEST ASP	Noida	Test ASP	9999644284	ajitbtech87@gmail.com
354	UPW	Noida	Vidhi Mobile Point	Shop No-1, Horam Complex, Naya Bass, Sec-15, Noida, Uatter Pardesh	Pradup Awana	1204358655	vidhimobilepoint@gmail.com
355	UPW	Dhampur	Ask Enterprises	Dr. Zakir Hussain Road, Dhampur, Bijnor, Utter Pradesh	Adarsh Aggarwal	9358581144	ask.dhampur@gmail.com
356	UPW	Badaun	Vaibhav Telecom	Hatal Ajenta Complex, Opp. Roadways Bes Stand, Badaun, Utter Pardesh	Sonia	9258756660	vaibhavtele@rediffmail.com
357	UPW	Pilibhit	Rathore Electronics	Madhuban Complex, Ground Floor, Pilibhit, Uttar Pradesh	Vijay Rathore	9259316555	vijayrathore20@yahoo.com
358	Uttanchal	Dehradun	Ujjwal Telecom	42 omkar road Behind GPO, Chukuwala, Dehradun	Mr.Roshan	9897388800	ujjwal.dehradun@lomonmobiles.com
359	Uttanchal	Jwalapur	Connecting Communication	G-76, New Ansari Market, Gurudwara Road, Jwalapur,	Manish Verma	9359246415	manishverma.hdr@gmail.com

				Haridwar, Uttarakhand			
360	Uttanchal	Roorkee	Mobile World(Roorkee)	Close to Kundan Sweets, Opp.- Masjid, 20 Civil Lines, Roorkee, Uttarakhand	Shahnawaz Ahmed	98978582 55	mobileworld.roorkee@gmail.com
361	Uttanchal	Pauri Garhwal	Naina Communication	Shop No.-4, Pundir Complex, Kala Road, Srinagar Pauri Garwal, Uttarakhand	Lalit Mohan Bisht	94124138 72	lalit.442@rediffmail.com
362	Uttanchal	Kashipur	Aman Enterprises	Aliganj Road, Tanda Ujjain, Kashipur, Udham Singh Nagar, Uttamchal	Gurdev Singh	98376878 46	singhgurdev38@yahoo.com
363	West Bengal	Midnapore	Mobile Care(W.B.)	Swarnarekha Aooartment, Opp.-Syndicate Bank, Near Web Computer, Malancha Road, Kharagpur, West Midnapur, West Bengal	Rajesh Sharma	93328766 12	rajeshsharmakgp@rediffmail.com
364	West Bengal	West Bengal	Rupa Telecom	College Para, Basirhat, North 24 Parganas, West Bengal	Mr.Debdutt Khara	91535955 88	rupatelecom@gmail.com
365	West Bengal	Ganga Rampur	Puja Telecom	Vill D.B. Road Para, Near	Pranabesh Ghosh	92331021 12	puja_grp@rediffmail.com

				Milonin Club, PO Gangarampur, PS Gangarampur, Distt. Dakshin Dinajpur, West Bengal.			
366	West Bangal	Jalpaiguri	M B Distributor	Sitalabari, Falakata, Jalpaiguri, West Bengal	Kuldip Agarwala	9832478833	agarwalakuldip@yahoo.com
367	West Bangal	Nadia	Porama Sales & Service	Bus Stand Complex Market, 37, 1st Floor, Krishnagar, Nadia	Amit Debnath	7797042203	amitdnath898@gmail.com
368	West Bangal	Bankura Town	Friends Mobile	KENDUADIHI, C HOTO MORE, NEAR SAMMILANI COLLEGE, POST:-BANKURADI ST:-BANKURA, WEST BENGAL	SK Nasir	9563177402	friendsmobilebkr@yahoo.in
369	West Bangal	Malda	Excel Service	Pranta Pally NH-34. Indera Appartment 1st Floor, Opp.-Hotel Chanakya, Distt.-Malda, West Bengal	Palash Karmakar	9593700360	excel.service@rediffmail.com
370	West Bangal	Kakdwip	Dwipshikha Electronics	Kakdwip New market, 94	Chitrlekha Jawa	9564457037	swapan_35kak@yahoo.com

				Busatand, South 24 Pas, West Bengal.			
371	West Bengal	Jalpaiguri	A2Z Mobile Multimedia	kamarpara, Jalpaiguri, West Bengal, India.	Bodhisattwa Basu	99324906 82	reshav@msn.com
372	West Bengal	Ramnagar	New Computer World	Vill+P.O.+P.S. -Ram Nagar, Distt-Purba Midinipur, West Bengal.	Prasun Dinda	94343410 81	dinda_prasun23@rediffmail.com
373	West Bengal	Birati	S S enterprise	1, Vidyapith Road, Beside Birati Big Bazaar, Birati, Kolkata, West Bengal	Sulagna Das	91432699 96	ssenterprises_51@yahoo.in
374	West Bengal	Kolkata	Mobi Care	1.A, Nandan Bagan Street, Kolkata, West Bengal	Mahua Paul	98048484 91	paulsouren@yahoo.co.in
375	West Bengal	Kolkata	AL Hera Electronics	26, Bentic Street, Near Orient Cinema, Kolkata, West Bengal	MD Sajid	98042149 73	alheraelc@gmail.com
376	West Bengal	Kolkata	Mobile Hub	62, D H Road, Shop No.-4, Near Bus Stop Janakalyan, Opp.-ICICI Bank ATM, Kolkata, West Bengal	Goutam Adhikary	91436132 27	servbehala.30@gmail.com
377	West	Kolkata	Pioneer	25 R B C	Rupam Dey	98317656	pioneerenterprise1

	Bangal		Enterprises	Road,Opp.-City Mall, Dackbangla Barast, Kolkata, West Bengal		34	1@gmail.com
378	West Bangal	Asansol	Swati Enterprises	Swati Enterprises, C/O- Shyam Plaza, S. B. Gorai road, Near Santivination School, Opp.-SBI Atm, Asansol,West Bengal	Subash KR Aggarwal	9434751635	subhasagarwal2002@yahoo.co.in
379	West Bangal	Nadia	Subhankar Bose	Raju Elctronics 52, R.N. Tagore Road, Roy Market, High Street, Krishnagar, Nadia, West Bengal	Subhankar Bose	9800692201	subhankarbose35@gmail.com
380	West Bangal	Siliguri	Subham Computers	622, Rishi Aurobindo Road2nd By Lane, Opp Back Side of Pradhan BuildingHakimpara, Siliguri	Mr. Nawal Kishor Mishra	9434044959	s.jha@subhamcomputers.com
381	West Bangal	Durgapur	Digitech Service	J.K. Paul Lane,Benachity	PINTU CHATTERJEE	9933162824	digitech.service@rediffmail.com
382	West Bangal	BIRBHUM	R.K.Sales & Service	RAMPURHAT NEWBUSTAND(ROFECUL ISLAM	9732174962	rofeculislam@rediffmail.com

				NEAR INDRANAI FURNITURE GALI),RAMPUR HAT,BIRBHUM			
383	West Bangal	Berham pore	S B COMMUNIC ATION	3 , station Road, Berhampore.mur shidabad	SOURAV MONDAL	97344496 11	sb_const123@rediffmail.com
384	West Bangal	Howrah	Air Voice	374, Belilious Road, Ner Howrah Maidan, Opposite Sales Tax Building, West Bengal.	Amit Kumar Bera	91434007 07	howrah.airvoide@gmail.com