

User Guide



SANYO

SCP-2300

Table of Contents

1. The Basics	2
Front View of Phone	2
Viewing the Display Screen	4
Turning Your Phone ON and OFF	5
Using the Battery	6
Displaying Your Phone Number	8
Making and Answering Calls	8
Making Calls	8
Dialing Options	10
Answering Calls	11
Using the Speakerphone	14
Changing the Ringer Volume	14
Adjusting Volume During a Conversation	15
Muting a Call	15
Displaying the Missed Call Notification	15
Calling Emergency Numbers	16
In-Call Options	17
End-of-Call Options	18
Saving a Phone Number	18
Finding a Phone Number	19
Dialing and Saving Phone Numbers With Pauses	19
Dialing From the Contacts Directory	20
Using One-Touch Speed Dialing	21
Selecting a Character Input Mode	22
Entering Characters Using T9 Text Input	23
Adding a Word to the T9 Database	23
Entering Characters by Tapping the Keypad	24
2. Your Phone's Settings	25
Sound Settings	25
Selecting a Tone Length	27
Setting a Start-up/Power-off Tone	27
Using Voice Prompt	27
Adjusting the Phone's Volume Settings	28
Alert Notification	29
Silence All	30
Display Settings	31
Changing the Greeting	31
Changing the Backlight Time Length	31
Changing the Display Screen	32
Changing the Display for Incoming Calls	32
Changing the Display for the Standby Mode	33
Changing the Screen Saver	34
Changing the Background	34
Changing the Contrast	35

Changing the Font Size	35
Location Settings	36
TTY Use	37
Airplane Mode	38
Phone Setup Options	39
My Shortcut	39
Auto Answer Mode	40
Setting Any Key Answer	40
Headset Mode	41
Sleep Mode	42
Setting Message Notification	42
Setting Push Options	42
Editing Canned Messages	43
Setting Your Callback Number	44
Setting the Current Time	44
Changing the Menu Language	45
Setting Your Signature	45
Setting the Open/Close Flip Option	46
Setting the Side Key Guard	47
Setting Up Key Press Echo	47
3. Security	48
Accessing the Security Menu	48
Locking Your Phone	48
Unlocking Your Phone	49
Lock Services	49
Changing the Lock Code	49
Calling in Lock Mode	49
Restricting Calls	50
Using Special Numbers	50
Erasing the Contacts Directory	51
Erasing the Downloads	51
Resetting Your Phone	51
4. Roaming	52
Understanding Roaming	52
Setting Your Phone's Roam Mode	53
5. Menu Navigation	54
Viewing the Menus	54
6. Managing Call History	56
Viewing History	56
Call History Options	56
Making a Call From Call History	57
Saving a Phone Number From Call History	57
Prepending a Phone Number From Call History	58
Erasing Call History	58

7. Contacts Directory59

Displaying the Contacts List	59
Adding a New Contacts Entry	59
Finding Contacts List Entries	60
Contacts List Entry Options	62
Assigning Speed Dial Numbers	63
Editing a Contacts Entry	64
Erasing a Contacts Entry From the List	64
Selecting a Ringer/Image Type for an Entry	65
Secret Contacts Entries	66
Dialing Services	66

8. Personal Organizer67

Managing Schedules	67
Adding an Event to the Scheduler	68
Event Alerts	69
Event Alert Menu	69
Viewing Events	69
Editing an Event	70
Adding a Call Alarm to the Scheduler	70
Call Alarm Alerts	71
Call Alarm Menu	71
Editing a Call Alarm	72
Erasing a Day's Event or Call Alarm	72
Viewing a Future/Past Day's Scheduled Events	72
Adding To Do Items	73
Viewing To Do List	73
Editing To Do Items	73
Adding a To Do Item to the Schedule	73
Deleting Items from the To Do List	74
Viewing Memory in Your Scheduler	74
Purging All Events, Call Alarms or To Do List Items	75
Displaying Phone Information	75
Finding Icon Definition	75
Displaying the Version Information	76
Displaying Advanced Information	76
Using Your Phone's Tools	76
Using the Alarm Clock	76
Using the Calculator	77
Using the World Clock	77
Using the Stop Watch	78
Downloading through Wireless Web	79
Confirming the Downloaded Data	80
Downloaded Data Options	81
Erasing the Downloaded Data	83

9. Voice Services	84
Using Voice-Activated Dialing	84
Programming Voice Dial Tag to Your Phone	84
Reviewing Voice Dialing Tags	85
Erasing All Voice Dial Tags	85
Managing Voice Memos	86
Recording Voice Memos	86
Reviewing Voice Memos	87
Erasing Voice Memos	88
Setting Up Screen Call	89
10. 10-4	92
Changing 10-4 Mode	92
10-4 Call Alerts	92
Displaying the 10-4 List	93
Selecting Contacts Lists	93
Making a 10-4 Call (1-to-1 Call)	94
Making a 10-4 Call (Group Call)	95
Making a 10-4 Call by Entering a Number	96
Missed Call Notification for 10-4 Calls	96
Receiving a 10-4 Call	97
10-4 Options	98
Copying an Entry to Personal List or Personal Group List	99
Saving a 10-4 Number	100
Finding an Entry in the 10-4 List	100
Adding a New Contact to Your Personal List	101
Adding a New Group to Your Personal Group List	102
Editing a Contact in Your Personal List	103
Editing a Group in Your Personal Group List	103
Erasing an Entry in Your Personal List or Personal Group List	105
Erasing a 10-4 List	106
Updating the Company List and Personal List	106
Setting Speed Dialing for 10-4 Entries	107
Setting 10-4 Guard	107
Setting Ringer Types for 10-4 Calls	108
Setting an Alert Notification for 10-4 Calls	108
Setting the Speakerphone for 10-4 Calls	109
Setting the Default View of the 10-4 List	109
Setting the Floor Display of the 10-4 Calls	109
11. Messaging	110
New Messages	110
Message Storage	110
Displaying Messages	111
Sending a Message	112
Message Options	114
Folder List Options	114

Message List Options	114
Messages Details Options	116
Changing the Display Font Size of a Message	117
Prepending a Phone Number From a Message	117
Creating Folders for Messages	118
Moving a Message Into Another Folder	119
Editing Folders	119
Erasing Messages	119
Erasing a Folder	120
Erasing Selected Messages in All Folders	120
Web Alerts Options	121
Web Alerts List Options	121
Web Alerts Details Options	121

12. Service Features122

Using Voicemail	122
Voicemail Notification	122
Displaying Voicemail Details	122
Retrieving Your Voicemail Messages	122
Clearing the Message Icon	123
Editing Your Voicemail Number	123
Responding to Call Waiting	124
Making a Three-Way Call	125
Web	126
Launching the Web	126
Net Guard	126
Browsing the Web	127
Games	131
Ringers	132
Screen Savers	133

13. Safety Guidelines135

Maintaining Your Phone's Peak Performance	135
Using Your Phone While Driving	135
Following Safety Guidelines	135
Using Your Phone Near Other Electronic Devices	136
Turning Off Your Phone Before Flying	136
Turning Off Your Phone in Dangerous Areas	137
Restricting Children's Access to Your Phone	138
Protecting Your Battery	138
Disposal of Lithium Ion (Li-Ion) Batteries	139
Cautions	139

Index141


SCP-2300

Dual Band/Tri Mode Phone

User Guide

1. The Basics

Front View of Phone































Key Features






- 1. Earpiece:** Lets you hear the caller's voice.
- 2. Main LCD (display):** Displays the phone's main menu, features, modes, etc.
- 3. Softkey (left):** Lets you select the menu corresponding to the bottom left line on the Main LCD.
- 4. Navigation Key:** Lets you navigate quickly and easily through the menu options. You can access the menu shortcuts by pressing **Right:** Contacts, **Left:** Shortcut, **Up:** Messaging, and **Down:** Downloads.

5. **MENU/OK:** Lets you access the phone's menus and select menu options.
6. **Web Key:** Lets you launch the Browser.
7. **TALK Key:** Lets you place or receive calls, answer Call Waiting, or use Three-Way Calling.
8. **Microphone:** To speak into or record your voice.
9. **Accessories Connector:** Connects accessories such as a travel charger (included) and USB cable (not included).
10. **Keypad:** Lets you enter numbers, letters, and characters, and navigate within menus. Press and hold keys 2-9 for speed dialing.
11. **SPEAKER Key:** Lets you place or receive calls in speakerphone mode.
12. **END/POWER Key:** Lets you turn the phone on/off, end a call, or return to standby mode.
13. **BACK Key:** Lets you display the previous page or clear characters from the screen.
14. **Softkey (right):** Lets you select the menu corresponding to the bottom right line on the Main LCD.
15. **Speaker:** Lets you hear the different ringers and sounds. You can mute the ringer when receiving incoming calls by pressing **END/⓪**, **BACK**, or the Side Up/Down Key. Also lets you hear the caller's voice in speakerphone mode.
16. **Sub LCD:** Lets you monitor the phone's status and see who's calling without opening the phone.
17. **LED Indicator:** Shows your phone's connection status at a glance.
18. **Antenna:** Fully extend the antenna for the best reception.
19. **Headset Jack:** Allows you to attach an optional phone headset for hands-free phone use. (For Monaural Headset Only.)
20. **10-4 Button:** Allows you to access the 10-4 List. (See "Displaying the 10-4 List" on page 93.)
21. **Side Up/Down Key:** Lets you adjust the receiver volume during a call or ringer volume in standby mode. Press and hold to make a voice dial or redial with the flip closed.

Viewing the Display Screen

This list identifies the symbols you'll see on your display screen.

- ▶  shows your current signal strength. The more lines you have, the stronger your signal.
- ▶  means your phone cannot find a signal.
- ▶  indicates a call is on hold.
- ▶  tells you a call is in progress.
- ▶  indicates the 1X Services/10-4 access are available.
- ▶  indicates the 1X Services/10-4 access are not available.
- ▶  indicates 1X Services/10-4 access are connected, but voice calls can be sent or received.
- ▶  indicates 1X Services/10-4 access are active.
- ▶  indicates you have new text messages waiting.
- ▶  indicates you have new voicemail messages waiting. Press and hold  to call your voicemail box.
- ▶  indicates you have text messages and voicemail messages waiting.
- ▶  indicates you are roaming on digital service network.
- ▶  indicates you are roaming on analog service network.
- ▶  indicates your phone is on analog service network.
- ▶  indicates the 10-4 service is enabled.
- ▶  indicates the 10-4 service is unavailable.
- ▶  indicates the 10-4 service is enabled and the speakerphone mode is set to on.
- ▶  shows the level of your battery charge. The more black you see, the more power you have left. It turns  while charging.
- ▶  indicates you have menus to scroll (in four directions).
- ▶  indicates a beep sound is set at level 1.
- ▶  indicates the vibrate feature is set to ON.
- ▶  indicates volume level 4 and vibrate feature is set to ON.
- ▶  indicates the voice call ringer setting is OFF.
- ▶  indicates all the sound settings are OFF.
- ▶  indicates the Location Service of your phone is enabled.
- ▶  indicates the Location Service of your phone is disabled.

- ▶  indicates you have new caller's message.
- ▶  indicates the Screen Call Auto setting is ON.
- ▶  indicates your phone is in TTY mode.
- ▶  indicates Headset mode is set to 10-4 and a headset is connected.
- ▶  indicates the speakerphone mode is set to ON.

Turning Your Phone ON and OFF

Turning Your Phone ON

- ▶ To turn your phone on, press .

Once your phone is ON, it displays “Looking for service...” which indicates that your phone is searching for a signal. When your phone finds a signal, it automatically enters standby mode. At this point, you are ready to begin making and receiving calls.

If your phone is unable to find a signal after 15 minutes of searching, a Power Save feature is automatically activated. When a signal is found, your phone automatically returns to standby mode.

In Power Save mode, your phone searches for a signal periodically without your intervention. You can also initiate a search for service by pressing any key (when your phone is turned ON).

Tip: The Power Save feature helps to save your battery power when you are in an area where there is no signal.

Turning Your Phone OFF

- ▶ Press and hold  until you see the powering down animation on the display screen.



Your screen remains blank while your phone is off (unless the battery is charging).

Using the Battery

Installing the Battery

To install the Lilon battery:



1. Insert the battery into the opening on the back of the phone and gently press down.
2. Place the battery cover into the position as indicated in the diagram, then slide it until you hear it snap into place.



Removing the Battery


To remove your battery:

1. Make sure the power is off. Press the battery release latch, then slide the battery cover and remove it.
2. Use your thumbnail to lift and then remove the battery as indicated in the diagram.



Charging the Battery

Your phone comes with a rechargeable battery. You should charge the battery as soon as possible so you can begin using your phone.

Keeping track of your battery's charge is important. If your battery level becomes too low, your phone automatically turns off and you will lose all the information you were just working on. For a quick check of your phone's battery level, glance at the battery charge indicator located in the upper-right corner of your phone's display screen. If the battery charge is getting too low, the battery icon  appears and the phone sounds a warning tone.

Always use an approved travel charger or vehicle power adapter to charge your battery.

Warning! Using the wrong battery charger could cause damage to your phone and void the warranty.

Note: Long backlight settings, searching for service, vibrate mode, and browser use affect the battery's talk and standby times.

Using the Travel Charger

To use the travel charger provided with your phone:



1. Plug the travel charger into a wall outlet.
2. Plug the other end of the travel charger into the side of your phone (with the battery installed).

Charging when your phone is turned on:

The battery icon  appears on the display while charging.

The battery icon turns to  when charging is complete.

Charging when your phone is turned off:

The battery icon  appears, and the message "BATTERY CHARGING-Power Off-" is shown on the display while charging. When the battery is completely discharged, you may wait for several minutes until the message is shown on the display. The battery icon turns to , and message changes to "CHARGING COMPLETE-Power Off-" when charging is complete.

Tip: Be sure to watch your phone's battery level indicator and charge the battery before it runs out of power.

Displaying Your Phone Number

1. Press **MENU OK** to access the main menu.
2. Highlight **Contacts** and press **MENU OK**.
3. Highlight **My Phone#** and press **MENU OK**.

Note: To access the phone's main menu, press **MENU OK** from standby mode. Menu items may be selected by highlighting them with the navigation key and pressing **MENU OK**, or you can press the number corresponding to the menu item on your keypad.

Making and Answering Calls


Making Calls

To place a call using your keypad:


1. Make sure your phone is on.
2. Enter a phone number. (If you make a mistake while dialing, press **BACK** to erase one digit at a time. Press and hold **BACK** to erase the entire number.)
3. Press **TALK** or **SPEAKER**.
4. When you're finished, press **END/⓪**.

Tip: To redial your last outgoing call, press **TALK** or **SPEAKER** twice.

Important: When you use your phone to maximize performance, extend the antenna and do not touch the antenna.



To place a call with the flip closed:

1. Make sure your phone is on.
 2. Press and hold  on the left side of the phone.
 3. Follow the system prompts. (The call will be made in speakerphone mode, unless you have a headset attached to the phone.)
- ▶ **Redial** to redial the last number you called.
 - ▶ **Voice Dial** to use the Voice Dial function (see “Using Voice-Activated Dialing” on page 84).



Tip: This function is available only when the Side Key Guard setting is off. See page 47 for the Side Key Guard.

Note: To use a Voice Dial, you must have stored Voice Dial entries (see “Programming Voice Dial Tag to Your Phone” on page 84).

Dialing Options

Dialing options are displayed when you press **Options** (right softkey) after entering numbers in the standby mode.

To select an option, highlight it and press .

- ▶ **Call** to dial the phone number.
- ▶ **Call:Speaker On** to dial the phone number in speakerphone mode.
- ▶ **Send Text** to send a text message (mobile numbers only). (See “Sending a Message” on page 112.)
- ▶ **Save Phone#** to save the phone number in your Contacts list. (See “Saving a Phone Number” on page 18.)
- ▶ **Find** to display Contacts list entries that end with the digits you entered. (See “Finding a Phone Number” on page 19.)
- ▶  **Hard Pause** to insert a hard pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 19.)
- ▶  **2-Sec. Pause** to insert a 2-second pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 19.)
- ▶ **Hyphen** to insert a hyphen manually where you like.

Tip: To Speed Dial a phone number, press and hold the appropriate Speed Dial location from 2-9. See page 63 for setting.

Answering Calls

To answer an incoming call with the flip open:

1. Make sure your phone is on. If your phone is off, incoming calls go to voicemail.
2. Press **TALK** or **SPEAKER** to answer an incoming call. (Depending on your phone's settings, you may also answer incoming calls by opening the phone or by pressing any number key. See "Setting Any Key Answer" on page 40 for more information.)

To answer an incoming call with the flip closed:


1. Make sure your phone is on. (If your phone is off, incoming calls go to voicemail.)
2. When your phone rings or vibrates, press and hold the Side Call key (**|||||**) on the left side of the phone. (The call will be answered in speakerphone mode.)
- or -
Open the phone to use the earpiece.

Note: If the setting for Open Flip is not set to **Answer Call**, opening the phone will not answer the call. (See "Setting the Open/Close Flip Option" on page 46.)

Your phone notifies you of incoming calls in the following ways:

- ▶ The phone rings or vibrates.
- ▶ The LED flashes.
- ▶ The backlight illuminates.
- ▶ The screen displays an incoming call message.
- ▶ If available, the phone number of the caller is displayed.
- ▶ If the phone number is in your Contacts list, the contact's name is displayed.

The following options are also displayed by pressing **Options** (right softkey).

To select an option, highlight it and press .



- ▶ **Answer** to answer the call.
- ▶ **Answer:Speaker** to answer the call in speakerphone mode.
- ▶ **Answer on Hold** to put the call on hold. (See “Setting Answer on Hold” on the next page.)
- ▶ **Screen Call** to answer the call by using pre-recorded announcement. (This feature appears when you are in service area or digital roaming area.) See page 89 for setting up.
- ▶ **Quiet Ringer** to mute the ringer. (This feature appears when the ringer is set.)

Note: If your phone is off, incoming calls go to voicemail.

Setting Answer on Hold

This feature allows you to hold an incoming call when you cannot answer immediately.

To set Answer on Hold:

1. When you receive an incoming call, press **Options** (right softkey).
2. Highlight **Answer on Hold** and press . (The caller hears a message to wait for you to answer.  will display on the screen while the call is on hold.)

To resume the call:

- ▶ Press **Answer** (left softkey) or **TALK**.
- or -
- Press **Options** (right softkey), highlight **Answer** or **Answer:Speaker** and press .

Note: Answer on Hold is not available in analog areas.

Ending a Call

- ▶ Close the phone or press **END/O**.

Note: If the setting for Close Flip is not set to **End Call**, closing the phone will not end the call. (See "Setting the Open/Close Flip Option" on page 46.)

Tip: Time/Date is displayed when you press **BACK** while the phone is in use.

Using the Speakerphone

The speakerphone feature lets you hear audio through the speaker and talk without holding the phone. When the speakerphone is activated, use the Side Up/Down key or press the navigation key up or down to adjust the volume.

To turn the speakerphone on during a call:

► Press **SPEAKER**.

– or –

Press **Options** (right softkey), highlight **Speaker On**, and press **MENU OK**.

To turn the speakerphone off during a call:

► Press **SPEAKER**.

– or –

Press **Options** (right softkey), highlight **Speaker Off**, and press **MENU OK**.

Changing the Ringer Volume

To change the ringer volume, adjust the Side Up/Down key when the phone is in standby mode.

Note: To change the ringer volume from the main menu, see “Adjusting the Phone’s Volume Settings” on page 28.

Adjusting Volume During a Conversation

Whether you need to hear more or less of a conversation, adjust the Side Up/Down key or press the navigation key up or down during a call.

Muting a Call

To mute a call:

- ▶ Press **Options** (right softkey), highlight **Mute**, and press **MENU OK**.
(When the phone is muted, “Mute” appears on the display.)

To unmute a call:

- ▶ Press **Options** (right softkey), highlight **Unmute**, and press **MENU OK**.

Tip: To use this feature with the flip closed, press and hold **◀ || ▶** (located on the side of your phone).

Displaying the Missed Call Notification

When an incoming call is not answered, your phone displays the Missed Call Notification.

- ▶ Press **View** (left softkey). (To call an entry, highlight the entry you want to call and press **TALK** or **SPEAKER**.)

Calling Emergency Numbers

You can place calls to 911 (dial **9** **1** **1** and press **TALK**), even if your phone is locked or your account is restricted. Once the dial is made, you will enter Emergency mode.

To select an option, press **Options** (right softkey), highlight it, and press **MENU OK**.

Options:

- ▶ **Speaker On** to activate speakerphone mode. (If you are in speakerphone mode, the option will appear as **Speaker Off** to deactivate.)
- ▶ **Unlock Phone** to unlock your phone (appears only if the phone is locked).
- ▶ **Close Menu** to close the pop-up menu (appears only if the phone is unlocked).

Tip: Press **My Phone** (left softkey) to display your phone number during Emergency mode.

To exit Emergency mode:

1. Press **END/⓪**.
2. Press **Options** (right softkey) to display the options.
3. Highlight **Exit Emergency** and press **MENU OK**.

Note: When you are in Emergency mode, you can only exit from the options menu.

To select Emergency mode options:

1. Press **END/⓪** during a 911 call.
2. Press **Options** (right softkey).
 - ▶ **Call 911** to call 911.
 - ▶ **Call 911:Speaker** to call 911 in speakerphone mode.
 - ▶ **Exit Emergency** to exit Emergency mode.
3. Select an option and press **MENU OK**.

In-Call Options

During a call, your phone displays menu options by pressing **Options** (right softkey).

To select an option, highlight it and press .

- ▶ **Flash** to answer an incoming Call Waiting call or connect a third party during Three-Way Calling.
- ▶ **Mute** to mute your phone's microphone. Select **Unmute** to reactivate the microphone.
- ▶ **Speaker On** or **Speaker Off** to activate or deactivate speakerphone mode. You can adjust the speakerphone volume using the Side Up/Down key.

Warning! Due to higher volume levels, do not place the phone near your ear during speakerphone use.

- ▶ **Three -Way Call** to call a third party.
- ▶ **Call History** to access the Call History menu. (See "Managing Call History" on page 56.)
- ▶ **Contacts** to access the Contacts menu. (See "Contacts Directory" on page 59.)
- ▶ **Messaging** to access the Messaging menu. (See "Messaging" on page 110.)
- ▶ **Settings** to access the Settings menu. (See "Your Phone's Settings" on page 25.)
- ▶ **Tools/Extras** to access the Tools/Extras menu. (See Calendar menu instructions on page 67.)

Note: Flash menu appears in Call Waiting and Three-Way Call. Mute menu does not appear during a 911 call.

End-of-Call Options

To display the following options, press **Options** (right softkey) within 10 seconds after disconnecting a call.




To select an option, highlight it and press .

- ▶ **Call Again** to dial the phone number.
- ▶ **Call:Speaker On** to dial the phone number in speakerphone mode.
- ▶ **Save Phone#** to save the phone number in your Contacts list. **Go to Phone Book** appears when the number is already in your Contacts list. (See “Saving a Phone Number” below.)

Note: The End-of-Call options are not displayed for calls identified as No ID or Restricted.

Saving a Phone Number

Your phone can store up to seven phone numbers in each of 300 Contact entries with up to 500 total numbers. Each entry's name can contain 16 characters. Your phone automatically sorts the Contacts entries alphabetically.

1. Enter a phone number.
2. Press **Options** (right softkey).
3. Highlight **Save Phone#** and press .
4. Select a label by highlighting **Mobile**, **Home**, **Work**, **Pager**, **Fax**, **Other**, or **No Label** and press .
5. Enter a Name and press .
Once you have stored an entry in Contacts list, you are prompted to select the following entry modes:
 - ▶ **New Name** to enter a name directly.
 - ▶ **From Ph. Book** to select a name from the Contacts entry list.
6. Press **Save** (left softkey).

Finding a Phone Number

You can search Contacts list entries for phone numbers that contain a specific string of numbers.

1. Enter the last four or more digits of the number and press **Options** (right softkey). The more numbers you enter, the more specific the search becomes.
2. Highlight **Find** and press **MENU OK**. The Contacts entry that ends with the digits you entered appears.
3. Highlight your desired entry.
Press **MENU OK** to display the entry details.
Press **TALK** or **SPEAKER** to dial.

Dialing and Saving Phone Numbers With Pauses

You can dial or save phone numbers with pauses for use with automated systems, such as voicemail or credit card billing numbers.




There are two types of pauses available on your phone:

- ▶ **Hard Pause** sends the next set of numbers when you press **TALK**.
- ▶ **2-Sec. Pause** automatically sends the next set of numbers after two seconds.




Note: You can have multiple pauses in a phone number and combine 2-second and hard pauses.




1. Enter the phone number and press **Options** (right softkey).
2. Highlight either **Hard Pause** or **2-Sec. Pause** and press **MENU OK**. Hard Pauses are displayed as a “H” and 2-second pauses as a “T”.
3. Enter additional numbers.
4. To dial the number, press **TALK** or **SPEAKER**. (When dialing a number with a hard pause, press **TALK** to send the next set of numbers.)
– or –
To save the number in your Contacts list, press **Options** (right softkey), highlight **Save Phone#**, and press **MENU OK**.

Dialing From the Contacts Directory

1. Press  to access the main menu.
2. Highlight **Contacts** and press .
3. Highlight **Find/Add Entry** and press .

Shortcut: Press the navigation key right to list entries.

4. Use your navigation key to scroll through the Contacts list and highlight one of the appropriate entries and press .
5. Highlight the number you wish to call.
6. Press  (right softkey) for the menu options.
7. Highlight **Call** or **Call:Speaker On** and press .

Tip: You can also make a call by pressing , , or  (left softkey) during step 5 above.

Note: The icon next to each entry represent the Contacts labels (for example, Mobile, Home, Work, etc.). A triangle next to an icon means there is another number for the entry. Press the navigation key right or left to select the desired label/number.

Using One-Touch Speed Dialing

With this feature, you can dial Speed Dial entries using one key press for locations 2-9. (See page 63 for storing a Speed Dial number.)

To use speed dial for voice calls:

- ▶ From standby mode, press and hold the appropriate key for approximately two seconds.

– or –

From standby mode, press the appropriate key and press **TALK** or **SPEAKER**.

The display confirms that the number has been dialed when it shows “Connecting...”.


To use speed dial for 10-4 calls:

- ▶ From standby mode, press the appropriate key then press **1044**.
(See “Setting Speed Dialing for 10-4 Entries” on page 107.)

The display confirms that the number has been dialed when it shows “10-4 calling...”.

Selecting a Character Input Mode

Your phone provides convenient ways to enter words, letters, punctuation, and numbers whenever you are prompted to enter text (for example, when adding a Contacts entry or when sending Email messages).

1. When you display a screen where you can enter text, press **Mode** (right softkey).
 2. Select a character input mode, highlight it and press .
- ▶ **Add Word** to store words that you use frequently.
 - ▶ **Canned Messages** to enter canned messages. (For Text Message only.)
 - ▶ **Recent Messages** to enter messages you have used recently. (For Text Message only.)
 - ▶ **Signature** to enter your signature. (For Text Message only.)
 - ▶ **T9 Word** to enter characters using T9 Text Input (see next page).
 - ▶ **Alphabet** to enter characters by tapping the keypad.
 - ▶ **SYMBOL** to enter symbols.
 - ▶ **NUMBER** to enter numbers.
 - ▶ **PRESET SUFFIX** to enter a preset suffix.
 - ▶ **SMILEYS** to enter smiley pictures.
 - ▶ **Emoticons** to enter an emotion icon. (For Text Message only.)
 - ▶ **Select Language** to select the language (English or French).
 - ▶ **Erase All** to erase all text (if applicable).
 - ▶ **Paste** to paste copied or cut text (if applicable).
 - ▶ **Select Text** to select stored text for copying or cutting.

Entering Characters Using T9 Text Input

T9 Text Input lets you enter text in your phone by pressing keys just once per letter. (To select the **T9 Word** mode when entering text, see “Selecting a Character Input Mode” on the previous page.)

T9 Text Input analyses the letters you enter using an intuitive word database and creates a suitable word. (The word may change as you type.) To accept a word and insert a space, press **Space#**.

If you make a mistake, press **BACK** to erase a single character. Press and hold **BACK** to delete a word.

Adding a Word to the T9 Database

If a word you want to enter does not display as an option when you are using T9 Text Input, you can add it to the database.

1. Press **MENU OK** to access the main menu.
2. Highlight **Settings** and press **MENU OK**.
3. Highlight **Others** and press **MENU OK**.
4. Highlight **Text Entry** and press **MENU OK**.
5. Highlight **Add Word** and press **MENU OK**.
6. Enter the word using multi-tap (Alphabet) text entry and press **Save** (left softkey).

Tip: To confirm the words you have added, select **My Words** and press **MENU OK** during step 5 above.

Entering Characters by Tapping the Keypad

To enter characters by tapping the keypad, select the **Alphabet** mode (see “Selecting a Character Input Mode” on page 22). Press the corresponding key until the desired character appears. By default, the first letter of a word is capitalized and following letters are lowercase.

Characters scroll in the following order:

Key	English Sequence	
	Upper Case	Lower Case
1	., @ 1 ? ! * # /	
2	A B C 2	a b c 2
3	D E F 3	d e f 3
4	G H I 4	g h i 4
5	J K L 5	j k l 5
6	M N O 6	m n o 6
7	P Q R S 7	p q r s 7
8	T U V 8	t u v 8
9	W X Y Z 9	w x y z 9
+ 0	0	
Space #	Space	
Shift ✕	Unshifted One-character- shifted Caps Lock	

In French mode, characters scroll in the following order.



Key	French Sequence	
	Upper Case	Lower Case
1	., @ 1 ? ! * # /	
2	A B C Â Ã Ç 2	a b c â â ç 2
3	D E F É Ê Ë 3	d e f é ê ë 3
4	G H I Î Ï 4	g h i î ï 4
5	J K L 5	j k l 5
6	M N O Ô 6	m n o ô 6
7	P Q R S 7	p q r s 7
8	T U V Ù Û Ü 8	t u v ù û ü 8
9	W X Y Z 9	w x y z 9
+ 0	0	
Space #	Space	
Shift ✕	Unshifted One-character- shifted Caps Lock	

See page 22 for changing French entering mode.

After a character is entered, the cursor automatically advances to the next space after two seconds or when you enter a character not on the same key.

Tip: The beginning of the word after the space is changed to upper/lower case depending on shift mode. You can change the shift mode by pressing **Shift ✕**.

2. Your Phone's Settings








Reminder: To access the phone's main menu, press  from standby mode. Menu items may be selected by highlighting them with the navigation key and pressing .

Sound Settings



Selecting Ringer Types for Voice Calls

Select a ringer type for voice calls so that you can recognize when a certain type of call is coming in:

To select a ringer type for voice calls:








1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Ringer Type** and press .
5. Highlight **Voice Calls** and press .
6. Highlight **With Caller ID** or **No Caller ID** and press .
7. Highlight your desired ringer type and press .

To select a distinctive ringer for voice calls while roaming:








1. Follow steps 1-5 above.
2. Highlight **Roaming** and press .
3. Highlight **Distinctive** and press .
- ▶ To confirm the ringer, press **Play** (right softkey).
- ▶ To deactivate this feature, select **Normal** during step 3 above.

Note: The Normal ringer is available only when you are in digital roaming area.








Selecting Ringer Types for 10-4 Calls

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Ringer Type** and press .
5. Highlight **10-4** and press .
6. Highlight **10-4 Calls**, **10-4 Missed**, or **10-4 Floor Tone**, and press .
7. Select your desired menu, and press .








Selecting Ringer Types for Voicemail

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Ringer Type** and press .
5. Highlight **Voicemail** and press .
6. Press , select your desired menu, and press .







Selecting Ringer Types for Messages

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Ringer Type** and press .
5. Highlight **Messaging** and press .
6. Press , select your desired menu, and press .







Selecting Ringer Types for Calendar and Alarm

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Ringer Type** and press .
5. Highlight **Calendar/Alarm** and press .
6. Press , select your desired menu, and press .

Selecting a Tone Length



1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Others** and press .
5. Highlight **Tone Length** and press .
6. Highlight **Short** or **Long** and press .

Setting a Start-up/Power-off Tone

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Others** and press .
5. Highlight **Start-up Tone** or **Power-off Tone** and press .
6. Highlight your desired option and press .

Using Voice Prompt







This feature allows you to hear voice prompts at Voice Memo, or Screen Call setting etc. (Default Setting is Off.)

1. Follow the steps 1-4 above.
2. Highlight **Voice Prompt** and press .
3. Highlight **On** and press .







Tip: When ringer volume is set to “Silence All”, voice prompts cannot be heard.

Adjusting the Phone's Volume Settings

To adjust the ringer/key volume:

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Ringer/Key Vol.** and press .
5. Select the menu you wish to change and press .
6. Adjust the volume level by using the navigation key up or down and press .




To adjust earpiece or speaker volume:

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Receiver Vol.** and press .
5. Highlight either **Earpiece** or **Speaker** and press .
6. Adjust the volume level by using the navigation key up or down and press .

Tip: You can adjust the ringer volume in standby mode by using the Side Up/Down key, and adjust earpiece volume during a call by using the navigation key up or down or Side Up/Down key.

To adjust the application volume:

This setting is available for the volume of downloaded data and browser.







1. Follow steps 1-3 above.
2. Select **Application Vol.** and press .
3. Press , select a volume level by pressing the navigation key up or down, and press .

Alert Notification

Your phone comes with several different options to keep you aware of what's going on by sounding the alert or ringer.







- ▶ **Service** sets alert On or Off for network services parameter changes.
- ▶ **10-4** sets an alert to notify you of 10-4 calls. Select **10-4 Calls** for incoming 10-4 calls, or **10-4 Missed** for missed 10-4 calls.
- ▶ **Voicemail** sets an alert to notify you of caller's message(s). Select **Ringer Length** to set the ringer length of Voicemail notification.
- ▶ **Messaging** sets an alert to notify you of text message(s). Select **Ringer Length** to set the ringer length of Messaging notification.
- ▶ **Minute Beep** sets a minute reminder that beeps ten seconds before the end of each minute during a call.
- ▶ **Signal Fade** sets alert to notify you when your phone loses a signal during a call.

To set the alerts:

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Alerts** and press .
5. Highlight your desired option and press .
6. Use your navigation key to select a setting and press .

Tip: You can select **Once** or **Repeat Alert** if you select **10-4 Calls**, **10-4 Missed**, **Voicemail**, or **Messaging**. **Repeat Alert** sounds an alert every two minutes for twenty minutes. (For 10-4 Calls, it sounds for 20 seconds continuously.)

Silence All

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Sounds** and press .
 4. Highlight **Ringer/Key Vol.** and press .
 5. Highlight **Ringer Volume** and press .
 6. Press the navigation key down until “Silence All” appears on the display and press .
- ▶ To deactivate this feature, select a volume level you wish during step 6 above.







Tip: When Ringer Volume is set as Silence All, other items are changed to Off and cannot be highlighted by cursor.

Shortcut: To activate Silence All, you can press the Side Up/Down key down repeatedly until **Silence All** appears on the display screen.


Display Settings

Changing the Greeting







To display or change your custom greeting:

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Display** and press .
 4. Highlight **Greeting** and press .
 5. Highlight **Custom** and press .
- ▶ You can customize the greeting. (See “Selecting a Character Input Mode” on page 22.)
6. Press .

To display the default greeting:

1. Follow steps 1-4 above.
2. Highlight **Default** and press .

Changing the Backlight Time Length

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Display** and press .
4. Highlight **Backlight** and press .
5. Highlight **Main LCD**, **Key** or **Sub LCD** and press .
6. Select **Always On**, **Always Off** or your defined time length and press .










Note: The **Always On** setting returns to the previous value the next time you turn on the phone.

Note: Long backlight settings affect the battery's talk and standby times.








Note: Depending on the Sleep Mode setting, the LCD backlight turns off even the setting is **Always On**. (See page 42 for details.)

Changing the Display Screen






Your new phone offers animation for what you see on the display screen when in Standby mode, Outgoing Calls or Service Search.

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Display** and press .
 4. Highlight **Animation** and press .
 5. Highlight **Standby**, **Outgoing Calls**, or **Service Search** and press .
 6. Press , select your desired menu, and press .
- ▶ For Standby, also set animation starting time. Select the option under **after** and press , then highlight your desired setting time and press .
 - ▶ To deactivate this feature, select **Off** during step 6 above.


Changing the Display for Incoming Calls

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Display** and press .
4. Highlight **Incoming Calls** and press .
5. Press , select your desired menu, and press .
6. Highlight your desired color or image and press .

Changing the Display for the Standby Mode









1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Display** and press .
 4. Highlight **Standby Display** and press .
 5. Select your desired item and press .
- ▶ **Screen Saver** selects the screen saver to display.
 - ▶ **Calendar** displays the Calendar.
 - ▶ **Digital Clock** displays the local time in digital view.
 - ▶ **World Clock** displays the time of the selected city or country along with the local time. You can scroll the World Clock list and change the country by pressing the navigation key right or left. When applicable, the **Summer** (left softkey)/**Standard** (right softkey) can be used to change between summer and standard time.

Tip: You can also display the World Clock from Tools/Extras menu. See "Using the World Clock" on page 77.






- ▶ **Default** sets this feature to default.
6. After following each system prompt or confirming the preview display, press  to save the setting.

Tip: In a no-service area, the signal search display appears instead of the display for standby mode.






Changing the Screen Saver

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Display** and press .
 4. Highlight **Standby Display** and press .
 5. Highlight **Screen Saver** and press .
 6. Press , select your desired menu, and press .
 7. Highlight your desired screen saver and press .
- To see a display preview, press **Preview** (right softkey) during step 6 above.
8. Press **Save** (left softkey) to save the screen saver.







Changing the Background

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Display** and press .
4. Highlight **Background** and press .
5. Select your desired color and press .

Changing the Contrast

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Display** and press .
4. Highlight **Contrast** and press .
5. Select your desired contrast and press .

Changing the Font Size






1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Display** and press .
4. Highlight **Font Size** and press .
5. Highlight either **Messaging** or **Browser** and press .
6. Select your desired font size.
 - ▶ Press **Preview** (right softkey) to display a font size example.
7. Press  to set the selected font.



Tip: From the preview display, you can switch your desired font size by pressing the navigation key right or left.

Location Settings

Your phone is equipped with a Location feature which will allow the network to detect your position, making some Applications easier to use. Turning Location off will hide your location from everyone except 911.

Note: Even if the Location feature is enabled, no service may use your location without your expressed permission.







1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Location** and press . (You will see a message on the display.)
4. Press  or **OK** (left softkey).
 - ▶ Press **Cancel** (right softkey) to return to the setting display.
5. Select **On** and press .
 - ▶ To deactivate this feature, select **Off** during step 5 above.

Tip: When the Location feature is on, your phone's standby screen will display the  icon. When Location is turned off, the  icon will be displayed.

TTY Use

A TTY (also known as a TDD or Text Telephone) is a telecommunications device that allows people who are deaf or hard of hearing, or who have speech or language disabilities, to communicate via a telephone.

Your phone is compatible with select TTY devices. Please check with the manufacturer of your TTY device to ensure that it supports digital wireless transmission. Your phone and TTY device will connect via a special cable that plugs into your phone's headset jack. If this cable was not provided with your TTY device, contact your TTY device manufacturer to purchase the connector cable.

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Others** and press .
4. Highlight **TTY** and press . (You will see a message on the display.)
5. Press  or **OK** (left softkey) to continue.
6. Select **Enable** or **Disable** and press .

Note: When you connect TTY devices, your phone will display  in TTY mode.







Note: If TTY mode is enabled, the audio quality of non-TTY devices connected to the headset jack may be impaired.

IMPORTANT NOTICE: 911 Emergency Calling

It is recommended that TTY users make emergency calls by other means including cellular and landline communications.

Airplane Mode

When your phone is in Airplane mode, it cannot send or receive any calls (except for 911 dialing) or access online information. You may still use the phone's other features, such as Voice Memo, Calculator, Calendar, etc., while you are in Airplane mode.

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Others** and press .
4. Highlight **Airplane Mode** and press . (You will see a message on the display.)
5. Press  or **OK** (left softkey).
- ▶ Press **Cancel** (right softkey) to return to the setting display.
6. Select **On** and press .
- ▶ To deactivate this feature, select **Off** during step 6 above.


Note: While in Airplane mode, your phone's standby screen will display "Phone Off."

Phone Setup Options


My Shortcut

Your phone offers you the option of assigning a shortcut key to a favourite or often-used function. Pressing the navigation key left in standby mode will launch your user-defined shortcut.



To assign your shortcut key:

1. Press the navigation key left.
2. Select an unassigned number and press  or **Add** (right softkey).
3. Select your desired menu and press **Set** (right softkey).

To edit the shortcut name:







1. Press the navigation key left.
2. Select your desired menu and press **Options** (right softkey).
3. Highlight **Edit Name** and press .
4. Edit the name and press **OK** (left softkey).
5. Press **Save** (left softkey) to save the name.

To unassign the shortcut:



1. Press the navigation key left.
 2. Select your desired menu and press **Options** (right softkey).
 3. Highlight **Reset** and press .
 4. Select **Yes** and press .
- To unassign all shortcuts, select **Reset All** during step 3 above.






Auto Answer Mode

This feature sets the phone to automatically pick up incoming calls after 5 seconds.

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Others** and press .
 4. Highlight **Auto Answer** and press .
 5. Highlight **Car Kit/Headset** or **Speakerphone** and press .
 6. Select **5 Seconds** and press .
- To deactivate this feature, select **Off** during step 6 above.

Setting Any Key Answer

This feature allows you to answer incoming calls by pressing any key (except , , softkeys, and sidekeys).

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Others** and press .
 4. Highlight **Any Key Answer** and press .
 5. Select **On** and press .
- To deactivate this feature, select **Off** during step 5 above.






Headset Mode

This feature allows you hands-free phone use. Set the headset mode to Voice Call or 10-4 and press the Turbo Button (the operation button) on the headset to activate useful functions.

To connect the headset:

- ▶ Simply plug the headset into your phone's headset jack.

To set headset mode:

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Others** and press .
4. Highlight **Headset Mode** and press .
5. Select **Voice Call** or **10-4** and press .

- ▶ To deactivate this feature, select **Off** during step 5 above.

With the headset:

- ▶ **Voice Call:** Press the Turbo Button to activate Voice dial. Press twice to redial the last call. Press and hold the button to activate the Voice Memo.
- ▶ **10-4:** Press and hold the Turbo Button to redial the last 10-4 call.






Tip: For an explanation of the Headset Mode setting, press  (right softkey) during step 5 above.

Note: If your headset doesn't have a Turbo Button, set headset mode to Off.

Note: When using the headset, **DO NOT** set the volume too high. Listening at high volume for an extensive period of time may cause hearing loss.






Sleep Mode

This feature helps conserve your battery power by restricting the display.

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Display** and press .
 4. Highlight **Sleep Mode** and press .
 5. Highlight your desired option and press .
- To deactivate this feature, highlight **Off** during step 5 above.






Setting Message Notification

You can see an icon or an icon and message notification when you receive a text message or Voicemail.

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Messaging** and press .
4. Highlight **Notification** and press .
5. Select **Msgs and Icon** or **Icon Only** and press .

Setting Push Options








This feature allows you to connect Web Alerts page automatically if possible when you receive. See page 121 for Web Alerts.

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Messaging** and press .
 4. Highlight **Push Options** and press .
 5. Select **Yes** and press .
- To deactivate this feature, select **No** during step 5 above.

Editing Canned Messages

Your phone can store canned messages for use with text messaging. You can edit your phone's default canned messages through the Settings menu.

To edit a canned message:

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Messaging** and press .
4. Highlight **Canned Msgs** and press .
5. Select the message you want to edit and press .
- ▶ To reset all messages, press **Options** (right softkey), select **Reset All Msgs**, and press  during step 5 above.
6. Use your keypad to edit the message and press **OK** (left softkey) or  to save your changes. ("Canned Msgs Saved" will display.)







To change the language of the canned messages:

1. Follow steps 1-4 above.
2. Press **Options** (right softkey) and select **Select Language**.
3. Select **English** or **French**.






Note: For information on editing text, see "Selecting a Character Input Mode" on page 22.

Setting Your Callback Number

With this feature, you can send a callback number with your text message.






1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Messaging** and press .
 4. Highlight **Send Callback#** and press .
 5. Select an option from the following and press .
- ▶ **None** to send no callback number.
 - ▶ **My Phone#** to send your phone number.
 - ▶ **Other** to send a defined number. To set a number, enter a phone number and press .

Setting the Current Time

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Others** and press .
4. Highlight **Set Time/Date** and press .
5. Set the current time and date and press .








Note: This feature is only available when you are in an area with no digital network available.

Changing the Menu Language

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Others** and press .
4. Highlight **Language** and press .
5. Select **Français** and press .

Setting Your Signature

This feature allows you to send a message with your signature.







1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Messaging** and press .
4. Highlight **Signature** and press .
5. Press , select **On**, and press .
6. Select **Text** and press .
7. Enter your signature and press **OK** (left softkey).
8. Press **Save** (left softkey) to save your signature.

Note: You can insert your signature even when your signature setting is off. Press **Mode** (right softkey) and select **Signature** while composing your message.




Setting the Open/Close Flip Option

This feature enables you to answer an incoming call by opening the flip or to end a call by closing the flip.

To activate the Open Flip feature:

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Others** and press .
 4. Highlight **Open/Close Flip** and press .
 5. Highlight **Open** and press .
 6. Select **Answer Call** and press .
- ▶ To deactivate this feature, select **No Action** during step 6 above.






To activate the Close Flip feature:

1. From step 5 above, select **Close** and press . (You will see a message on the display.)
 2. Press  (left softkey) to continue.
 3. Select an option from the following and press .
- ▶ **End Call** to end the call.
- ▶ **Mute** to continue the call. Your voice is muted, however you can hear the caller's voice from the speaker.

Note: The Close Flip feature does not apply during 10-4 calls or when you are using the speakerphone, a headset, or a car kit.

Setting the Side Key Guard







This feature enables you to lock the Side Up/Down key while the flip is closed.

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Others** and press .
 4. Highlight **Side Key Guard** and press .
 5. Select **On** or **Off** and press .
- **Key Guard** appears when the Side Up/Down key is pressed while the Side Key Guard is enabled.

Note: This feature does not apply when the flip is open.

Setting Up Key Press Echo




With this feature, your phone echoes the number when you press the keypad. This feature is available when you are in standby mode.

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Sounds** and press .
4. Highlight **Others** and press .
5. Highlight **Key Press Echo** and press .
6. Select **On** or **Off** and press .

3. Security

Accessing the Security Menu




You must enter your lock code to view the Security menu.

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Security** and press .
4. Enter your lock code.

Tip: If you can't recall your lock code, try using the last four digits of your phone number or 0000.

Locking Your Phone

When your phone is locked, you can only receive incoming calls or make calls to 911, Customer Service, or special numbers.

1. From the Security Menu display (See “Accessing the Security Menu” above), highlight **Lock Phone** and press .
2. Highlight **Lock Now** or **On Power-up** and press .
3. Depending on your preference, highlight either **Full Lock** or **Excp. Incom.Calls** and press .
 - ▶ **Full Lock:** All phone calls except for emergency number, Customer Service, or special numbers cannot be made. No phone calls can be received except for special numbers.
 - ▶ **Excp. Incom.Calls:** All phone calls except for emergency number, Customer Service or special numbers cannot be made, but all incoming calls can be received.





Tip: If you want to cancel the “On Power-up” setting before turning the phone off, select **Unlocked** during step 2 above.

Unlocking Your Phone

1. Press **Unlock** (left softkey).
2. Enter your lock code.



Lock Services

With this feature, you can choose to restrict access to the Internet and incoming and outgoing voice calls and 10-4 calls.

1. From the Security Menu, select **Others** and press .
2. Highlight **Lock Services** and press .
3. Highlight **Voice Calls**, **Internet**, or **10-4** and press .
4. Highlight **Locked** and press .

- ▶ To deactivate this feature, select **Unlocked** during step 4 above.


Changing the Lock Code

1. From the Security Menu display (See “Accessing the Security Menu” on the previous page), highlight **Others** and press .
2. Highlight **Change Lock** and press .
3. Enter a new lock code, “1234” for example.
4. Reenter the new code.

Calling in Lock Mode





You can place calls to 911, Customer Service, and to your special numbers when in lock mode.

To place an outgoing call in lock mode:

- ▶ To call an emergency number, special number, or Customer Service, enter the phone number and press .

Restricting Calls

You can restrict phone numbers your phone dials or receives. (The Restrict Calls setting does not apply to 911 or Customer Service.)

1. From the Security Menu display (See “Accessing the Security Menu” on page 48), highlight **Others** and press .
2. Highlight **Limit Use** and press .
3. Highlight **Outgoing Calls** or **Incoming Calls** and press .
4. Highlight your desired option and press .

Options:






- ▶ **Allow All:** You can make or receive all calls.
- ▶ **Phone Book Only:** Only Contacts entries, Voicemail or special numbers (see below) are available to make or receive calls.
- ▶ **Special #s Only:** Only three special numbers are available to make or receive calls.

Note: Restricted incoming calls are forwarded to voicemail.




Using Special Numbers

You can save three special numbers in addition to your Contacts entries (the same number may be in both directories). You can make and receive calls from special numbers even when your phone is locked.




To add or replace a special number:

1. From the Security Menu display (See “Accessing the Security Menu” on page 48), highlight **Others** and press .
 2. Highlight **Special #s** and press .
 3. Highlight the box under the entry number and press .
 4. Enter the number you wish to add and press .
- or –
- Press **Options** (right softkey), then highlight **From Phone Book** or **Voicemail** and press .

Erasing the Contacts Directory


1. From the Security Menu display (See “Accessing the Security Menu” on page 48), highlight **Erase Ph. Book** and press .
2. Press  (left softkey) to continue.
3. If you're sure you want to erase your Contacts, highlight **Yes** and press .

Erasing the Downloads

1. From the Security Menu display (See “Accessing the Security Menu” on page 48), highlight **Erase Download** and press .
 2. Press  (left softkey) to continue.
 3. If you're sure you want to erase all data downloaded from the Web, highlight **Yes** and press .
- If you have assigned downloaded data, the function returns to its default setting.

Resetting Your Phone

Resetting the phone restores all the factory defaults, including the ringer types and display settings. The Contacts, Call History, Scheduler, and Messaging are not affected.




1. From the Security Menu display (See “Accessing the Security Menu” on page 48), highlight **Reset Phone** and press .
2. Press  (left softkey) to continue.
3. If you're sure you want to reset your phone, highlight **Yes** and press .

4. Roaming

Understanding Roaming

Recognizing Icons on the Display Screen

Your phone's display screen always lets you know when you're off the home network and whether your phone is operating in analog or digital mode. The following chart indicates what you'll see depending on where you're using your phone.

Network	Indicator
Digital Home	
Analog Home	
Digital Roaming	
	Digital Roam
Analog Roaming	
	Analog Roam

Roaming on Digital Networks

When you're roaming on digital networks, your call quality and security will be similar to the quality you receive when making calls on the home network. You may not be able to access certain features, such as Web.

Roaming on Analog Networks

When you roam on analog networks, you will experience a similar quality provided by other analog carriers today. Although some features, such as Web, will be unavailable, you can still make and receive calls. You will experience a few differences:

- ▶ You are more likely to experience cross-talk, fade-out, and dropped calls.
- ▶ Some features which are standard on the home network are unavailable.
- ▶ There are security and privacy risks (eavesdropping and cloning) that exist with conventional analog services today.
- ▶ Your battery needs recharging sooner when you use your phone for analog roaming.

Note: If you're on a call when you leave the home network and enter an area where roaming is available (whether digital or analog), your call is dropped. If your call is dropped in an area where you think service is available, turn your phone off and on again to reconnect to the home network.





Note: When using your phone in analog mode, the handset may feel warm. This behaviour is normal for analog operation.

Setting Your Phone's Roam Mode

Your phone allows you to control your ability to roam. By using the **Roaming** menu option, you can determine which signals your phone accepts.

Set Mode

Choose from four different settings on your dual band/tri mode phone to control your roaming experience:

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **Roaming** and press .
 4. To select an option, select it and press .
- ▶ **Automatic:** This setting seeks Service. When Service is unavailable, the phone searches for an alternate system.
 - ▶ **Home Only:** This setting allows you to access the home network only and prevents roaming on other networks.
 - ▶ **Digital Only:** This setting forces the phone to seek a digital roaming system.
 - ▶ **Analog Only:** This setting forces the phone to seek an analog roaming system.

5. Menu Navigation

Viewing the Menus

Menu Diagram

Menus let you check or change your phone settings. The following outline shows your phone's menu structure.

1. Call History

1. Outgoing
2. Incoming
3. Missed
4. Erase History

2. Contacts

1. Find/Add Entry
2. Speed Dial #s
3. My Phone#
4. Services

3. Messaging

1. Send Text
2. Text Msgs
3. Web Alerts
4. Voicemail

4. Web

5. Downloads

- Games
- Ringers
- Screen Savers
- Applications
- Dynamic 1-10 (If applicable)
- Others (If applicable)

6. Settings

1. Sounds
2. Display
3. Internet
4. 10-4
5. Location
6. Roaming
7. Messaging
8. Security
9. Others
10. Phone Info




7. Tools/Extras

1. Voice Services
2. Calendar
3. Alarm Clock
4. Calculator
5. Stop Watch
6. World Clock

6. Managing Call History

Viewing History

You'll find the Call History feature very helpful. It is a list of the last 20 phone numbers (or Contacts entries) for each calls that you placed, accepted, or missed. Call History makes redialing a number fast and easy. It is continually updated as new numbers are added to the beginning of the list and the oldest entries are removed from the bottom of the list.

1. Press  to access the main menu.
2. Highlight **Call History** and press .
3. Highlight **Outgoing**, **Incoming**, or **Missed** and press .








Tip: You can switch the Voice Call history to the 10-4 call history by pressing **10-4** (left softkey). To return to the Voice Call history, press **Voice Call** (left softkey).

Call History Options

For additional information and options on a particular call, highlight a Call History entry and press **Options** (right softkey).









- ▶ **Call** to dial the phone number.
- ▶ **Call:Speaker On** to dial the phone number in speakerphone mode.
- ▶ **Send Text** to send a text message. See page 112 for details.
- ▶ **Save Phone#** to save the phone number (if applicable). If the caller's phone number is already saved in your Contacts list, **Go to Phone Book** appears. (See "Saving a Phone Number From Call History" on the next page.)
- ▶ **Prepend** to add numbers to the beginning of the phone number. (See "Prepending a Phone Number From Call History" on page 58.)
- ▶ **Copy to Personal** to copy the phone number to the 10-4 Personal List. (Only appears when 10-4 mode is set to Enable and the number does not match any stored entry in your Personal List.)
- ▶ **Erase** to erase the entry.

Making a Call From Call History

1. Press  to access the main menu.
2. Highlight **Call History** and press .
3. Highlight **Outgoing**, **Incoming**, or **Missed** and press .
4. Highlight the entry you want to call by scrolling through the list.
5. Press  or .
- or –
- Press  (right softkey), highlight **Call** or **Call:Speaker On**, and press .

Note: You cannot make calls from Call History to entries identified as No ID or Restricted.







Saving a Phone Number From Call History

1. Press  to access the main menu.
2. Highlight **Call History** and press .
3. Highlight **Outgoing**, **Incoming**, or **Missed** and press .
4. Highlight the call history entry you want to save.
5. Press  (right softkey) to display the options.
6. Highlight **Save Phone#** and press .
7. Highlight the appropriate label (Mobile, Home, Work, Pager, Fax, Other, or No Label) and press .
8. Enter a name and press .
- Once you have stored an entry in the Contacts list, you are prompted to select from the following entry modes:
 - ▶ **New Name** to enter a name directly.
 - ▶ **From Ph. Book** to select a name from Contacts entry list.
9. Press  (left softkey).



Note: You cannot save phone numbers already in your Contacts list or from calls identified as No ID or Restricted. If the selected entry has already been stored in the Contacts list, **Go to Phone Book** appears during step 3 above.

Prepending a Phone Number From Call History







If you need to make a call from Call History and you happen to be outside your local area code, you can add the appropriate prepending by following these steps:

1. Press  to access the main menu.
2. Highlight **Call History** and press .
3. Highlight **Outgoing, Incoming, or Missed** and press .
4. Highlight a call history entry and press **Options** (right softkey).
5. Highlight **Prepend** and press .
6. Enter the digits you want to add to the number.
7. Press  or  to place a call.

To select an option, press **Options** (right softkey), highlight it and press .




- ▶ **Call** to dial the phone number.
- ▶ **Call:Speaker On** to dial the phone number in speakerphone mode.
- ▶ **Save Phone#** to store the phone number in your Contacts directory.
- ▶  **Hard Pause** to insert a hard pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 19.)
- ▶  **2-Sec. Pause** to insert a 2-second pause. (See “Dialing and Saving Phone Numbers With Pauses” on page 19.)

Erasing Call History

1. Press  to access the main menu.
2. Highlight **Call History** and press .
3. Highlight **Erase History** and press .
4. Highlight **Outgoing, Incoming, Missed, or All** and press .
5. Select **Voice Calls** or **10-4** and press .
- ▶ **Voice Call** to erase Call History for Voice Calls.
- ▶ **10-4** to erase Call History for 10-4.
6. Select **Yes** and press .








7. Contacts Directory

Displaying the Contacts List

- ▶ Press the navigation key right.
- or –
- 1. Press  to access the main menu.
- 2. Highlight **Contacts** and press .
- 3. Highlight **Find/Add Entry** and press .

Adding a New Contacts Entry

Your phone can store up to 300 Contacts entries. Contacts entries can store up to a total of 500 phone numbers and each entry's name can contain 16 characters.






- 1. Press  to access the main menu.
- 2. Highlight **Contacts** and press .
- 3. Highlight **Find/Add Entry** and press .
- ▶ Press the navigation key right for the shortcut (steps 1 through 3).
- 4. Highlight **<Add Contact>** and press .
- 5. Enter a name and press .
- 6. Select a label by using your navigation key and press .
- 7. Enter the phone number or address and press .
- 8. Press **Save** (left softkey).

Finding Contacts List Entries



There are several ways to display your Contacts entries: by name, by speed dial number, by 10-4 list, and by voice dial numbers. Follow the steps outlined in the sections below to display entries from the Contacts list menu.

Finding Names

To find Contacts list entries by name:




1. Press  to access the main menu.
2. Highlight **Contacts** and press .
3. Highlight **Find/Add Entry** and press .
 - ▶ Press the navigation key right for the shortcut (steps 1 through 3).
4. Scroll to select your desired entry or press **Options** (right softkey), select the option from the following and press .
(The options appear alternately.)
 - ▶ **Find:First Name** will search the entry by first name.
 - ▶ **Find:Full Name** will search the entry by part of the name.
5. Enter the first letter of the name or part of the name. (The display shows the entries beginning with the letter entered.)
6. To display the entry's details, select your desired entry and press .

To find 10-4 List entries:






1. From standby mode, press the navigation key right to display your Contacts list.
2. Press **Go to** (left softkey). Highlight your desired 10-4 list and press .
 - ▶ **Phone Book** to display the Contacts list.
 - ▶ **Company List** to display the Company List.
 - ▶ **Company Groups** to display the Company Group List.
 - ▶ **Personal List** to display the Personal List.
 - ▶ **Personal Groups** to display the Personal Group List.
3. Scroll through the list and press  to select your desired entry.

Note: The **Go to** (left softkey) option does not appear when 10-4 mode is set to Disable (see “Changing 10-4 Mode” on page 92).



Finding Speed Dial Numbers

1. Press  to access the main menu.
2. Highlight **Contacts** and press .
3. Highlight **Speed Dial #s** and press . (The Speed Dial numbers list appears.)

Finding Voice Dial Numbers

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Voice Dial** and press .
5. Highlight **Review** or **Review:Speaker** and press . (The Voice Dial numbers list appears.)

Contacts List Entry Options

To access Contacts options, display the entry list, highlight an entry and press , then select a phone number and press **Options** (right softkey). To select an option, highlight it and press .








- ▶ **Edit** to edit your desired label.
- ▶ **Call** to dial the phone number.
- ▶ **Call:Speaker On** to dial the phone number in speakerphone mode.
- ▶ **Send Text** to send a text message. (See page 112 for details.)
- ▶ **Call Alarm** to set a call alarm to the entry (see page 70).
- ▶ **Set Speed Dial** to set the Speed Dial to the entry (see page 63).
- ▶ **Set Voice Dial** to set a Voice Dial to the entry (see page 84).
- ▶ **Prepend** to alter a phone number by adding numbers to the beginning of the entry. (See “Prepending a Phone Number From Call History” on page 58.)
- ▶ **Copy to Personal** to copy the phone number to your 10-4 Personal List. (Only appears when 10-4 mode is set to Enable and the number does not match any stored entry in your Personal List.)

Tip: You can view the next entry by pressing the navigation key right or view the previous entry by pressing the navigation key left.

Assigning Speed Dial Numbers

With this feature you can dial Contacts Directory entries with one key press for locations 2-9. Save your memory locations 2-9 for speed dialing your most commonly used phone numbers. Speed Dial numbers must be stored in your Contacts to use this feature.





To set Speed Dial:

1. Press  to access the main menu.
 2. Highlight **Contacts** and press .
 3. Highlight **Speed Dial #s** and press .
 4. To select a corresponding speed dial number from 2-9, highlight an unassigned number and press .
 5. Select an entry from the list and press .
 6. Select the phone number you want to set as a speed dial and press .
- ▶ When you highlight an assigned number and press , you'll be asked whether you want to overwrite the assigned number. Select **Yes** to overwrite or **No** to cancel.



To use Speed Dial:

- ▶ From standby mode, just press and hold the appropriate key.

Editing a Contacts Entry

1. Press the navigation key right.
2. Highlight the entry you wish to edit and press .
3. Highlight a phone number, press **Options** (right softkey), highlight **Edit**, and press .
– or –
Highlight an email address or Web address and press **Edit** (right softkey).
4. Select the field you want to edit and press .
5. Edit the entry by using your keypad and press .
6. Press **Save** (left softkey) to save your changes.





Erasing a Contacts Entry From the List

1. Press the navigation key right to display the Contacts list.
2. Highlight the entry you wish to delete using the navigation key.
3. Press **Options** (right softkey).
4. Highlight **Erase Contact** and press .
5. Highlight **Yes** and press .




Selecting a Ringer/Image Type for an Entry

You can assign a ringer/image type to a Contacts entry so you can identify the caller by the ringer or image type.

To select a ringer type for an entry:



1. Press the navigation key right.
 2. Select the entry you want to set as the incoming ringer and press .
 3. Highlight a phone number, press **Options** (right softkey), highlight **Edit**, and press .
– or –
Highlight an Email address or Web address, and press **Edit** (right softkey).
 4. Highlight **Ringer** and press .
 5. Select a ringer type by scrolling up or down and press .
 6. Press **Save** (left softkey).
- ▶ To confirm the ringer, highlight **Ringer** and press **Play** (right softkey).

To select an image type for an entry:

1. Follow steps 1-3 above.
 2. Highlight **Picture ID** and press .
 3. Select a menu by scrolling up or down and press .
 4. Press **Save** (left softkey).
- ▶ To see a display preview of an image, press **Preview** (right softkey) during step 4 above.
- ▶ If you set an animation ringer (indicated with  icon) and an image, your phone plays the ringer (audio) of the animation ringer and displays the image you selected.

Secret Contacts Entries






You can hide an entry's phone number(s) by making them secret, which requires your lock code to edit the entry. The entry name is still displayed, but the entry's phone numbers are replaced by "<Secret>".

1. Press the navigation key right.
 2. Scroll to the Contacts entry you want to tag Secret.
 3. Press **Options** (right softkey) to display the menu options.
 4. Highlight **Set Secret** and press .
 5. Enter the 4-digit lock code.
 6. Select **On** and press .
- To make an entry public, select **Off** during step 6 above.

Tip: If you can't recall your lock code, try using the last four digits of your phone number, or 0000.

Dialing Services

You must be in digital mode to access Services.

1. Press  to access the main menu.
2. Highlight **Contacts** and press .
3. Highlight **Services** and press .
4. Highlight **Cust Service** or **Dir Assistance** and press .
5. Press **TALK** or **SPEAKER**.
- or -
Press **Options** (right softkey), highlight **Call** or **Call:Speaker On** and press .




8. Personal Organizer

Managing Schedules

Calendar

Use the Calendar to remind you of events or important calls you need to make. You can schedule up to 100 events, 15 Call Alarms and 20 To Do Items.

Displaying Your Calendar



1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Calendar** and press .

Note: In a no-service area or an analog service area, it's necessary to set the actual time and date to use the Calendar function after removing and installing your battery.

Setting Holidays





You can set your personal holidays by displaying the date in red on the Calendar display. The default holidays displayed in red are Sundays and National holidays.

Note: You can set holidays from Jan 1, 2000 to Dec 31, 2020.


1. From the Calendar display, highlight the day you want to set to the holiday by using the navigation key (Left: previous day, Right: next day, Up: previous week, Down: next week, Side Up/Down key: previous/next month).
2. Press **Options** (right softkey), highlight **Holiday**, and press .
3. Highlight **Set Date** or **Set Weekly**, and press .

Tip: The current day is framed by a rectangle.

Adding an Event to the Scheduler

1. From the Calendar display, highlight the day you want to add an event by using the navigation key and press .
2. Press **Options** (right softkey) to display the options.
3. Highlight **Add Event** and press .
4. Highlight **Schedule** and press .
5. Enter the description and press  (or press **Mode** [right softkey] to select a description from “From To Do List”).

Note: The “From To Do List” option will not appear if there are no items stored in the To Do List. See “Adding To Do Items” on page 73 for details.

6. Select the following options and press :
 - ▶ **Description** Entering a description of your event (up to 14 characters).
 - ▶ **From** Scheduling the start time.
 - ▶ **To** Scheduling the end time.
 - ▶ **Location** Editing the location of your event (up to 14 characters).
 - ▶ **Alarm** Select the ringer you wish to set.
 - ▶ **Alarm Time** Editing the alarm time (number of hours or minutes before the event starts). Default alarm time is 10 minutes.
 - ▶ **Repeat** Repeating the event. Select **None**, **Daily**, **Weekly**, **Monthly**, or **Yearly**.
7. Press **Save** (left softkey) to schedule the event.

Tip: Press the navigation key up or down to scroll by week through the Scheduler calendar, and the Side Up/Down key to scroll by month.

Tip: The date you have scheduled events for is indicated by “▶”.




Event Alerts

There are several ways your phone alerts you of scheduled events.

- ▶ By playing the alert tone (depending on the Alert and Ringer Volume setting).
- ▶ By blinking the LED.
- ▶ By displaying the event's description on the Main LCD when the flip is open.
- ▶ By lighting the LCD backlight (depending on the backlight setting).





Event Alert Menu

When your phone is turned on and you have an event alarm scheduled, your phone alerts you and displays the event summary.




1. Press  or **View** (left softkey) to silence the alarm and see the event details.
2. Highlight the unchecked event and press  to see the event details, or press **Options** (right softkey) for following options. To select an option, highlight it and press .
 - ▶ **Snooze** to repeat the alarm in ten minutes.
 - ▶ **Exit** to exit the options.

Note: If you press **Exit** (left softkey) during step 2 above, you are prompted to erase the unchecked event. Select **Yes** to erase or **No** to cancel.





Viewing Events

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Calendar** and press .
4. Select the date for which you set events and press .
(The selected day's events list will display.)

Editing an Event

1. From the Event list display, highlight one of the events and press .
2. Select the box under each item you want to edit and press . (See “Adding an Event to the Scheduler” on page 68 for options.)
3. Enter or select a new setting and press .
4. Press **Save** (left softkey).

Adding a Call Alarm to the Scheduler

1. From the Calendar display, highlight the day you want to add an event by using the navigation key and press .
2. From the event list display, press **Options** (right softkey) to display the options.
3. Highlight **Add Event** and press .
4. Highlight **Call Alarm** and press .
5. Enter the phone number directly or press **Options** (right softkey) for the following options:
 - ▶ **From Phone Book** select the number from your Contacts list.
 - ▶ **Voicemail** select the number for voicemail access.
6. Select the box under the following items and press :
 - ▶ **Time/Date** Editing the start time/date.
 - ▶ **Alarm** Selecting the ringer alarm.
 - ▶ **Repeat** Repeating the Call Alarm. Select **None**, **Daily**, **Weekly**, **Monthly**, or **Yearly**.
7. Press **Save** (left softkey).

Tip: You can also add a Call Alarm from the Contacts menu (see “Contacts List Entry Options” on page 62).




Call Alarm Alerts

There are several ways your phone alerts you of scheduled call alarms.

- ▶ By playing the alert tone (depending on the Alert and Ringer Volume setting).
- ▶ By blinking the LED.
- ▶ By displaying the call alarm notification on the Main LCD when the flip is open.
- ▶ By lighting the LCD backlight (depending on the backlight setting).




Call Alarm Menu

When your phone is turned on and you have scheduled a call alarm, your phone alerts you and displays the name or phone number.



1. Press  or **View** (left softkey) to silence the alarm and see the unchecked event list.
2. Highlight the unchecked call alarm and press  to see the call alarm details, or press **Options** (right softkey) for following options. To select an option, highlight it and press .
- ▶ **Call** to dial the scheduled phone number.
- ▶ **Call:Speaker On** to dial the scheduled phone number in speakerphone mode.
- ▶ **Snooze** to repeat the alarm in ten minutes.
- ▶ **Save Phone#** to save the scheduled phone number in your Contacts list. **Go to Phone Book** appears when the number is already in your Contacts list.

Note: If you press **Exit** (left softkey) during step 2 above, you are prompted to erase the unchecked event. Select **Yes** to erase or **No** to cancel.




Editing a Call Alarm

1. From the Event list display, highlight one of the call alarms and press .
2. Select the box under each item you want to edit and press . (See “Adding a Call Alarm to the Scheduler” on page 70 for options.)
3. Enter or select a new setting and press .
4. Press **Save** (left softkey).

Erasing a Day's Event or Call Alarm





1. From the Event list display, highlight one of the events or call alarms and press **Options** (right softkey).
2. Highlight **Erase Event** and press .
3. Highlight **Yes** and press .

Viewing a Future/Past Day's Scheduled Events

1. From the Event list display, press **Options** (right softkey).
2. Highlight **Go To Date** and press .
3. Enter the date by using numeric keys and the navigation key and press  or **OK** (left softkey).
4. Press  again to view the day's Event List.

Adding To Do Items




Your phone can store and manage 20 To Do items.

1. From the Calendar display, press **Options** (right softkey).
2. Highlight **To Do List** and press .
3. Press **Options** (right softkey).
4. Highlight **Add Item** and press .
5. Enter the description and press  (up to 14 characters).
6. Highlight **Priority** and press  to edit the To Do's priority.
You can select from **Normal**, **!Urgent**, or **√Done**.
7. Press **Save** (left softkey).



Viewing To Do List

1. From the Calendar display, press **Options** (right softkey).
2. Highlight **To Do List** and press .
- ▶ To see the details of each To Do item, select an item and press .





Editing To Do Items

1. From the To Do list display, highlight the item you want to edit and press .
2. Highlight the box you want to edit and press .
3. Edit description or change the priority and press .
4. Press **Save** (left softkey).

Adding a To Do Item to the Schedule



1. From the To Do List display, highlight the item you want to add to schedule and press **Options** (right softkey).
2. Highlight **Add To Schedule** and press .
3. Enter the description using your keypad and press . (See "Adding an Event to the Scheduler" on page 68 for entering.)
4. Press **Save** (left softkey).
- ▶ **Add To Schedule** extracts the item from the To Do list and makes it a scheduled event.

Deleting Items from the To Do List



1. From the To Do List display, highlight the item you want to erase and press **Options** (right softkey).
2. Highlight your desired option and press .
 - ▶ **Erase Item** erases an item from the To Do List.
 - ▶ **Erase Selection** erases the selected To Do items at one time. Press  to check the box next to To Do item and press **Erase** (left softkey) to erase. To check all boxes, press **Options** (right softkey) and highlight **Check All** and press .
 - ▶ **Erase All** erases all the To Do items.
3. Highlight **Yes** and press .

Note: If you have saved a To Do List item to the scheduler, deleting it from the To Do List will not delete it from the scheduler. To remove an item saved to the scheduler, see “Purging All Events, Call Alarms or To Do List Items” on page 75.


Viewing Memory in Your Scheduler

1. From the Calendar display, press **Options** (right softkey).
2. Highlight **View Memory** and press .
3. Highlight **Schedule**, **Call Alarm**, or **To Do List** and press .





Purging All Events, Call Alarms or To Do List Items

1. From the Event list display, press **Options** (right softkey).
2. Highlight **Erase Memory** and press .
3. Highlight one Options item and press .






Options:

- ▶ **Erase Old** deletes the old events, call alarms, and completed To Do items.
 - ▶ **Erase All** deletes all the events, call alarms, and To Do items.
4. Highlight **Yes** and press .





Displaying Phone Information

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Phone Info** and press .
4. Highlight **My Phone#** and press .





Finding Icon Definition

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Phone Info** and press .
4. Highlight **Help** and press .
5. Highlight the item for which you want to see the explanation and press .

Displaying the Version Information

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Phone Info** and press .
4. Highlight **Version** and press .







Displaying Advanced Information

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Phone Info** and press .
4. Highlight **Advanced** and press .

Using Your Phone's Tools

Using the Alarm Clock

To use the alarm clock:

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Alarm Clock** and press . (A caution appears on the display.)
4. Press **Continue** (left softkey) to continue.
5. Highlight the box under the following items and press .
 - ▶ **Alarm** to set the alarm **On/Off**. Select **On** and press .
 - ▶ **Time** to enter the alarm time. Enter the desired alarm time and press .
 - ▶ **Repeat** to select the alarm frequency. Select **None** to set your alarm once or **Daily** to set your alarm daily.
6. Press **Done** (left softkey) to save the alarm settings.

Note: The alarm will not sound when the phone is powered off.





To stop the alarm:

- ▶ Press any key to stop the alarm.
- ▶ Press **Exit** (right softkey) to exit the alarm clock display.

Tip: The alarm stops in 30 seconds automatically.




Note: You can adjust the ringer type and ringer volume in your Settings menu. To change the ringer type, see “Selecting Ringer Types for Calendar and Alarm” on page 26. To change the ringer volume, see “Adjusting the Phone’s Volume Settings” on page 28.

Using the Calculator

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Calculator** and press .
4. Enter numbers using your keypad. Press the left softkey to insert a decimal point.
5. Press the appropriate navigation key for an arithmetic option. (Up for addition, Down for subtraction, Left for multiplication, Right for division)
6. Enter numbers and press  for the result.
 - ▶ To clear the numbers, press **CLR** (right softkey).

Using the World Clock




This feature is available only in digital areas.

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **World Clock** and press .
4. The World Clock display appears.
 - ▶ Press the navigation key right or left for changing city or country.

Tip: Press **Summer** (left softkey) or **Standard** (right softkey) for changing between summer and standard time, if applicable. “☀” is shown while summer time is displayed.

Using the Stop Watch


To start the stop watch:

1. Press  to access the main menu.
 2. Highlight **Tools/Extras** and press .
 3. Highlight **Stop Watch** and press .
- ▶ Press **Start** (left softkey) to start the stop watch operation.
 - ▶ Press **Stop** (left softkey) to stop the stop watch operation.
 - ▶ Press **Resume** (left softkey) to start the stop watch operation again.

To record a lap time while the stop watch is running:

- ▶ Press **Lap** (right softkey) to record time of first lap.
- ▶ Press **Lap** (right softkey) again to record next lap. (You may continue this until lap 5.)

To display the stop watch options:


1. During stop watch operation, press **Options** (right softkey).
 2. To select an option, highlight it and press .
- ▶ **Go to Lap List** to display a saved Lap List. Press **Detail** (left softkey) to display the lap list detail.
 - ▶ **Save to Lap List** to save the recorded lap times.
 - ▶ **Reset** to reset the time to zero and clear any recorded lap times.

Downloading through Wireless Web

Your phone allows you to download images (screen savers), ringers, games, etc., from a website. It is also possible to download from certain menus (Contacts list, Ringer Setting, or Display Setting).

1. Press  to access the main menu.
2. Highlight **Downloads** and press .





Shortcut: Instead of steps 1 and 2 above, press the navigation key down.

3. Press **Options** (right softkey) to display options.
4. Highlight **Get New** and press  to start up the browser.
5. Select your desired image or ringer file, and follow the system prompts.

Confirming the Downloaded Data

The downloaded data will be automatically classified as games, ringers, images (screen savers) or an application folder. However, if any data has a different category, it is classified as a Dynamic folder. If data doesn't belong to any of the above categories, it is classified in the Others folder.

To confirm the downloaded games folder:

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight your desired data folder (for example, **Games**, **Ringers**, or **Screen Savers**) and press .
4. Highlight the downloaded data you want to confirm and press .







Tip: The names of dynamic folders are variable depending on data.

Downloaded Data Options

Selecting Download Settings






This feature is available when you select a Java application.

To select the settings for the downloaded data:

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Games** or **Applications** and press .
4. Highlight the data for which you want to select settings and press **Options** (right softkey).
5. Highlight **Settings** and press .
6. Highlight **Network Access** and press .
7. Highlight your desired option and press .






Assigning the Downloaded Data

To assign the downloaded data:

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Ringers** or **Screen Savers** and press .
4. Highlight the data you want to assign and press **Options** (right softkey).
5. Highlight **Set as** and press .
6. Highlight the menu you want to assign and press .





Sorting the downloaded data

The files downloaded via website are stored in alphabetical order. You may store the data in memory size order:

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight each folder that includes the downloaded data you want to sort and press .
4. Press **Options** (right softkey).
5. Highlight **Sort by** and press .
6. Highlight **Name** or **Size** and press .




Viewing the Downloaded Data Size

This feature allows you to confirm each downloaded data size and the rest of the download capacity.





1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight each folder that includes the downloaded data you want to confirm and press .
4. Press **Options** (right softkey).
5. Highlight **Icon/Size** and press . (Data size is displayed at the left of the downloaded data name.)

Viewing the memory space for downloading

This feature allows you to confirm how much memory is left and used for downloading.

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Press **Options** (right softkey).
4. Highlight **View Memory** and press . (Used and Free memory size are displayed.)

Erasing the Downloaded Data

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight a folder and press .
4. Highlight the downloaded data you want to erase and press **Options** (right softkey).
5. Highlight **Erase** and press .
6. Follow the onscreen prompts to erase the data.

Tip: To erase all data, select **Erase All** during step 5 above.

Note: It takes a while when you erase a large amount of downloaded data.

9. Voice Services

Using Voice-Activated Dialing

You can use a Voice Dial tag to automatically dial a phone number in your Contacts list. Your phone can store up to 30 Voice Dial tags. (To create a Voice Dial tag, see “Programming Voice Dial Tag to Your Phone” below.)

With the flip open:

1. Press **TALK** or **SPEAKER** briefly.
2. Follow the voice prompts and recite the entry’s Voice Dial tag into your phone’s microphone.

With the flip closed:

1. Press and hold **CALL**.
2. Follow the system prompts and recite the entry’s Voice Dial tag into your phone’s microphone.

Note: To use this feature, you must have stored entries (see “Programming Voice Dial Tag to Your Phone” below).








Programming Voice Dial Tag to Your Phone

1. Press **MENU OK** to access the main menu.
2. Highlight **Tools/Extras** and press **MENU OK**.
3. Highlight **Voice Services** and press **MENU OK**.
4. Highlight **Voice Dial** and press **MENU OK**.
5. Highlight **Program** and press **MENU OK**.
6. The phone will prompt you to say the name you want to program. Wait for the beep and then say the name.
7. Respond to the prompt by repeating the name after the beep.
8. Highlight the Voice Dial entry (name) in the Contacts list, and press **MENU OK**.

9. Select the phone number you want to program and press .
(The display shows “Voice Dial Recorded”).

Note: Record Voice Dial tags in a quiet environment and without the aid of an accessory.







Reviewing Voice Dialing Tags

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Voice Dial** and press .
5. Highlight **Review** or **Review:Speaker** and press .
6. Highlight the desired entry and press .
– or –
Highlight the desired entry and press **Options** (right softkey).
To select an option, highlight it and press .

Options:

- ▶ **Play** to play the recorded voice dial tag.
- ▶ **Speaker On** to play the recorded voice dial tag in speakerphone mode. (If you are in speakerphone mode, the option will appear as **Speaker Off** to deactivate.)
- ▶ **Erase** to erase the voice dial tag. Select **Yes** to erase and **No** to cancel.

Erasing All Voice Dial Tags






1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Voice Dial** and press .
5. Highlight **Erase All** and press .
6. Highlight **Yes** and press .

Managing Voice Memos

You can use your phone's Voice Services to record brief memos during a call.


Recording Voice Memos

To record a voice memo:






1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Voice Memo** and press .
5. Highlight **Record** and press .
6. Start recording after the beep.

To end the recording of your memo:




- ▶ Press , , or .

Tip: To record in speakerphone mode, press and hold  in standby mode.

To record the other party's voice during a phone call:

1. During a call, press  (right softkey).
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Voice Memo** and press .
5. Highlight **Record** and press .
6. Start recording after the beep.

To end the recording of voice memo:

- ▶ Press  or  while recording.
– or –
Press  and disconnect the call when recording in Use State.

Recording also stops when the other party hangs up the call.

- ▶ Memo recording during a phone call is disabled while you are roaming in analog service areas.

- ▶ When the recording capacity is full, highlight an old memo, press **Erase** (left softkey), highlight **Yes**, and press **MENU OK** to make room for additional memos.

Note: Your phone can store up to 12 memos and the total available recording time is 72 seconds (maximum of 18 seconds per memo).

Tip: Voice Memos are stored with the date and time stamp in reverse chronological order, except when recorded in a no service area.







Reviewing Voice Memos

1. Press **MENU OK** to access the main menu.
2. Highlight **Tools/Extras** and press **MENU OK**.
3. Highlight **Voice Services** and press **MENU OK**.
4. Highlight **Voice Memo** and press **MENU OK**.
5. Highlight **Play** or **Play:Speaker** and press **MENU OK**.
6. Highlight one memo from the list and press **MENU OK**.
– or –
If you want to play all memos continuously, highlight **All** and press **MENU OK**.
7. Press **MENU OK** to stop playing.
 - ▶ You can change the message playing speed by pressing **Slow** (left softkey) or **Fast** (right softkey).
 - ▶ To play the newer/older memo, press the navigation key right or left.




Tip: To set the speakerphone mode on or off, press **Options** (right softkey), highlight **Speaker On/Off**, and press **MENU OK** during step 6 above.

Erasing Voice Memos

To erase all voice memos:

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Voice Memo** and press .
5. Highlight **Erase All** and press .
6. Highlight **Yes** and press .

To erase an individual memo:


1. Follow steps 1-4 above.
2. Highlight **Play** or **Play:Speaker** and press .
3. Display the memo list, highlight the memo you want to erase, and press **Options** (right softkey).
4. Highlight **Erase** and press .
5. Highlight **Yes** and press .

Setting Up Screen Call









This feature enables you to answer incoming calls by using pre-recorded announcements, either one that is pre-recorded or one that you record. You can also record the caller's message into the Voice Memo list. To listen to the message, see "Reviewing Voice Memos" on page 87.






Activating Screen Call

To start Screen Call when you have incoming calls:

1. When the phone rings or vibrates, press **Options** (right softkey) to display the options.
2. Highlight **Screen Call** and press .







To set Auto Screen Call:

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Screen Call** and press .
5. Highlight **Auto** and press .
6. Highlight **On** and press .
- ▶ If you want to change the answer time, enter your desired number (from 1 to 10 seconds) by using numeric keys or the navigation key up or down.
7. Press  or **OK** (left softkey). The  icon is displayed on the Standby display.











Tip: If a new caller's message is waiting,  appears on the display. The memos recorded while activating "Screen Call" are shown with "" or "" icon in the list. ("": once played, "": not played yet)

Tip: While the caller is recording: Pressing  stops recording and disconnects the call. Pressing  answers the call.






Selecting Announcement for Screen Call

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Screen Call** and press .
5. Highlight **Announcement** and press .
6. Depending on your preference, highlight **Pre-Recorded** or **Custom**, and press .







Recording Name for Pre-Recorded Announcement

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Screen Call** and press .
5. Highlight **Announcement** and press .
6. Highlight **Pre-Recorded** and press **Edit** (right softkey).
7. Highlight **Record Name** and press .
- ▶ If your name has already been recorded, select **Yes** or **No** for overwriting.
8. Press  to start the 1st recording. (Press  to stop recording.)
9. After the 1st recording, press  again to start the 2nd recording.
10. To stop recording, wait for 12 seconds or press .




Recording Customized Announcement

1. Follow steps 1-5 on the previous page.
2. Highlight **Custom** and press **Edit** (right softkey).
3. Highlight **Record** and press .
- ▶ If your announcement has already been recorded, select **Yes** or **No** for overwriting.
4. Press  to start the 1st recording. (Press  to stop recording.)
5. After the 1st recording, press  again to start the 2nd recording.
6. To stop recording, wait for 12 seconds or press .


Reviewing an Announcement

1. Press  to access the main menu.
2. Highlight **Tools/Extras** and press .
3. Highlight **Voice Services** and press .
4. Highlight **Screen Call** and press .
5. Highlight **Announcement** and press .
6. Highlight **Pre-Recorded** or **Custom** and press **Edit** (right softkey).
7. Highlight **Play** or **Play:Speaker** and press .






Erasing an Announcement

1. Follow steps 1-6 above.
2. Highlight **Erase Name** to erase name for Pre-Recorded announcement and press .
– or –
Highlight **Erase** to erase message for Custom and press .
3. Highlight **Yes** and press .

10. 10-4

10-4 allows you to enjoy quick, two-way, “walkie-talkie-style” communication with your friends, family, and co-workers. You can make 1-to-1 or 1-to-many calls (up to 5 others on the same call) to any other 10-4 user, anywhere on the Network. You can make and receive 10-4 calls when your phone displays .

Changing 10-4 Mode

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **10-4** and press .
 4. Highlight **Enable/Disable** and press .
 5. Select **Enable** or **Disable** and press .
- ▶ **Enable:** Lets you make or receive 10-4 calls any time your phone is not in use.
 - ▶ **Disable:** Disables your phone’s 10-4 service; you will not be able to make or receive 10-4 calls or access your 10-4 contacts.


10-4 Call Alerts

There are several ways your Phone alerts you during 10-4 calls.


When you make or receive a 10-4 call:

- ▶ The phone beeps (depending on the Ringer Type).
- ▶ The backlight illuminates.
- ▶ The screen displays a 10-4 call message.
- ▶ The other party’s 10-4 number and name (if available) are displayed.
- ▶ The screen displays who has the floor.

The status of a 10-4 call:

- ▶ The LED On indicates you or another contact have the floor.
- ▶ The LED Off indicates the floor is open. (You can take the floor and speak by pressing and holding .)

Displaying the 10-4 List

- ▶ From standby mode, press **10-4** (left softkey) or the 10-4 button on the side of your phone () to access the 10-4 List.


Tip: The first time you access the list, the 10-4 Help message will appear. Press **Yes** (left softkey) and **Next** (left softkey) to read a brief introduction of 10-4.

Selecting Contacts Lists

When your phone displays a 10-4 List, the left softkey is labeled **Go to**. To switch to another contacts list, press the left softkey, highlight your desired list, and press .

- ▶ **Company List/Company Groups** contain company-provided contacts (up to 200 entries). Your company list can only be created and modified by an authorized administrator on the 10-4 server. When the lists are empty, Company List/ Company Groups will not appear on the display. You cannot add, edit, or delete Company List items, but you can copy entries to your Personal List/Personal Groups.
- ▶ **Personal List/Personal Groups** contain your personal 10-4 contact names and numbers, separately or in groups. You can create and edit your own Personal List. Your phone can store a total of 200 entries (you may include up to five contacts per group).
- ▶ **Outgoing** shows the last 10 different 10-4 calls you placed.
- ▶ **Incoming** shows the last 10 different 10-4 calls you accepted.
- ▶ **Missed** shows the last 10 10-4 calls you missed.

Tip: You can also select **Enter 10-4#** from **Go to** option to enter a 10-4 number directly. See page 96 for details.

Note: The  icon next to the group name indicates a group.

Making a 10-4 Call (1-to-1 Call)

You can place a 1-to-1 10-4 call by entering a 10-4 number or by selecting a contact from the 10-4 List.

1. Press **10-4** (left softkey) or press **10-4** to access the 10-4 List.
2. Press **Go to** (left softkey), highlight the list from which you want to place a call (**Company List**, **Personal List**, **Outgoing**, **Incoming**, or **Missed**), and press **MENU**.
3. Highlight the contact you want to call, and press and hold **10-4** to place the call and get the floor. (You will see **10-4 calling...** and **Connecting...** followed by **"You have floor."** You can now begin speaking.)
- or -
Highlight the contact you want to call and press and release **10-4** to place the call. (The call will connect as described above, but **"Floor is open."** will appear on the screen and either you or your contact may press and hold **10-4** to take the floor and speak.)

Note: During a 10-4 call, the **"floor"** is the right to speak. When you see **"Floor is open,"** the first person to press the 10-4 button (**10-4**) can speak (while holding the button). Only the person who has the floor can speak. The phone beeps if you press the 10-4 button when another contact has the floor.

4. Continue holding **10-4** as you speak. When you are finished speaking, release the 10-4 button to allow other contacts to speak. (When the other party takes the floor, you will see the speaker's name and phone number and the text **"has floor."**)
5. When you are finished, press **END/⓪**.

Note: When neither party has the floor during a 10-4 call, **"Floor is open."** appears on the display. If no one takes the floor for 20 seconds, the 10-4 call ends automatically.

Tip: If you press **TALK** or **SPEAKER** during step 3 above, you can make a standard voice call.

Making a 10-4 Call (Group Call)

You can make a 10-4 call to all members in a Group entry, which you have in your 10-4 List. You can communicate with up to five members at a time.

1. Press **10-4** (left softkey) or press **|||||** to access the 10-4 List.
2. Press **Go to** (left softkey), highlight the list from which you want to make a Group call (**Company Groups**, **Personal Groups**, or **Outgoing**), and press **MENU OK**.
3. Highlight the group you want to call, and press and hold **|||||** to place the call and take the floor. (You will see **10-4 calling...** and **Connecting...** followed by “**You have floor.**” Continue with the 10-4 call as described previously.)
 - ▶ To make a 10-4 call to a group member, select your desired group, highlight your desired group member, and press and hold **|||||**.
 - ▶ If one of the group members takes the floor, you will see the member’s name and 10-4 number on the display. The phone beeps if you press the 10-4 button when another contact has the floor.
4. When the call is finished, press **END/⓪**.

Tip: You can also make a Group Call after checking the group member. Press **MENU OK** to display group members, highlight **<Call Group>** and press and hold **|||||** during step 3 above.

Making a 10-4 Call by Entering a Number

1. From standby mode, enter the 10-4 number you want to dial.
2. Press **|||||** to place the 10-4 call.
 - ▶ The contact's name appears if there is a matched number in your 10-4 List.
3. Continue with the 10-4 call, pressing and holding **|||||** to speak and releasing it to allow others to reply.
4. When the call is finished, press **END/⊙**.

- or -

1. Press **10-4** (left softkey) or press **|||||** to access the 10-4 List.
2. Press **Go to** (left softkey), highlight **Enter 10-4#** and press **MENU OK**.
3. Enter the 10-4 number you want to dial.
4. Follow steps 2-4 above.

Missed Call Notification for 10-4 Calls




When an incoming 10-4 Call is not answered, the Missed Call Notification is displayed on your screen.

To call the last Missed 10-4 Call:

- ▶ Simply press and hold **|||||** while the Missed Call Notification is displayed. (Continue with the 10-4 call as described previously.)

To display the Missed 10-4 Call Log:

- ▶ Press **View** (left softkey). To call the entry, highlight the entry you want to call, and press and hold **|||||**. (Continue with the 10-4 call as described previously.)


Note: When you display Missed Calls entries, you will see the  icon next to the name. Once you confirm the entry by pressing **MENU OK**, the icon turns to the  icon. The  icon will remain until you make or receive a 10-4 call to or from the entry.

Receiving a 10-4 Call

1. Make sure your phone's 10-4 mode is enabled (see "Changing 10-4 Mode" on page 92).
2. When you receive a 10-4 call from a contact, "10-4 Call," the contact's name, and the 10-4 number appear on the display.
 - ▶ When you receive a group call, "Group Call" and the 10-4 number appear.
 - ▶ If nobody takes the floor for 20 seconds, the call will be a missed 10-4 call.
3. If the person placing the call has kept the floor (held the 10-4 button), you will see the contact name and 10-4 number along with **"has floor,"** and you will hear the caller speaking.
4. When the caller finishes speaking and releases **10-4**, you will see **"Floor is open."** on the display screen. Press and hold **10-4** to take the floor and reply to the caller. (You will see **"You have floor."** and hear a tone confirming that you may speak.)
5. When the conversation is finished, press **END/⓪**.

Tip: You can also receive a 10-4 call with the flip closed. Press **10-4** and hold to take the floor when the floor is open.

10-4 Options

When you use 10-4, several user options are available by pressing **Options** (right softkey). To select an option, highlight it and press .

- ▶ **Edit** to edit a 10-4 number and/or name. (See page 103.)
- ▶ **Send Text** to send a text message. (See page 112 for details.)
- ▶ **Copy to Personal** to copy a contact to the Personal List.
Copy Group appears when you highlight a group. (This option doesn't appear if the entry is already in the Personal List or when you select Personal List/Personal Groups.)
- ▶ **Copy to Ph. Book** to copy a contact to the Contacts List.
- ▶ **Erase** to erase a contact. **Erase Group** appears when you highlight a group.
- ▶ **Add Contact** to add a new contact. (See page 101 for details.)
Add Group appears when you highlight a group list. (See page 102 for details.)
- ▶ **Find:First Name** to find a contact by first name.
Find:Full Name appears when your phone's setting is "Find:First Name".
- ▶ **Erase 10-4 List** to erase entries saved in the 10-4 List (except Company List/Company Groups).
- ▶ **Help** to see the 10-4 instruction page.


Copying an Entry to Personal List or Personal Group List

You can copy an entry to your Personal List/Personal Groups from several different sources. If the selected entry is already stored in the Personal List/Personal Groups, the “copy” option does not appear.

1. Press **10-4** (left softkey) or press **1000** to access the 10-4 List.
2. Press **Go to** (left softkey), highlight the list from which you want to copy an entry (**Company List**, **Company Groups**, **Outgoing**, **Incoming**, or **Missed**), and press **MENU OK**.
3. Highlight the entry you want to copy (or scroll to highlight the **Redial** entry at the top of your screen) and press **Options** (right softkey). To select an option, highlight it and press **MENU OK**.
 - ▶ **Copy to Personal** to copy the contact to the Personal List.
 - ▶ **Copy Group** to copy the group to the Personal Group List.
 - ▶ **Copy to Ph. Book** to copy the contact to the Contacts list.
4. Press **Yes** (left softkey) to copy and save the entry to your Personal List or Personal Group List.

Saving a 10-4 Number

You can save a 10-4 number from the ending display to your Personal List/Personal Groups.




1. From the ending display, press **Save** (right softkey).
2. Enter a name and press .
3. Press **Save** (left softkey).
4. Press **Yes** (left softkey).

Tip: If the entry already has a name, skip step 2 and 3 above.

Note: If the number is already stored in the Personal List/Personal Groups, the "Save" softkey does not appear.

Finding an Entry in the 10-4 List

You can find your desired entry by entering a few letters.

1. Press **10-4** (left softkey) or press  to access the 10-4 List.
2. Press **Go to** (left softkey), highlight your desired list (**Company List**, **Company Groups**, **Personal List**, or **Personal Groups**), and press .
3. Enter the first letter or the first few letters of the name.
 - ▶ The display shows the list beginning with the letter(s) you entered.
4. Scroll through the list and press  to select your desired entry.

Adding a New Contact to Your Personal List

You can store the total of 200 entries in the Personal List/
Personal Groups.

1. Press **10-4** (left softkey) or press **|||||** to access the 10-4 List.
2. Press **Go to** (left softkey), highlight **Personal List**, and press **MENU OK**.
3. Highlight **<Add Contact>** and press **MENU OK**.
– or –
Highlight an entry and press **Options** (right softkey). Then highlight **Add Contact** and press **MENU OK**.
4. Enter a name for the new contact and press **MENU OK**. (This is the name you will see when calling or receiving a call from the contact.)
5. Highlight the **10-4 Number** field, enter the contact's 10-digit 10-4 number (their phone number) and press **MENU OK**.
6. Press **Save** (left softkey) to save the new contact to your Personal List.



Tip: You are not allowed to use the following symbols during step 4:
:, @, ,, /, *,), and (.

Adding a New Group to Your Personal Group List



You can add new groups to the Personal Group List. Each group can include up to five members. You can enter a group member directly, or select the member from the Company List or Personal List.

1. Press **10-4** (left softkey) or press **||||** to access the 10-4 List.
2. Press **Go to** (left softkey), highlight **Personal Groups**, and press **MENU OK**.
3. Highlight **<Add Group>** and press **MENU OK**.
– or –
Highlight an entry and press **Options** (right softkey). Then highlight **Add Group** and press **MENU OK**.
4. Enter a Group Name, press **MENU OK**, and press **Next** (left softkey).
5. To add contacts to the group, press **Add** (right softkey).
6. Highlight one item from the following and press **MENU OK**:
 - ▶ **New** to add a new contact. See the previous page for details.
 - ▶ **from Company** to add a contact from your Company List (if applicable).
 - ▶ **from Personal** to add a contact from your Personal List.
7. Scroll to select the contacts you want to add and press **MENU OK** or **Pick** (right softkey) to include the entries.
8. Press **Done** (left softkey) when you are finished selecting contacts, then press **Update** (left softkey) to update your Personal Group List with the new group entry.

Editing a Contact in Your Personal List



1. Follow steps 1-2 in “Adding a New Contact to Your Personal List” on page 101.
2. Highlight the entry you want to edit and press **Options** (right softkey).
3. Highlight **Edit** and press .
4. Highlight the field you want to edit (**Name** or **10-4 Number**), and press .
5. Edit the entry, press **OK** (left softkey), and press **Save** (left softkey) to save your changes.

Editing a Group in Your Personal Group List

1. Follow steps 1-2 in “Adding a New Group to Your Personal Group List” on the previous page.
2. Highlight the group entry you want to edit and press **Options** (right softkey).
3. Highlight **Edit** and press .
4. Edit the group name and press  or **OK** (left softkey).
 - If you don't need to edit the group name, press **Next** (left softkey) during step 4 above and skip step 5.
5. Press **Save** (left softkey) to save your changes.
6. To edit a group member, highlight the contact you want to edit and press **Options** (right softkey).




Options:

- ▶ **Edit** to edit a group member's name and phone number.
- ▶ **Erase** to erase the group member.
- ▶ **Add New** to add a new group member in the Personal Group List.
- ▶ **Add (Company)** to add a new group member from the Company List.
- ▶ **Add (Personal)** to add a new group member from the Personal List.
- ▶ **Details** to display a group member's information.





7. Highlight **Edit** and press .
8. Highlight the field you want to edit (**Name** or **10-4 Number**) and press .
9. Edit the entry, press **OK** (left softkey), and press **Save** (left softkey) to save your changes.
10. Press **Update** (left softkey) to update your Personal Group List.

Erasing an Entry in Your Personal List or Personal Group List

To erase a contact or a group:



1. From the 10-4 List, press **Go to** (left softkey), highlight **Personal List** or **Personal Groups**, and press .
2. Highlight the entry you want to erase and press **Options** (right softkey).
3. Highlight **Erase** and press .
- ▶ **Erase Group** appears when you select Personal Groups.
4. Select **Yes** and press .

To erase a group member:

1. From the 10-4 List, press **Go to** (left softkey), highlight **Personal Groups**, and press .
2. Highlight your desired group and press  to display the group members.
3. Highlight the contact you want to erase and press **Options** (right softkey).
4. Highlight **Erase** and press .
5. Select **Yes** and press .
6. Press **Update** (left softkey) to update your Personal Group List.

Erasing a 10-4 List

You can erase all entries saved in the 10-4 List (except Company List/Company Groups).

1. From the 10-4 List, press **Options** (right softkey).
2. Highlight **Erase 10-4 List** and press .
3. Highlight your desired option and press .





Options:

- ▶ **Outgoing** to erase all outgoing 10-4 calls.
- ▶ **Incoming** to erase all incoming 10-4 calls.
- ▶ **Missed** to erase all missed 10-4 calls.
- ▶ **All Calls** to erase all 10-4 call history, except redial.
- ▶ **All Personal Ent.** to erase all entries in Personal List and Personal Groups. You are prompted to enter your 4-digit lock code. (See “Unlocking Your Phone” on page 49.)









4. Select **Yes** and press .

Tip: The Redial number will not be erased.

Updating the Company List and Personal List

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **10-4** and press .
4. Highlight **List Update** and press .

Setting Speed Dialing for 10-4 Entries






1. Press  to access the main menu.
 2. Highlight **Contacts** and press .
 3. Highlight **Speed Dial #s** and press .
 4. Highlight an unassigned number and press .
 5. Press **Go to** (left softkey), highlight the list from which you want to set a speed dial (**Company List**, **Company Groups**, **Personal List**, or **Personal Groups**) and press .
 6. Select the contact and press .
– or –
Select the group and press , select an option, and press .
- ▶ **Set as** to assign the selected group as a speed dial.
 - ▶ **Details** to display the group details. You can select the group member from the group list.

To use Speed Dial for a 10-4 entry:








- ▶ From standby mode, press the appropriate key and press and hold .

Setting 10-4 Guard








This feature enables you to display the warning message when you cannot receive 10-4 calls. The warning message appears when you are launching the Web.

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **10-4** and press .
 4. Highlight **10-4 Guard** and press . (A message will appear.)
 5. Press **OK** (left softkey) to continue.
 6. Select **On** and press .
- ▶ To deactivate this feature, select **Off** during step 6 above.






Setting Ringer Types for 10-4 Calls

1. Press  to access the main menu.
 2. Highlight **Settings** and press .
 3. Highlight **10-4** and press .
 4. Highlight **Sounds** and press .
 5. Highlight **Ringer Type** and press .
 6. Highlight **10-4 Calls**, **10-4 Missed**, or **10-4 Floor Tone** and press .
 7. Highlight your desired ringer type and press .
- To confirm the ringer, press **Play** (right softkey).

Setting an Alert Notification for 10-4 Calls





1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **10-4** and press .
4. Highlight **Sounds** and press .
5. Highlight **Alerts** and press .
6. Highlight **10-4 Calls** or **10-4 Missed** and press .
7. Use the navigation key to select **Once**, **Repeat Alert** for 10-4 or **Once**, **Repeat Alert**, or **Off** for 10-4 Missed.
8. Press  to save the setting.

Setting the Speakerphone for 10-4 Calls






1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **10-4** and press .
4. Highlight **Speakerphone** and press .
5. Select **On** or **Off** and press .

Note: If the phone's ringer volume is set to Vibrate, Ringer off, or Silence All, the speakerphone turns off.

Setting the Default View of the 10-4 List


1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **10-4** and press .
4. Highlight **Default View** and press . (The default setting is Personal List.)
5. Highlight your desired list and press .

Setting the Floor Display of the 10-4 Calls

1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **10-4** and press .
4. Highlight **Floor Display** and press .
5. Highlight **Text Only** or **Text & Image** and press .

11. Messaging

New Messages

When you receive new messages, the message notification and the  icon will appear. Press **View** (left softkey) to display the message details.

- ▶ Press **Call** (left softkey) to dial the phone number. (Appears when a callback number is highlighted.)
- ▶ Press **Reply** (left softkey) to reply the message. (Appears when a phone number or email address is highlighted.)
- ▶ Press **Go** (left softkey) to go to the website. (Appears when a URL is highlighted.)
- ▶ Press **Forward** (left softkey) to forward the message. (Appears only if there are no phone numbers and URLs in the message.)
- ▶ Press **Options** (right softkey) to display options. (See page 114 for details.)

Tip: You may receive a Service Indication (SI) message on your phone. It consists of header information, the text message and an URL, where more information can be retrieved. To display the message details, press **View** (left softkey).



Message Storage

Your phone can store up to 200 received Messages, 180 sent Messages, and 20 Web Alerts. When the message memory is full, the oldest unlocked message will be deleted automatically (see page 116 for locking the message).




Displaying Messages

To display a Message from the message notification alert, see “New Messages” on the previous page.





To display a Message from the main menu:

1. Press  to access the main menu.
2. Highlight **Messaging** and press .

Shortcut: Press the navigation key up to display the Messaging menu.

3. Highlight **Text Msgs** and press . (The folder list appears.)
4. Highlight **Inbox**, **Sent**, **Outbox**, **Drafts**, or your defined folder and press . (The message list appears.)
5. Highlight the header of the message you want to see and press . (The message detail appears.)

To display Web Alerts:






1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **Web Alerts** and press . (The Web Alerts list appears.)
4. Highlight the header of the message you want to see and press . (The Web Alerts detail appears.)

To read other messages:

- ▶ Press the navigation key right to read the next message.
- ▶ Press the navigation key left to read the previous message.

Note: Web Alerts are URLs. When you buy a ringer or image through your computer for your phone, your phone will receive Web Alerts. Press **Go** (left softkey) to go to the website and follow steps to download it to your phone.

Sending a Message

1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **Send Text** and press .
4. Highlight an option from the following and press .
 - ▶ **Phone Book Entry** to select recipients from your Contacts list. Highlight the box next to an entry and press  to select. Or select **<Add Entry>** to enter a new entry. Press **Done** (left softkey) when you are finished selecting/entering recipients.
 - ▶ **Company List Ent.** to select recipients from your Company list (if applicable).
 - ▶ **Personal List Ent.** to select recipients from your Personal list.
 - ▶ **Personal Grp. Ent.** to select recipients from your Personal Group member.
 - ▶ **Mobile Phone#** to enter a mobile phone number directly.
 - ▶ **Email Address** to enter an email address directly.
 - ▶ **From Recent List** to select recipients from a list of recent message recipients.

Tip: If you have unsent messages, you are prompted to send the messages during step 4 above. Press **OK** (left softkey) to go to **Outbox**. Press **Cancel** (right softkey) to create a new message.

Tip: **Company List Ent.**, **Personal List Ent.**, and **Personal Grp. Ent.** options appear only when 10-4 mode is enable. See page 92 for the setting.



5. Press **Next** (left softkey) when you are finished selecting/entering recipients (you may include up to 10 recipients).

Tip: To add recipients, press **Options** (right softkey) and select **Add Recipient** during step 5 above.

6. To enter a message, select the box under Message and press .



7. Use your keypad to enter a text message (or press the right softkey to select from **Canned Messages**, **Recent Messages**, or **Signature**) and press **OK** (left softkey).

Tip: See page 43 for **Canned Messages**.

8. To set the message priority, select the box under Priority and press .
9. Highlight **Normal** or **Urgent** and press .
10. Press **Send** (left softkey) to send the message.

To change the recipients or to save the message as a draft, press **Options** (right softkey) and select **Chg Recipients** or **Save to Drafts** during steps 6-9 on the previous page.


- ▶ **Chg Recipients** to change Recipients.
- ▶ **Send Callback#** to select from **None**, **My Phone#**, or **Other** to notify your recipients of your callback number. (See “Setting Your Callback Number” on page 44.)
- ▶ **Save to Drafts** to save the message to a Drafts folder. (See below to edit and send the draft message.)

Note: If there is a failure when sending a message in no-service area, you are prompted to select to send the message automatically. Press **Yes** (left softkey), and the message goes to the Outbox folder with . If you press **No** (right softkey), the message goes to the folder with .

Message Options


Several options are available when you display a folder list, message list, or message details.


Folder List Options


Highlight **Inbox**, **Sent**, **Outbox**, **Drafts**, or your defined folder and press **Options** (right softkey). To select an option, highlight it and press .


- ▶ **Edit Folder** to edit the folder (your defined folder only).
- ▶ **Erase Folder** to erase the folder (your defined folder only).
- ▶ **Create Folder** to create a new your defined folder.
- ▶ **Compose New** to compose a new message.
- ▶ **Erase Messages** to erase messages (if applicable).


Message List Options

To display message list options, highlight **Inbox** (or defined folder), **Sent**, **Outbox**, or **Drafts** and press . Then press **Options** (right softkey).



- ▶ **Reply** to reply to the message. (Inbox only.)
- ▶ **Forward** to forward the message. (Inbox, your defined folder, and Sent only.)
- ▶ **Edit** to edit a message. (Outbox and Drafts only.)
- ▶ **Send** to send a message. (Outbox and Drafts only.)
- ▶ **Move** to move a message to the Inbox or to your defined folder. Select a folder and press , or press **<Add Folder>** to create a new folder. (Inbox and your defined folder only.)






- ▶ **Lock** to lock a message. Locked messages will not be erased automatically. To unlock the message, select **Unlock** and press . (Inbox and Sent only.)
- ▶ **Compose New** to compose a new message.
- ▶ **Sort by** to sort the message. (Inbox, your defined folder, and Sent only.)
- ▶ **Erase** to erase the selected message.
- ▶ **Erase Read Msgs** to erase read messages in the folder (except locked messages). (Inbox and your defined folder only.)
- ▶ **Erase All** to erase all messages in the folder (except locked messages). A warning message appears if there are unread messages.

Tip: You can lock up to 40 messages. Locked messages will be displayed with .

Tip: To make a call from the list, highlight a message and press  (if applicable).

Messages Details Options

After you display the Message list in Inbox, Sent, or your defined folder, press  to display the message details. Press **Options** (right softkey) to display message options. To select an option, highlight it and press .

- ▶ **Call(Go to List)** to call a number in the message. Select a number and press  or **Call** (left softkey) to make a call.
- ▶ **Call:Speaker On** to call in speakerphone mode. Select a number and  or **Call** (left softkey) to place a call.
- ▶ **Prepend** to add numbers to the beginning of the phone number (if applicable).
- ▶ **Go to URL List** to display URLs in the message.
- ▶ **Send Text** to display phone numbers and email addresses to send a message.
- ▶ **Reply** to reply to the message. (Message in Inbox and defined folder only.)
- ▶ **Forward** to forward the message.
- ▶ **Move** to move the message to another folder. Select a folder and press  or press **<Add Folder>** to create a new folder. (Message in Inbox and defined folder only.)
- ▶ **Lock** to lock the message. Locked messages will not be erased automatically. To unlock the message, select **Unlock** and press .
- ▶ **Font Size** to change the font size.
- ▶ **Save to Ph. Book** to save the phone number, email address and URLs. Select a data category and press  to save.
- ▶ **Go to Phone Book** to go to the Contacts list (if applicable).
- ▶ **Copy to Personal** to copy the phone number to the 10-4 Personal List (if applicable).
- ▶ **Compose New** to compose a new message.
- ▶ **Erase** to erase the message.

Changing the Display Font Size of a Message

After you display a Message in the Inbox, Sent, or your defined folder, press **Options** (right softkey) to display message options.

1. Highlight **Font Size** and press **MENU OK**.
2. Highlight **Small** or **Normal** and press **MENU OK**.

Prepending a Phone Number From a Message










After you display a Message in the Inbox, Sent, or your defined folder, press **Options** (right softkey) to display message options.

1. Highlight **Prepend** and press **MENU OK**.
2. Select your desired phone number and press **OK** (left softkey).
3. Enter the digits or pauses you want to add to the number.
4. Press **TALK** or **SPEAKER** to make a call.


Creating Folders for Messages

You can create up to ten folders to store your Messages. When 10 your defined folders exist, the “Create Folder” option will not appear.

To create a new folder:



1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **Text Msgs** and press .
4. Press **Options** (right softkey).
5. Highlight **Create Folder** and press .
6. Enter a folder name and press  or **OK** (left softkey).
 - ▶ Pressing **Save** (left softkey) allows you to save the folder name.
7. If you want the message to be filed into the folder automatically, highlight **Auto Filing** and press .
8. Highlight **On** and press .
9. Highlight the box under **Keyword** by scrolling down and press .
10. Enter a keyword and press  or **OK** (left softkey).
11. Press **Save** (left softkey).

To set an optional feature for the added folder:




1. During step 9 above, scroll down to select other menu options. Highlight each item and press .
 - ▶ **Notify** to set the display notification to on or off when you have unread message matching the defined folder.
 - ▶ **Envelope Icon** to set the envelope icon display to on or off when you have unread message matching the defined folder.
2. After selecting each setting, press **Save** (left softkey).

Moving a Message Into Another Folder







After you display a message, press **Options** (right softkey) to display message options. You need at least one defined folder. (Inbox or your defined folder only.)

1. Highlight **Move** and press .
2. Highlight your desired folder and press .

Editing Folders



1. From the folder list display, highlight a defined folder.
2. Press **Options** (right softkey).
3. Highlight **Edit Folder** and press .
4. Highlight the box under your desired option and press .
5. Enter or select a new folder name/setting.
6. Press  or **OK** (left softkey).
7. Press **Save** (left softkey).

Erasing Messages

1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **Text Msgs** and press .
4. Highlight **Inbox**, **Sent**, **Outbox**, **Drafts**, or your defined folder and press .
5. Press **Options** (right softkey).
6. Highlight **Erase** and press . (A confirmation will display.)
7. Highlight **Yes** and press .




Tip: To erase all messages, select **Erase All** during step 6 above.

Erasing a Folder

1. From the folder list display, highlight the defined folder you want to erase.
2. Press **Options** (right softkey).
3. Highlight **Erase Folder** and press .
4. Highlight **Yes** and press .

Note: When you erase a folder, the messages within the folder are also erased. If the folder contains a new (unread) message or locked message, you are prompted to select **Erase** or **Don't Erase**.

Erasing Selected Messages in All Folders


1. From the folder list display, press **Options** (right softkey).
2. Highlight **Erase Messages** and press .
3. Select **Read**, **Unread**, and/or **Sent** and press  to check the appropriate box(es).
4. After selecting the boxes, press **Done** (left softkey).
5. Highlight **Erase** and press  to erase selected messages (except locked messages).


Web Alerts Options

Several options are also available for Web Alerts.



Web Alerts List Options


From Messaging display, highlight **Web Alerts**, press  and press **Options** (right softkey). To select an option, highlight it and press .

- ▶ **Lock** to lock a message. Locked messages will not be erased automatically. To unlock the messages, select **Unlock** and press .
- ▶ **Erase** to erase the messages.
- ▶ **Erase Read Msgs** to erase read messages in the folder (except locked messages).
- ▶ **Erase All** to erase all messages in the folder (except locked messages). A warning message appears if there are unread messages.

Tip: You can lock up to 10 messages. Locked messages will be displayed with .

Web Alerts Details Options

After you display the Web Alerts list, press  to display the Web Alerts details. Press **Options** (right softkey) to display Web Alerts options. To select an option, highlight it and press .

- ▶ **Go to URL** to go to the website.
- ▶ **Lock** to lock a message. Locked messages will not be erased automatically. To unlock the messages, select **Unlock** and press .
- ▶ **Font Size** to change the font size from **Small** or **Normal**.
- ▶ **Erase** to erase the message.


12. Service Features

Using Voicemail





All unanswered calls to your phone are automatically transferred to voicemail, even if your phone is in use or turned off.

VoiceMail Notification


There are several ways your phone alerts you to new voicemail messages:

- ▶ By displaying a message on the screen.
- ▶ By playing the assigned ringer type.
- ▶ By blinking the LED.
- ▶ By displaying  at the top of your screen.





Displaying Voicemail Details

1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **VoiceMail** and press .
4. Highlight **Details** and press .

Retrieving Your Voicemail Messages






- ▶ Press and hold . (Your phone will dial your voicemail box.)

– or –

1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **VoiceMail** and press .
4. Highlight **Call VoiceMail** and press .






Note: You are charged for airtime minutes when you are accessing your voicemail from your Phone.

Clearing the Message Icon

1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **Vicemail** and press .
4. Highlight **Clear Count** and press .
5. Highlight **Yes** and press .

Editing Your Voicemail Number

To edit your voicemail number:

1. Press  to access the main menu.
2. Highlight **Messaging** and press .
3. Highlight **Vicemail** and press .
4. Highlight **Edit Voicemail#** and press .
5. Edit your voicemail number and press .

To reset your voicemail number:

1. Follow steps 1-4 above.
2. Press **Options** (right softkey).
3. Highlight **Reset Voicemail#** and press .
4. Highlight **Yes** and press .

Responding to Call Waiting

When you're on a call, Call Waiting alerts you to incoming calls by sounding beeps. Your phone's screen informs you that another call is coming in and displays the caller's phone number (if it is available and you are in digital mode).

To respond to an incoming call while you're on a call:

- ▶ Press **TALK** (or press **Options** [right softkey], highlight **Flash** and press **MENU OK**). This puts the first caller on hold and answers the second call.

To respond to an incoming call when Answer on Hold is activated:

- ▶ Press **TALK** (or press **Options** [right softkey], highlight **Flash**, and press **MENU OK**). (The Answer on Hold will be automatically deactivated. See page 13 for Answer on Hold.)

To switch back to the first caller:

- ▶ Press **TALK** (or press **Options** [right softkey], highlight **Flash** and press **MENU OK**) again.

Note: Call Waiting may not be available while roaming off the home network.

Making a Three-Way Call

With Three-Way Calling, you can talk to two people at the same time. When using this feature, the normal airtime rates will be charged for each of the two calls.



1. Enter a number you wish to call and press **TALK** or **SPEAKER**.
2. Once you have established the connection, press **TALK** (or press **Options** [right softkey], highlight **Three-Way Call** and press **MENU OK**) to put the first caller on hold.
3. Enter the second number you wish to call and press **TALK** (or press **Options** [right softkey], highlight **Call** or **Call:Speaker On** and press **MENU OK**).
4. When you're connected to the second party, press **TALK** again (or press **Options** [right softkey], highlight **Flash** and press **MENU OK**) to begin your three-way call.

If one of the people you called hangs up during your call, you and the remaining caller stay connected. If you initiated the call and are the first to hang up, all three callers are disconnected.

Web






With Web on your phone, you will be able to browse full-color graphic versions – not just text versions – of your favorite website, making it easier than ever to stay informed while on the go. Check sports scores, trade stocks, and shop all on your phone.

Launching the Web

1. Press  to access the main menu.
2. Highlight **Web** and press .

Net Guard

With the Net Guard setting, the confirmation display will appear to connect to the Internet. This feature helps you avoid accidental connections. You can disable the Net Guard in the future by selecting **Always Auto-Connect** when the Net Guard is displayed.



1. Press  to access the main menu.
2. Highlight **Settings** and press .
3. Highlight **Internet** and press .
4. Highlight **Net Guard** and press .
5. Select **On** or **Off** and press .
 - ▶ **On** to make the Net Guard appear when connecting to the Internet.
 - ▶ **Off** to avoid the Net Guard when connecting to the Internet.

Note: When enabled, the Net Guard appears only once per session. The Net Guard does not appear if the phone is merely re-connecting due to a time-out.

Browsing the Web



Creating a Bookmark

Bookmarks allow you to store the address of your favorite websites for easy access at a later time.



1. Launch the Web page you want to mark.
2. Press  (right softkey) to go to the browser menu.
3. Highlight **Mark this page** and press  or **OK** (left softkey).

Note: Bookmarking a page does not store the page contents, just its address. Some pages cannot be bookmarked. Whether a particular Web page may be marked is controlled by its creator.


Accessing a Bookmark

1. Access the browser menu by pressing  (right softkey).
2. Highlight **View Bookmarks** and press **OK** (left softkey).
3. Highlight the bookmark you'd like to access and press  or **OK** (left softkey) to go to the website.

Editing a Bookmark


1. Launch the Web and press  (right softkey) to access the browser menu.
2. Highlight **View Bookmarks** and press **OK** (left softkey).
3. Select the bookmark you wish to edit and press  (right softkey).
4. Select **Edit Address** or **Edit Title** and press **OK** (left softkey).
5. Press **Edit** (right softkey), use your keypad to edit the address or title, and press **OK** (left softkey).
6. To save the bookmark, press **OK** (left softkey).

Deleting a Bookmark





1. Access **View Bookmarks** menu as outlined on the previous page in steps 1-2.
2. Highlight the bookmark you wish to erase and press  (right softkey).
3. Highlight **Delete** and press **OK** (left softkey).
4. Press **Yes** (right softkey).

Tip: To delete all bookmarks, select **Delete All** during step 3 above.

Moving a Bookmark



1. Access the **View Bookmarks** menu as outlined in steps 1-2 on the previous page, and press  (right softkey).
2. Highlight **Reorder** and press **OK** (left softkey).
3. Highlight the bookmark you wish to move and press **Move** (left softkey).
4. Move the bookmark to a new location by pressing the navigation key up or down and press **Drop** (left softkey).
5. When you're finished, press **Finish** (right softkey).

Going to a Specific Website

1. Launch the Web and press  (right softkey) to display the browser menu.
2. Highlight **Go to URL...** and press  (left softkey).
3. Highlight **Address** and press  (left softkey).
4. Use your keypad to enter the URL of the website you wish to go to, and press  (left softkey).




Note: Not all websites are viewable on your phone.

Reloading a Web Page

1. Launch the Web and press  (right softkey) to display the browser menu.
2. Highlight **Refresh this page** and press  (left softkey).




Restarting the Web Browser

If the Web browser appears to be malfunctioning or stops responding, you can usually fix the problem by simply restarting the browser.






1. From an active Internet connection, press  (right softkey) to display the browser menu.
2. Highlight **More...** and press  (left softkey).
3. Highlight **Restart Browser** and press  (left softkey).

Sending a Web Page






This feature allows you to send a URL (website address) you're viewing through SMS text messaging.

1. Launch the Web and press  (right softkey) to display the browser menu.
2. Highlight **More...** and press  (left softkey).
3. Highlight **Send Page** and press  (left softkey).
4. To complete and send a Web Page, follow steps 4-11 in "Sending a Message" on page 112.

Adjusting the Browser Sound Volume





1. Launch the Web and press  (right softkey) to display the browser menu.
2. Highlight **More...** and press  (left softkey).
3. Highlight **Preferences** and press  (left softkey).
4. Highlight **Sound Volume** and press  (left softkey).
5. Highlight your desired volume level by pressing the navigation key up or down and press .

Selecting Your Preference Settings

1. Launch the Web and press  (right softkey) to display the browser menu.
2. Highlight **More...** and press  (left softkey).
3. Highlight **Preferences** and press  (left softkey).
4. Highlight the setting you want to change and press  (left softkey).
5. Select your preference setting and press .






Games

Downloading Games

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Games** and press .
4. Highlight **Get New** and press . The browser will launch and take you to the Games download menu.
5. Use your navigation key to highlight and select a game you wish to download.
6. Follow the system prompts to download.





Note: You may store a limited number of downloaded data on your phone, depending on the file sizes.

Playing Games

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Games** and press .
4. Select the game you wish to play and press .
5. Press the left softkey if a prompt displays the days remaining on the game license.
6. Follow the onscreen instructions to play the game. When you are finished, press .
7. A prompt will display: "Resume the Application?" Select **Yes** to continue playing or **No** to exit.

Ringers








Downloading Ringers

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Ringers** and press .
4. Highlight **Get New** and press . The browser will launch and take you to the Ringers download menu.
5. Use your navigation key to highlight and select a ringer you wish to download.
6. Follow the system prompts to download.

Note: You may store a limited number of downloaded data on your phone, depending on the file sizes.

Assigning Downloaded Ringers

Downloaded ringers may be assigned directly from the Downloads menu and are also available through the Settings menu.





1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Ringers** and press .
4. Highlight a downloaded ringer and press **Options** (right softkey).
5. Highlight **Set as** and press .
6. Highlight **Voice Calls**, **Voicemail**, **Messaging**, **Calender/Alarm**, **Start-up Tone**, **Power-off Tone**, or **Phone Book**, **10-4 Calls**, and press . The following two items require an extra step:
 - ▶ **Voice Calls**: highlight **With Caller ID** or **No Caller ID**, and press .
 - ▶ **Phone Book**: highlight your desired entry and press .

(A message appears confirming the data has been assigned.)

To assign a downloaded ringer through the Settings menu, see “Selecting Ringer Types for Voice Calls” on page 25, “Selecting Ringer Types for Voicemail” on page 26, “Selecting Ringer Types for Messages” on page 26, “Selecting Ringer Types for Calendar and Alarm” on page 26, “Setting a Start-up/Power-off Tone” on page 27 or “Selecting a Ringer/Image Type for an Entry” on page 65.

Screen Savers







Downloading Screen Savers (Images)

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Screen Savers** and press .
4. Highlight **Get New** and press . The browser will launch and take you to the Screen Savers download menu.
5. Use your navigation key to highlight and select a Screen Saver you wish to download.
6. Follow the system prompts to download.

Note: You may store a limited number of downloaded data on your phone, depending on the file sizes.

Assigning Downloaded Screen Savers (Images)

Downloaded Screen Savers may be assigned directly from the Downloads menu and are also available through the Settings menu.

1. Press  to access the main menu.
2. Highlight **Downloads** and press .
3. Highlight **Screen Savers** and press .
4. Highlight a downloaded Screen Saver and press **Options** (right softkey).
5. Select **Set as** and press .
6. Highlight one of **Incoming Calls**, **Screen Saver**, or **Phone Book**, and press . The following item needs an extra step:
 - ▶ **Phone Book**: highlight your desired entry and press .

(A message appears confirming the data has been assigned.)

Note: Depending on the data, you can select where to assign the data:
Image data: **Incoming Calls**, **Screen Saver**, or **Phone Book**.
Animation data: **Standby**, **Outgoing Calls**, or **Service Search**.

Note: You may assign a Screen Saver to more than one task.

To assign a downloaded Screen Saver through the Settings menu, see “Changing the Display Screen” on page 32, “Changing the Display for Incoming Calls” on page 32, “Changing the Screen Saver” on page 34 or “Selecting a Ringer/Image Type for an Entry” on page 65.

13. Safety Guidelines

Maintaining Your Phone's Peak Performance

- ▶ Try not to hold, bend, or twist the phone's antenna.
- ▶ Don't use the phone if the antenna is damaged.
- ▶ Avoid exposing your phone and accessories to rain or liquid spills. If your phone does get wet, turn the power off and immediately remove the battery.

Using Your Phone While Driving

Talking on your phone while driving (or operating the phone without a hands-free device) is prohibited in some jurisdictions. Laws vary as to specific restrictions.

- ▶ Let the person you are speaking to know you are driving; if necessary, suspend the call in heavy traffic or hazardous weather conditions.
- ▶ Do not take notes or look up phone numbers while driving.

Following Safety Guidelines

To operate your phone safely and efficiently, always follow any special regulations in a given area. Turn your phone off in areas where use is forbidden or when it may cause interference or danger.

Using Your Phone Near Other Electronic Devices

Most modern electronic equipment is shielded from radiofrequency (RF) signals. However, RF signals from wireless phones may affect inadequately shielded electronic equipment.

RF signals may affect improperly installed or inadequately shielded electronic operating systems and/or entertainment systems in motor vehicles. Check with the manufacturer or their representative to determine if these systems are adequately shielded from external RF signals. Also check with the manufacturer regarding any equipment that has been added to your vehicle.

Consult the manufacturer of any personal medical devices, such as pacemakers and hearing aids, to determine if they are adequately shielded from external RF signals.

Note: Always turn off the phone in health care facilities and request permission before using the phone near medical equipment.

Turning Off Your Phone Before Flying

Turn off your phone or set your phone to Airplane mode before boarding any aircraft. To prevent possible interference with aircraft systems, Transport Canada regulations require you to have permission from a crew member to use your phone while the plane is on the ground.

Turning Off Your Phone in Dangerous Areas

To avoid interfering with blasting operations, turn your phone off when in a blasting area or in other areas with signs indicating two-way radios should be turned off. Construction crews often use remote-control RF devices to set off explosives.

Turn your phone off when you're in any area that has a potentially explosive atmosphere. Although it's rare, your phone and accessories could generate sparks. Sparks can cause an explosion or fire, resulting in bodily injury or even death. These areas are often, but not always, clearly marked. They include:

- ▶ Any area where it is very humid and with inflammables.
- ▶ Fueling areas such as gas stations.
- ▶ Below deck on boats.
- ▶ Fuel or chemical transfer or storage facilities.
- ▶ Areas where the air contains chemicals or particles such as grain, dust, or metal powders.
- ▶ Any other area where you would normally be advised to turn off your vehicle's engine.

Note: Never transport or store flammable gas, liquid or explosives in the compartment of your vehicle that contains your phone or accessories.

Restricting Children's Access to Your Phone

Your phone is not a toy. Do not allow children to play with it as they could hurt themselves and others, damage the phone or make calls that increase your telephone bill.

Protecting Your Battery

The guidelines listed below help you get the most out of your battery's performance.

- ▶ Use only approved batteries, AC adapters, and chargers. These chargers are designed to maximize battery life. Using other batteries or chargers voids your warranty and may cause damage.
- ▶ In order to avoid damage, charge the battery only in temperatures that range from 0° C to 45° C (32° F to 113° F).
- ▶ Don't store the battery in a high humidity environment.
- ▶ Don't use the battery charger in direct sunlight or in high humidity areas, such as the bathroom.
- ▶ Never dispose of the battery by incineration.
- ▶ Keep the metal contacts on top of the battery clean.
- ▶ Don't attempt to disassemble or short-circuit the battery.
- ▶ Don't store the battery in high temperature areas for long periods of time. It's best to follow these storage rules:

Less than one month:

-20° C to 60° C (-4° F to 140° F)

More than one month:

-20° C to 45° C (-4° F to 113° F)

Disposal of Lithium Ion (Li-Ion) Batteries

For safe disposal options of your Li-Ion batteries, please ensure that disposal of this in accordance with law and regulation.

- ▶ Do not dispose of the battery in fire; the cell may explode.
- ▶ Do not open or puncture the battery; the released electrolyte is corrosive and may cause damage to the eyes and skin.

Special Note: Be sure to dispose of your battery properly. In some areas, the disposal of batteries in household or business trash may be prohibited.

Note: For safety, do not handle a damaged or leaking Li-Ion battery.

Cautions

Any changes or modifications to your phone not expressly approved in this document could void your warranty for this equipment and void your authority to operate this equipment. Only use approved batteries, antennas and chargers. The use of any unauthorized accessories may be dangerous and void the phone warranty if said accessories cause damage or a defect to the phone.

Although your phone is quite sturdy, it is a complex piece of equipment and can be broken. Avoid dropping, hitting, bending or sitting on it.

NetFront is the trademark or registered trademark of ACCESS Co., Ltd. in Japan and in all other countries.
Copyright (c) 1996-2005 ACCESS Co., Ltd.

This mobile telephone uses JBlend™ of Aplix Corporation. JBlend and Aplix are registered trade marks of Aplix Corporation in Japan and similar applications have been filed in other countries.

Index

A

- Airplane Mode 38
- Alarm Clock 76
- Alert Notification 29
- Answering Calls 11
- Answer on Hold 13
- Any Key Answer 40
- Auto Answer 40

B

- Backlight Time Length 31
- Battery
 - Charging 7
 - Installing 6
 - Removing 6

C

- Calculator 77
- Calendar 67
- Call Alarm 70
- Call History
 - Erasing 58
 - Making a Call 57
 - Options 56
 - Prepend 58
 - Saving 57
- Call Waiting 124
- Callback Number 44
- Calling in Lock Mode 49
- Canned Messages 43
- Contacts
 - Adding 59
 - Editing 64
 - Erasing 64
 - Finding 60
 - Options 62
 - Secret 66

D

- Dialing
 - Contacts 20
 - Numbers With Pauses 19
 - Options 10
 - Speed Dialing 21, 63, 107
 - Voice-Activated Dialing 84
- Display Settings
 - Background 34
 - Backlight Time Length 31
 - Contrast 35
 - Display Screen 32
 - Font Size 35
 - Greeting 31
 - Incoming Calls 32
 - Screen Saver 34
 - Standby Mode 33
- Downloading
 - Data Size 82
 - Erasing 83
 - Viewing Memory 83

E

- Emergency Calling 16
- End-of-Call Options 18

F

- Font Size 35, 117

G

- Games 131
- Greeting 31

H

- Hard Pause 19
- Headset Mode 41

I

- Icon indication 4
- In-Call Options 17
- Input Mode 22

K

Key Press Echo 47

L

Language 45

Limit Use 50

Location Settings 36

Lock Code 49

Locking Phone 48

M

Making 10-4 Calls 94

Making Calls 8

Menu Diagram 54

Message Notification 42

Messaging

 Displaying 111

 Erasing 119

 Folder

 Creating 118

 Editing 119

 Erasing 120

 Font Size 117

 Moving a Message 119

 Options 114

 Prepend 117

 Sending 112

 Storage 110

Missed Call Notification 15, 96

Muting 15

My Shortcut 39

N

Net Guard 126

O

Open/Close Flip options 46

P

Phone Number

 Dialing With Pauses 19

 Displaying 8

 Finding 19

 Saving 18

Power-off Tone 27

Prepend Dialing 58

Push Options 42

Q

Quiet Ringer 12

R

Resetting Phone 51

Ringer

 Assigning 132

 Downloading 132

 Tone Length 27

 Volume 14

Roaming

 Analog Networks 52

 Digital Networks 52

 Setting 53

S

- Safety Guidelines 135
- Scheduler
 - Calendar 67
 - Call Alarm 70
 - Erasing 72, 74, 75
 - Event 68
 - Memory 74
 - Setting Holidays 67
 - To Do 73
- Screen Call
 - Activating 89
 - Customize 91
 - Pre-Record 90
 - Selecting Announcement 90
- Screen Savers 133
- Secret Mode 66
- Security Menu
 - Accessing 48
 - Changing the Lock Code 49
 - Locking Phone 48
 - Unlocking Phone 49
- Side Key Guard 47
- Signature 45
- Silence All 30
- Sleep Mode 42
- Sound Settings
 - Alert Notification 29
 - Silence All 30
 - Start-up/Power-off Tone 27
 - Tone Length 27
 - Voice Prompt 27
 - Volume Settings 28
- Speakerphone 14
- Special Number 50
- Speed Dialing 21, 107
- Start-up Tone 27
- Stop Watch 78

T

- 10-4
 - 10-4 Guard 107
- Adding 101
- Changing the Mode 92
- Contacts List 93
- Copying 99
- Editing 103
- Erasing 105, 106
- Finding 100
- Making Calls
 - by Entering Number 96
 - Contact 94
 - Group 95
 - Options 98
- Receiving 97
- Saving 100
- Updating 106
- T9 Text Input 23
- Three-Way Call 125
- Tone Length 27
- TTY 37
- Turbo Button 41
- Turning On and Off 5
- 2-Second Pause 19

U

- Unlocking Phone 49
- Unmute 15

V

Version 76

Voice Dial

- Erasing 85

- Programming 84

- Reviewing 85

- Using 84

Voice Prompt 27

Voicemail

- Clearing Message Icon 123

- Editing Number 123

- Notification 122

- Retrieving 122

Voice Memo 86

Volume Settings

- During a Conversation 15

- Muting 15

- Ringer 14

W

Web

- Browsing 127

- Launching 126

- Net Guard 126

Web Alerts 121

World Clock 77